

SMSQ/E

QDOS Compatible Operating System for the Atari ST/STE/TT Gold Card Family

Aurora

QXL

Q40

QPC

Manual Revision 1.04

Important - please read this first!

SMSQ/E

How to use this manual

This manual consists of up to five different sections, depending on which version(s) of SMSQ/E you own.

SMSQ/E

The first section applies to all versions of SMSQ/E: for the GoldCard and SuperGoldCard, Aurora card, the ATARI versions, QXL and QXL 2 and also for QPC. It describes all the new features compared to ordinary QDOS or QDOS with Toolkit II and other extensions. You can skip this section and look at it later, if you prefer to get SMSQ/E first. All features explained in here will work in the various versions for the various systems.

Both the sources and compiled binaries of SMSQ/E for the various platforms may be downloaded from the SMSQ/E Registrar's website at <http://www.wlenerz.com/smsqe/>

Now that SMSQ/E has been in existence for a while we have been able to compile a 'Troubleshooter Guide' at the end of this section. This should explain some of the more common problems encountered by users. It should also tell you why things may not look how you expect them to and give hints on how to make changes to the display. Please read through this section before contacting your supplier about any problems you may experience. There is a separate QPC 'Troubleshooting Guide' at the end of the QPC section of the manual.

SMSQ/E for the GoldCard and SuperGoldCard

Go to this section if you are using SMSQ/E on a GoldCard or SuperGoldCard. It explains how to add it to your normal BOOT file and all of the special features that are specific to this hardware. If you want to get it going instantly from a floppy disk copy, put the disk into FLP1_ and type

EXEC flp1_SMSQ_GOLD

Or if Toolkit 2 is active:

LRESPR flp1_SMSQ_GOLD

Note that if you use the version available from the SMSQ/E Registrar's website, the filename is now GoldCard.bin.

SMSQ/E for the Aurora

The version of SMSQ/E for the Aurora card supports a 256 colour (8-bit) graphics mode where the Aurora card is used with a Super Gold Card. The standard Gold Card version of SMSQ/E may also be used, although this would not support the 256 colour modes. The loading procedure is the same as for the Gold Card version, except that the filename is AURORA.BIN if you use the binaries downloaded from the SMSQ/E Registrar's website.

SMSQ/E for the ATARI

To start SMSQ/E on the ATARI, insert the floppy disk and reset your system. You can also copy the file SMSQ.PRG into an AUTO-folder on your harddisk (your ATARI harddisk driver manual will explain how to do this). The original SMSQ/E ATARI floppy disk has a special root sector which will make sure that, when the floppy disk is inserted, it boots with the highest priority. This section describes all of the extra features that are available on the ATARI-version.

SMSQ/E for QXL and QXL 2

Go to this section to see how to start SMSQ/E on the QXL. The method of doing this is the same as that used by the original SMSQ which was shipped with the board and the extra features which are now available are all described in this section.

SMSQ/E for QPC1

VERY IMPORTANT: QPC needs to be installed on your PC, or it requires you to prepare a special DOS BOOT disk which boots up your PC with modified versions of the files CONFIG.SYS and AUTOEXEC.BAT. It is very important to read this section first and carefully follow the instructions how to install QPC on DOS or WINDOWS95. If you run into problems, make sure you do exactly what is written there and please check the special QPC troubleshooter at the end of the QPC section too. Please note that as QPC1 is no longer developed, only a subset of the commands described in this manual may be available.

SMSQ/E for QPC2

Double-click the QPC2-SETUP program - just follow the on-screen installation step by step - it is very easy!

You can switch between other Windows applications and QPC2 by holding the ALT key, then press TAB.

SMSQ/E for Q40

SMSQ/E is supplied as a file called Q40.rom for the Q40.

SMSQ/E Display

One of the many advantages of using SMSQ/E on the ATARI, AURORA, QXL and QPC is the control that it gives over the display. Many users who are new to this system have been puzzled by the way that SMSQ/E, when used at display sizes higher than the standard QL size of 512 x 256, appears in the top left hand corner of the screen. They assume that this is the extent of the screen which is now available to them. The reason for this is that SMSQ/E is displaying a standard three window QL display and the sizes given to these windows are the same as those on a standard QL. If you have set a display size of 800 x 600 these windows will leave 288 pixels free in the horizontal plane and 344 pixels free in the vertical plane. This area of the

screen is not unavailable - it is available to any of the modern Pointer driven programs and other programs such as Text 87, Master Spy (v 3.03) and any other program that allows you to resize its windows.

If you want to open up the standard three window display to fill the available screen area you should change your normal boot file to use different parameters in the WINDOW commands. Full descriptions of these commands can be found in the QL User Guide, Jan Jones' excellent SuperBasic book or the Hyper Help system supplied by Jochen Merz.

As a rough guide you can multiply the parameters in line with the screen size used in the following way :

	Standard QL Display 512 x 256	New Display 640 x 480	New Display 1024 x 512
window #0	512,42,0,214	640,79,0,401	1024,84,0,428
window #1	256,140,256,60	320,263,320,113	512,280,512,120
window #2	256,140,0,60	320,263,0,113	512,280,0,120

Once you have calculated your windows you can add the following lines to your boot file (assuming a 640x480 display):

```
100 WINDOW#0,640,79,0,40  
110 WINDOW#1,320,263,320,113  
120 WINDOW#2,320,263,0,113
```

You can adjust the sizes as you wish but I have left a space at the top to accommodate the button frame. This ensures that the button frame is always active and not covered by the System screen. If you use the border commands you may find you have to reduce the window sizes by a few pixels in order to avoid an 'out of range' error.

The above procedure will give you larger Basic windows but programs such as Quill, Archive, Abacus, Easel, Xchange, Perfection etc were written with the old screen size of 512 x 256 coded into them and cannot be expanded. Most current programs also have their font sizes coded into them as well so there is very little that can be done to increase the size of the letters displayed on the screen. The only current exceptions to this are ProWesS and Text 87 which do allow you to configure font sizes for display purposes.

The best advice is to try several different display sizes until you find the one that fits both your eyesight and your monitor. Don't forget that you can alter the display size without having to reset the computer by using the DISP_SIZE command.

Contents

SMSQ/E	1
How to use this manual	1
SMSQ/E.....	1
SMSQ/E for the GoldCard and SuperGoldCard	1
SMSQ/E for the Aurora.....	2
SMSQ/E for the ATARI.....	2
SMSQ/E for QXL and QXL 2	2
SMSQ/E for QPC1.....	2
SMSQ/E for QPC2.....	2
SMSQ/E for Q40.....	2
SMSQ/E Display.....	2
Contents.....	4
Introduction	14
New and Modified Facilities.....	14
SMSQ Performance	16
IO_PRIORITY.....	16
CACHE_ON CACHE_OFF	16
SLUG.....	17
Execution Wait Delay	17
SBASIC / SuperBASIC Language Differences	17
Hexadecimal and Binary Values.....	17
IF Clauses	17
SElect Clauses.....	17
WHEN ERRor.....	18
Loop Handling	18
FOR Loop Types	18
In-Line Loops.....	18
The "NEXT Bug".....	18
Unnamed NEXT, EXIT and END Statements	18
REPeat Loops	19
Multiple Index Lists and String Slicing	19
Writing Compiler Compatible Programs	19
DEVTYPE.....	21
Error Reporting and Statement Numbering	21
Extended SuperBASIC Commands and Functions	21
File Keywords.....	21
LOAD LRUN MERGE MRUN	21
SAVE SAVE_O.....	21
QLOAD QLRUN	21
QMERGE QMRUN QSAVE QSAVE_O.....	21
RESET.....	22
LBYTES SBYTES SBYTES_O SEXEC SEXEC_O.....	22
EPROM_LOAD.....	22
Peeking and Poking.....	23
PEEK\$ POKE\$	23
PEEK PEEK_W PEEK_L PEEK_F.....	23
POKE POKE_W POKE_L POKE_F	23
Absolute PEEK, POKE	23
Peeking and Poking in the System Variables	23
Peeking and Poking in the SBASIC Variables.....	24

Screen Functions.....	24
SCR_BASE SCR_LLEN.....	24
SCR_XLIM SCR_YLIM.....	24
File I/O.....	24
BPUT BGET.....	24
WGET, WPUT, LGET, LPUT.....	24
HGET, HPUT.....	25
UPUT.....	25
Maths.....	25
ATAN.....	25
Date Keywords.....	25
PROT_DATE.....	25
YEAR% MONTH% DAY% WEEKDAY%.....	25
VER\$ Function.....	26
VER\$.....	26
INSTR and INSTR_CASE.....	26
INSTR_CASE.....	26
System Fonts.....	26
CHAR_DEF.....	26
CHAR_USE.....	27
Program Editing.....	27
ED.....	27
Command Line History.....	27
Stuffer Buffer.....	27
HOT_GETSTUFF\$.....	27
Outlining.....	27
OUTLN.....	27
Job ID Function.....	28
JOBID.....	28
EX command extensions.....	28
FEX EXF.....	28
FET.....	28
FEW.....	28
FEP.....	28
EX_M FEX_M.....	28
Medium Information - DMEDIUM_xxx.....	29
DMEDIUM_NAME\$.....	29
DMEDIUM_DRIVE\$.....	29
DMEDIUM_RDONLY.....	29
DMEDIUM_REMOVE.....	29
DMEDIUM_DENSITY.....	29
DMEDIUM_FORMAT.....	29
DMEDIUM_TYPE.....	29
DMEDIUM_TOTAL DMEDIUM_FREE.....	29
EOFW.....	29
Print Formatting.....	30
PRINT_USING.....	30
Multiple Copies of SBASIC.....	30
SBASIC Daughter Jobs.....	31
SBASIC Command.....	31
WTV WMON.....	31
JOB_NAME.....	31
Executing SBASIC Programs.....	32
Channel #0.....	32
SBASIC and Resident Extensions.....	32
SBASIC Executable Thing.....	32
The SBASIC Interface Things.....	33
Terminate An SBASIC Program.....	33
QUIT.....	33
Input Line Editing.....	33

Language Facilities	34
Language Specification	34
Language Control Procedures	34
LANG_USE	34
LANGUAGE LANGUAGE\$	35
KBD_TABLE	35
TRA	35
The Home Thing	36
HOME_xxx Extensions	36
HOME_DIR\$	36
HOME_FILES\$	36
HOME_CURR\$	36
HOME_DEF	36
HOME_VER\$	37
HOME_CSET	37
HOME_SET	37
The Recent Thing	37
Concepts	38
The lists	38
Job IDs	38
Buffers	39
The Thing Interface In Assembler	39
SBASIC Keywords	39
RCNT_INFO	39
RCNT_JOBS	40
RCNT_ADDF	40
RCNT_GFFA\$	41
RCNT_GFFJ\$	41
RCNT_GALL	41
RCNT_GALJ	41
RCNT_GARR	42
RCNT_GARJ	42
RCNT_HASH\$	43
RCNT_SAVE	43
RCNT_LOAD	43
RCNT_REMV	44
RCNT_SYNC	44
Configuration	44
Performance penalty	44
Machine Type Functions	45
MACHINE	45
PROCESSOR	45
Display Extensions	45
DISP_xxx Keywords	45
DISP_BLANK	45
DISP_COLOUR	46
DISP_INVERSE	46
DISP_RATE	46
DISP_SIZE	47
DISP_TYPE	47
Graphic Device Interface Version 2	48
Limitations	48
Extended Colour SBASIC Procedures	48
Wallpaper	48
BGCOLOUR_QL	48
BGCOLOUR_24	48
BGIMAGE	49

Palette Maps.....	49
PALETTE_QL.....	49
PALETTE_8.....	49
SBASIC Colour Definition Selection	50
COLOUR_QL.....	50
COLOUR_PAL.....	50
COLOUR_24.....	50
COLOUR_NATIVE.....	50
Alpha Blending.....	50
ALPHA_BLEND.....	50
The System Palette and Window Manager 2.....	51
Colours List.....	51
Colour Commands.....	52
WM_INK.....	52
WM_PAPER.....	52
WM_STRIP.....	52
WM_BORDER.....	53
WM_BLOCK.....	53
System and Job Palette Handling.....	53
SP_RESET.....	53
SP_GETCOUNT.....	53
SP_GET.....	53
SP_SET.....	53
SP_JOBPAL.....	54
SP_JOBOWNPAL.....	54
Window Move.....	54
WM_MOVEMODE.....	54
Background drawing.....	55
PE_BGON PE_BGOFF.....	55
Cursor Extensions.....	55
How to load a cursor sprite.....	55
CURSPRLOAD.....	55
How to use a sprite as cursor.....	55
CURSPRON CURSPROFF.....	55
Load A Sprite And Set As System Sprite Number.....	56
SYSSPRLOAD.....	56
Common keyboard driver.....	56
CTRL-C Action.....	56
SERIAL IO Devices.....	57
Serial and Parallel Port Names.....	57
Serial Port Control.....	58
Standard BAUD Command.....	58
BAUD.....	58
Extended BAUD Command.....	58
SER_FLOW.....	58
SER_ROOM.....	58
SER_BUFF.....	58
SER_CLEAR SER_ABORT.....	59
SER_CDEOF.....	59
SER_USE.....	59
Parallel Port Control.....	59
PAR_BUFF.....	59
PAR_CLEAR PAR_ABORT.....	59
PAR_USE.....	59
PRT_USE.....	59
Virtual Devices.....	60

NUL Device	60
PIPE Device	60
HISTORY Device.....	61
DEV - A Virtual Filing System Device	62
DEV_USE	62
DEV_LIST.....	62
DEV_USE\$ DEV_NEXT	63
Interaction between DATA_USE, PROG_USE and DEV	63
DEV_USEN	63
Directory Devices	63
DOS disks.....	63
SMSQ/E Event Handling	64
Principles.....	64
SBASIC Implementation.....	64
WAIT_EVENT.....	64
SEND_EVENT.....	65
Utility Programs.....	65
DRVCHK and DRVLINK Hard Disk Utilities.....	65
SERNET V3.....	65
xNET_STATION	66
xNET_STATION%	66
xNET_TEST%	66
xNET_START.....	66
xNET_STOP.....	66
xNET_BAD%	66
xNET_RETRIES%.....	66
SERNET via Modem	66
xNET_CONNECT%.....	67
SERNET File Protection	67
SERNET Batchfile Execution.....	67
SMSQ/E Troubleshooting	68
Hints on various extensions and files	70
SMSQ/E FOR ATARI ST AND TT.....	72
Introduction	72
Machine Type.....	72
MACHINE	72
PROCESSOR.....	72
Memory Protection.....	72
PROT_MEM	72
POKES POKES_W POKES_L POKES_F POKES\$	73
PEEKs PEEKS_W PEEKS_L PEEKS_F PEEKS\$.....	73
Atari ST and TT Displays	73
Display Type.....	73
DISP_TYPE.....	73
Monochrome Display.....	73
DISP_INVERSE	73
Colour Displays	74
DISP_SIZE	74
DISP_RATE.....	74
DISP_BLANK	74
DISP_SIZE Experimenter.....	74

Serial (RS232) Ports on the Atari ST and TT Series	75
SER1	75
SER2	75
SER3	76
SER4	76
Atari ST Printer Port	76
PAR_PULSE	76
Atari ST and TT Hard Disks	76
ACSI and SCSI Drives.....	76
WIN Drive Numbers and Name	76
WIN_DRIVE.....	77
WIN_DRIVE\$.....	77
WIN_USE	77
Handling ACSI Adapter Timing Faults	77
WIN_SLUG.....	77
Format WIN	77
WIN_FORMAT	78
WIN Control Commands.....	78
WIN_WP.....	78
WIN_START WIN_STOP	78
WIN_REMV	78
Atari ST and TT Floppy Disks.....	78
Floppy Disk Driver Name.....	79
FLP_USE.....	79
Format FLP.....	79
FLP_DENSITY	79
FLP_TRACK.....	79
FLP Control Commands	79
FLP_SEC.....	79
FLP_START	79
FLP_STEP.....	80
Configuration.....	80
SMSQ/E FOR GOLD AND SUPER GOLD CARDS	81
Introduction	81
Loading SMSQ/E.....	81
Machine Type.....	81
MACHINE	81
PROCESSOR.....	81
GOLD Card Display	81
DISP_TYPE.....	81
Serial (RS232) Ports on the GOLD & Super GOLD Card	81
BAUD	82
STX	82
XON XOFF	82
SER_PAUSE	82
Super GOLD Card Printer Port	82
GOLD Card Floppy Disks.....	82
Floppy Disk Driver Name.....	83
FLP_USE.....	83

Format FLP.....	83
FLP_DENSITY	83
FLP_TRACK.....	83
FLP Control Commands	83
FLP_SEC.....	83
FLP_START	83
FLP_STEP.....	84
GOLD Card Microdrives.....	84
SER Mouse.....	84
Loading the driver	84
Function.....	84
Printer.....	84
Cable Connector.....	85
Focussing	85
Hermes	85
Configuration	86
Mouse Buttons.....	86
BASIC Commands	87
BAUDRATE%.....	87
BLS.....	87
SERMAWS	87
SERMCUR SERMPTR	87
SERMOFF	87
SERMON.....	87
SERMRESET	87
SERMSPEED	87
SERMWAIT	88
Configuration.....	88
SMSQ/E FOR THE AURORA	89
Introduction	89
Loading SMSQ/E.....	89
Machine Type.....	89
MACHINE	89
PROCESSOR.....	89
GOLD Card Display	89
DISP_TYPE.....	89
SMSQ/E FOR THE QXL	90
Introduction	90
Loading SMSQ/E.....	90
Machine Type.....	90
MACHINE	90
PROCESSOR.....	91
QXL Display	91
DISP_TYPE	91
DISP_SIZE	91
Serial (COM) Ports on the PC.....	91

BAUD.....	91
PC Printer Port.....	91
PC Floppy Disks	91
Floppy Disk Driver Name.....	92
FLP_USE.....	92
Format FLP.....	92
FLP Control Commands	92
FLP_SEC FLP_START FLP_STEP.....	92
PC Hard Disks.....	92
Hard Disk Driver Name.....	92
WIN_USE	92
Format WIN	92
WIN_FORMAT	92
Configuration.....	93
SMSQ/E FOR Q40	94
Introduction	94
Machine Type.....	94
MACHINE	94
PROCESSOR.....	94
Memory Protection.....	94
PROT_MEM	94
POKES POKES_W POKES_L POKES_F POKES\$	94
PEEKs PEEKS_W PEEKS_L PEEKS_F PEEKS\$.....	94
Q40 Display.....	94
DISP_TYPE.....	95
DISP_INVERSE	95
DISP_SIZE	95
DISP_RATE.....	95
DISP_BLANK	95
Mouse driver	95
MOUSE_SPEED	95
MOUSE_STUFF	96
Serial (RS232) Ports on the Q40.....	96
Parallel Printer Ports	96
PAR_PULSE	97
PAR_WAIT	97
Q40 Hard Disks.....	97
IDE drives.....	97
WIN Drive Numbers and Name	97
WIN_DRIVE.....	98
WIN_DRIVE\$.....	98
WIN_USE	98
Format WIN	98
WIN Control Commands.....	99
WIN_WP.....	99
WIN_START WIN_STOP	99
Q40 Floppy Disks	99

Floppy Disk Driver Name.....	99
FLP_USE.....	99
Format FLP.....	99
FLP_DENSITY	100
FLP_TRACK.....	100
FLP Control Commands	100
FLP_SEC.....	100
FLP_START	100
FLP_STEP.....	100
Sampled Sound System.....	100
SMSQ/E FOR QPC2	103
Mouse	103
MOUSE_SPEED	103
MOUSE_STUFF	103
Machine Type.....	103
MACHINE	103
PROCESSOR.....	103
QPC-Specific Commands	103
QPC_CMDLINE\$.....	103
QPC_EXEC	103
QPC_EXIT	104
QPC_HOSTOS.....	104
QPC_MAXIMIZE QPC_MINIMIZE QPC_RESTORE.....	104
QPC_MSPEED.....	104
QPC_NETNAME\$	104
QPC_QLSCREMU	104
QPC_SYNCSCRAP.....	105
QPC_VER\$	105
QPC_WINDOWSIZE	105
QPC_WINDOWTITLE	105
Serial (COM) Ports.....	105
BAUD.....	105
SER_GETPORT\$	106
SER_SETPORT	106
Printer Support (PAR)	106
PAR_DEFAULTPRINTER\$	106
PAR_GETPRINTER\$	106
PAR_SETPRINTER.....	106
PAR_GETFILTER	106
PAR_SETFILTER.....	106
PAR_PRINTERCOUNT	107
PAR_PRINTERNAME\$	107
PC Floppy Disks	107
Native Floppy Support.....	107
Floppy Image Support	107
Floppy Disk Driver Name.....	107
FLP Control Commands	107
FLP_USE.....	107
FLP_DRIVE	107
FLP_DRIVE\$.....	107
FLP_DENSITY	108
FLP_SEC, FLP_START and FLP_STEP.....	108

WIN Disks	108
Hard Disk Driver Name.....	108
WIN_USE	108
Format WIN	108
Drive/Filename Assignment.....	109
WIN_DRIVE WINDRIVE\$.....	109
Removable Drives	109
WIN_REMV	109
The DOS Device	109
Drive/Directory Assignment	109
Restrictions And Some Background Information On The DOS Device.....	109
DOS Control Commands	110
DOS_USE	110
DOS_DRIVE	110
DOS_DRIVE\$.....	110
The QPC CD-Audio Module	111
New Basic Commands	111
CD_INIT.....	111
CD_PLAY	111
CD_STOP.....	111
CD_RESUME	111
CD_EJECT, CD_CLOSE.....	111
CD_ISPLAYING, CD_ISCLOSED, CD_ISINSERTED, CD_ISPAUSED.....	111
CD_TRACK	112
CD_TRACKTIME.....	112
CD_ALLTIME	112
CD_HSG2RED, CD_RED2HSG.....	112
CD_TRACKSTART.....	112
CD_TRACKLENGTH.....	112
CD_FIRSTTRACK, CD_LASTTRACK.....	112
CD_LENGTH.....	112
CD_HOUR, CD_MINUTE, CD_SECOND.....	112
SMSQ/E MANUAL REVISION HISTORY	113

Introduction

SMSQ/E is based on the SMS kernel which was designed to provide a QDOS compatible interface. The kernel has been modified to improve compatibility with most of the "dirty tricks" which QL programmers were either forced to use or used to satisfy their perverted sense of fun.

The kernel itself (memory management, task management, scheduling, and IO) has also been extended to provide facilities which were not available with QDOS. It is now an over-inflated 10k bytes. Despite this inflation, the SMSQ operating system kernel remains more efficient than the old QDOS kernel.

SuperBASIC has been replaced by SBASIC which is a threaded code interpreter which executes at speeds more often associated with compiled SuperBASIC than interpreted SuperBASIC. There is no longer any need to compile SuperBASIC programs: you can just EXECute them.

The SMSQ/E CONsole driver incorporates slightly improved versions of the Pointer Interface, Window Manager and HOTKEY System 2: these do not need to be loaded in your BOOT files.

In addition, SMSQ/E is supplied with entirely new filing system device drivers which allow "foreign" disk formats to be recognised and new formats to be added "at run time".

SMSQ/E allows the user-selected "warmstart". This is achieved by pressing ALT SHIFT CTRL TAB at the same time. The system reboots without loading itself in again. This might be useful, for example, to clean the memory when your heap becomes too fragmented, or to get rid of unwanted extensions after you modified your BOOT file.

It is not advisable to use this warmstart feature when your system has crashed, as SMSQ/E itself might have been damaged by the system crash and you do not notice it immediately, but your data might become corrupted later due to system errors.

New and Modified Facilities

SMSQ/E includes all the QL SuperBASIC commands, the TK2 commands and the commands which have provided to support the various add-on drivers. (This manual does not concern itself with the standard SuperBASIC or TK2 commands.) SMSQ/E supports 99.9% of SuperBASIC. SMSQ/E supports all the devices which were supported by the drivers supplied with the Atari QL Emulator, the GOLD card and the QXL.

There are, however, a number of significant new facilities or improvements, some of which may be familiar to some users. Some facilities (marked HW) are hardware dependent are described in the appropriate hardware specific manuals.

Facility	Usage or Difference
\$nnn %nnn	Hexadecimal and binary values accepted
ATAN	ATAN (x,y) yields four quadrant result
BAUD	Independent baudrates
BGCOLOUR_xx	Set background colour
BGET BPUT	Transfer multiple bytes to and from strings
BGIMAGE	Background image, wallpaper
CACHE_ON _OFF	Turn internal caches on or off
CD_xx	CD-Audio extensions in QPC2
CHAR_DEF	To activate new system fonts
COLOUR_xx	Colour definition selection
CURSPRLOAD	Load a file to use as cursor sprite
CURSPROFF CURSPRON	Switch cursor sprite off/on
DAY%	Returns current day number or that of supplied DATE value
DEV	A defaulting filing system device
DEV_LIST	Lists the current DEVs
DEV_NEXT	Enquires the next DEV for a DEV
DEV_USE	Sets the real device for a DEV
DEV_USEN	Allows renaming of DEV device
DEV_USE\$	Enquires the real device for a DEV

DEVTYPE	Find the type of device open as a channel
DISP_xxx	Display control facilities
DMEDIUM_xxx	Driver- and medium-information
DOS_xx	DOS device extensions for QPC2
ED	Line can be put into the HOTKEY buffer
END FOR END REPEAT	Do not need names
EOF_W	Wait for end of file
EPROM_LOAD	Loads and initialises a "QL EPROM cartridge"
EX EW EXEC EXEC_W	Extended to execute SBASIC programs
EX_M	Create job owned by calling job, which continues executing
EXF	Alternate form of FEX function
EXIT	Does not need a name
FEX EXF FET FEW FEP	Functions corresponding to EX, EW, ET and EXEP
FLP_xxx	FLP device control facilities
FOR	Both integer and floating point FOR
HISTORY	A last in, first out rubbish bin
HOME_xxx	Home Thing extensions
HOT_GETSTUFF\$	Get current or previous content of stuffer buffer
HPUT HGET	Reads and writes part of a file header
IF	Multiple nested inline IFs. Nesting is checked
INSTR_CASE	Switches between case-dependent and case-independent INSTR
IO_PRIORITY	Set the priority of IO retry scheduling
JOBID	Return 32-bit Job ID number
JOB_NAME	Sets the Job name for SBASIC jobs
KBD_TABLE	Uses international codes to set keyboard tables
LANG_USE	Sets the message language
LANGUAGE (\$)	Language enquiry
LBYTES	Accepts channel number in place of name
LOAD LRUN	Accept QLOAD _SAV files and save filename
LPUT LGET	Puts and gets long words
LRESPR	If used to load extensions within an SBASIC job other than job 0, the extensions are private to that job
MACHINE	Return machine type number
MERGE MRUN	Accept QLiberator _SAV files
MONTH%	Returns current month number or that of supplied DATE value
MOUSE_SPEED	Define scaling and acceleration factor
MOUSE_STUFF	Defines character string for mouse centre button
NEXT	Does not need a name
NUL	A bottomless bin for output or endless input
OUTLN	Does not require window parameters
PALETTE_xx	Palette colour mapping
PAR	Centronics port driver with dynamic buffering
PAR_xx	Parallel port control extensions
PE_BGON PE_BGOFF	Turn on/off background drawing
PEEK etc.	Extended to access system and SBASIC vars
PEEKs etc.	Supervisor mode access to IO hardware (Atari/Q40)
PEEK\$	PEEKs multiple bytes
PIPE	Named or unnamed pipes for inter task comms
POKE etc.	Extended to access system and SBASIC vars
POKEs etc.	Supervisor mode access to IO hardware (Atari)
POKE\$	POKEs multiple bytes
PRINT_USING	Extended version
PROCESSOR	Returns processor type value
PROT_DATE	Protect the real time clock
PROT_MEM	Set the memory protection level (Atari)
PRT	Pseudonym for PAR
PRT_USE	Sets the port to be used for PRT
QLOAD QLRUN	QLiberator compatible quick load for _SAV file
QMERGE QMRUN	QLiberator compatible quick merge for _SAV file
QPC_xx	QPC-specific extensions
QSAVE QSAVE_O	QLiberator compatible save to _SAV file
QUIT	Removes this SBASIC job, optional quit value
REPEAT	Does not need a name

RESET	RESETs the computer
SAVE SAVE_O	Use previously defined filename, update version
SBASIC	Starts an SBASIC daughter
SBYTES SBYTES_O	Accepts channel number in place of filename
SCR_BASE SCR_LLEN	Find the screen base and line length
SCR_XLIM SCR_YLIM	Find window limits
SElect	Both integer and floating point SElects
SEND_EVENT	Notify events to another job
SER	Additional options and dynamic buffering
SER_xx	Serial port extensions
SEXEC SEXEC_O	Accepts channel number in place of name
SLUG	Slows the machine down
SNET_xx	Sernet extensions
SP_xx	System Palette extensions
SRX	As SER but input port only
STX	As SER but output port only
SYSSPRLOAD	Load sprite and set as a system sprite
TRA	language selectable and language independent
UPUT	send untranslated characters to channel
VER\$	extended to be Minerva-compatible
WAIT_EVENT	Wait for one or more events
WEEKDAY%	returns current day of the week or that of supplied DATE value
WHEN ERROR	suppressed within command line
WIN_xxx	WIN device control facilities
WM_xxx	Window Manager system palette colour commands
WM_MOVEMODE	Set window move mode
WM_MOVEALPHA	Set window move transparency
WMON WTV	Allow the SBASIC windows to be offset
WPUT WGET	Puts and gets words
YEAR%	Returns current year number or that of supplied DATE value

SMSQ Performance

In general, SMSQ is more efficient than QDOS. There are, however, a number of policy differences which are either accidental because, unlike other "QDOS compatible" systems SMSQ is not based on QDOS but is completely re-designed, or deliberate because certain QDOS policies have shown to be less than ideal.

In particular, the IO retry scheduling policy is completely different. This results in a very much higher priority for retry operations which greatly improves the responsiveness of a heavily loaded system at the cost of a modest reduction in crude performance (typically 10%). If crude performance is important to you, you can reduce the the IO priority to QDOS levels.

IO_PRIORITY

The IO_PRIORITY (priority) command sets the priority of the IO retry operations. In effect, this sets a limit on the time spent by the scheduler retrying IO operations.

A priority of one sets the IO retry scheduling policy to the same as QDOS, thus giving a similar level of response but with a higher crude performance.

IO_PRIORITY 1	<i>QDOS levels of response, higher crude performance</i>
IO_PRIORITY 2	<i>QDOS levels of performance, better response under load</i>
IO_PRIORITY 10	<i>Much better response under load, degraded performance</i>
IO_PRIORITY 1000	<i>Maximim response, the performance depends on the number of jobs waiting for input.</i>

CACHE_ON CACHE_OFF

The performance of the more powerful machines depends on the use of the internal cache memory. For the MC680x0 series processors, the implementation of the caches is less than perfect. As well as introducing

unnecessary overheads on operating system calls (slightly improved in the MC68040) the MC680x0 cache policy is incompatible with certain programming techniques. It may, therefore, be necessary to disable the internal caches.

No provision is made for disabling the external caches (where these exist) as none of these external caches seem to suffer from the design flaws of the MC680x0 series.

CACHE_OFF *turn the caches off to run naughty software*
CACHE_ON *and turn back on again*

SLUG

The designers of SMSQ have spent much time and effort trying to make the system fairly efficient. Their efforts seem not to be appreciated. Some people will always complain!

SLUG (slug factor) will slug your machine by a well defined factor.

SLUG 2 *Half speed ahead*
SLUG 5 *Dead slow*
SLUG 1 *Full ahead both*

Execution Wait Delay

Traditionally, commands like EX waited for half a second before returning to give the executed job a chance to open up a window. This, for example, ensures that buttons in the button frame show up in the order you start them in the boot file. Today's machines, however are much faster and don't really need such a long pause anymore.

To counter this problem there is now a new system variable **sys_xdly** (byte at **\$17e**) that determines the delay for a specific machine. This is preset to 5/50th of a second for QPC originally, which results in a much faster boot time. However for the full effect QPAC2 had to be updated too, which was done with release v1.45.

On machines that don't set **sys_xdly**, half a second will again be used by default. To change **sys_xdly** yourself, for example to lower it even further to 3, you can poke a new value using this command:

POKE !;\$17F,3 *lower execution delay to 3/50 second*

SBASIC / SuperBASIC Language Differences

Some differences between SBASIC and SuperBASIC may be accidental. There are, however a number of known, deliberate, differences. Most of these differences are extensions to SuperBASIC. In some cases, however, limitations have been introduced to reduce the chances of difficult-to-track-down program errors.

Hexadecimal and Binary Values

Hexadecimal and binary values may be included directly in SBASIC source. Hexadecimal values are preceded by a \$. Binary values by a %.

IF a% && %1001 *Check bits 3 and 0 of a%*
IF PEEK_L (\$28000) = \$534D5351 *Check if SMSQ (very naughty)*

IF Clauses

Multiple "in-line" IF clauses can be nested on one line.
SBASIC checks for incorrectly nested IF clauses.

SElect Clauses

SElect clauses may SElect an action on the value of an integer variable (integer SElect) or on the value of a floating point variable or expression (floating point SElect). Integer SElect is more efficient.

SBASIC checks for incorrectly nested or inconsistent SElect clauses.

WHEN ERRor

WHEN ERRor is suppressed within the command line to stop SBASIC rushing off into your error processing if you mistype a command.

You can turn off WHEN ERRor by executing an empty WHEN ERRor clause.

```
100 WHEN ERRor
110 CONTINUE      :REMark ignore errors
120 END WHEN
130 a = 1 / 0     :REMark no error
140 WHEN ERRor   :REMark restore error processing
150 END WHEN
160 a = 1 / 0     :REMark BANG!!
```

Loop Handling

FOR Loop Types

SuperBASIC requires FOR loops to have a floating point control variable. SBASIC allows both floating point and integer control variables. Integer FOR loops are more efficient than floating point for loops: particularly if the control variable is to be used to index an array.

```
FOR i% = 0 to maxd%: array(i%) = array(i%) * 2:      is preferred to
FOR i = 0 to maxd: array(i) = array(i) * 2:          which is less efficient
```

N.B. the type is determined before the program is executed.

In-Line Loops

Whereas SuperBASIC only allows a single structure to be defined "in-line", SBASIC allows many loops (and other structures) to be nested in-line without requiring END statements:

```
100 FOR i = 1 TO n: FOR j = 1 TO m: a(i,j) = a(i,j) + b(i,j)
```

The "NEXT Bug"

The "NEXT bug" reported in many articles about SuperBASIC, which many people have asked to be fixed, has not been fixed. IT IS NOT A BUG. NEXT is defined to fall through to the next statement when the loop is exhausted. It does not go to the statement after the END FOR (which may not be present). If that is what you wish to do, follow the NEXT by an EXIT.

Unnamed NEXT, EXIT and END Statements

Loop structures are "opened" with a FOR or REPEAT statement and closed with an END FOR or END REPEAT statement. SuperBASIC requires all loop closing statements as well as the intermediate NEXT and EXIT statements to identify the loop to which they apply. SBASIC, on the other hand, will accept unnamed NEXT, EXIT, END FOR and END REPEAT statements. These are applied to the most recent (innermost) unclosed loop structure.

```
100 FOR i = 1 TO 10
110 FOR j = 1 TO 10
120 IF a(i,j) < 0: EXIT      implicitly EXIT j
130 sum = sum + a(i,j)
140 END FOR                 implicitly END FOR j, closes FOR j
150 IF sum < 100: NEXT      loop j is closed, so this is NEXT i
160 PRINT i,sum
170 sum=0
180 END FOR                 implicitly END FOR i, closes FOR i
```

REPeat Loops

Whereas SuperBASIC requires all REPeat clauses to have a name, SBASIC allows unnamed REPeats. These unnamed REPeats may be combined with unnamed NEXT, EXIT and END REpeat statements.

```
100 REPeat
110 a$ = INKEY$(-1)
120 IF a$ = ESC$: EXIT      goes to 200 (outer loop)
130 IF a$ <> 'S': NEXT      goes to 110 (outer loop)
130 REPeat
140 a$ = INKEY$(-1)
150 IF a$ = ESC$: EXIT      goes to 180 (inner loop)
160 x$ = x$ & a$
170 END REPeat              goes to 140 (inner loop)
180 IF LEN (x$) > 20: EXIT   goes to 200 (outer loop)
190 END REPeat              goes to 110 (outer loop)
200 PRINT 'DONE'
```

Multiple Index Lists and String Slicing

For various reasons SBASIC does not support multiple index lists.

```
100 DIM a(10,10,10)
110 a(3,4)(5) = 345      OK for SuperBASIC, SBASIC will not handle this
120 a(3,4,5) = 345      Means the same, is easier to type and SBASIC likes it
```

To make up for this limitation, SBASIC allows you to slice strings at any point in an expression.

```
200 a$ = 2468 (3)        Sets a$ to '6' in SBASIC, prohibited in SuperBASIC
210 ax=1234
220 a$ = ('abcdef' & ax) (5 to 8)  Sets a$ to 'ef12' in SBASIC
230 b$ = 'abcdefghi'
240 a$ = b$(2 TO 7)(3 TO 5)(2)    Sets a$ to 'e' in either SBASIC or SuperBASIC
```

Also, in SBASIC, the default range for a string or element of a string array is always (1 TO LEN(string)) and zero length slices are accepted at both ends of a string (i.e. a\$(1 to 0) or a\$(LEN(string)+1 TO LEN(string)) are both null strings).

Writing Compiler Compatible Programs

SuperBASIC programs which are written in such a way as to be used both compiled and interpreted by SuperBASIC often have a small code fragment at the start to allow for the differences in compiled and interpreted environments.

The problem is not that SBASIC is "incompatible" with these code fragments but that SBASIC is compatible with SuperBASIC in a way which the two "compiled" SuperBASICS are not. The simplest way to avoid these problems is to give up using compiled BASIC and remove the junk from your programs. If, on the other hand, you wish to continue using compiled BASIC and also wish to use these programs in SBASIC daughter jobs, you may require some code changes.

There are three principal differences between the SuperBASIC environment and the Liberator and Turbo environments.

1. When executing in compiled form, the program will probably not be requiring windows #0, #1 and #2 in the same form as when it is being interpreted by SuperBASIC. In particular:
 - channel #0 (the command channel) may not be required at in the compiled version, but it is essential to keep it open in the SuperBASIC version otherwise no commands can ever be given again.;
 - a compiled program may be started with no windows open, a program interpreted by SuperBASIC will (usually) start with windows #0, #1 and #2 open.

This distinction is not so much a difference between compiled and not compiled, but is a difference between interpreting a program within the permanent SuperBASIC interpreter and executing a transient program.

2. An interpreted program may be interrupted and rerun (so that the starting state may be different each time), while a compiled program will always start "clean" (always having the same starting state).
3. An interpreted program will report error messages to window #0 while compiled programs have their own error message facilities.

From the point of view of the last two differences, SBASIC is always much closer to SuperBASIC than to a compiled BASIC. For the first (and most important difference) SBASIC can behave either like a compiled BASIC or SuperBASIC.

- If SBASIC is started off with an SBASIC command, then SBASIC behaves like SuperBASIC: window #0 (at least) is open.
- If SBASIC is started off with an EX (etc.) command or from a HOTKEY or QPAC2 EXEC menu, then SBASIC behaves more like a compiled program: there are no windows open by default and window #0 is not required.

Unfortunately, the code that usually appears at the start of these compatible programs does not distinguish between compiled and interpreted environments, but between job 0 and other jobs.

```

100 IF JOB$(-1)<>"           :REMark is it a named job (NOT SuperBASIC)
110 CLOSE #0,#2             :REMark close spare windows in case
120 OPEN #1,con_512x256a0x0 :REMark our #1
130 ELSE
140 WINDOW 512,256,0,0      :REMark for SuperBASIC, just set #1
150 END IF
160 CLS

```

When used in an SBASIC daughter job, this will treat SBASIC as compiled whereas it should possibly be treated as interpreted as SBASIC programs can be re-run.

The problem cannot be resolved by using a function to distinguish between compiled, SuperBASIC and SBASIC, as there is no such function in SuperBASIC and it cannot be assumed that a suitable extension has been loaded.

SBASIC jobs are, however, always called SBASIC until the name is set by the JOB_NAME command.

The best approach would be to have program start up code which is sensitive to the environment and not having a different behaviour just because the job number is 0 or the job has no name. This is however, not practical with the old QL BASIC compilers.

The least bad solution may be to have a "four way switch" at the start of the program.

```

100 my$ = 'myjob': j$ = JOB$(-1)   :REMark set my assumed and real names
110 IF j$ = "                     :REMark is it an unnamed job (SuperBASIC)?
120 do SuperBASIC or SBASIC job 0 fiddles
130 END IF
140 IF j$ = 'SBASIC'              :REMark is it start of an SBASIC daughter?
150 do SBASIC daughter initialisation
160 JOB_NAME my$                  :REMark from now on it is a named job
170 j$ = "                        :REMark no further action required
180 END IF
190 IF j$ = my$                   :REMark is it rerun an SBASIC daughter?
200 do SBASIC daughter re-initialisation
210 j$ = "                        :REMark no further action required
220 END IF
230 IF j$ <> "                    :REMark must be compiled!
240 do compiled BASIC initialisation
250 END IF

```

DEVTYPE

Within the initialisation code for SBASIC, the DEVTYPE function may be used to determine whether a channel is open.

This returns an integer value of which only the most significant (the sign bit) and least significant two bits are set. To ensure future compatibility, nothing should be assumed about the other bits.

The value returned will be negative if there is no channel open. Otherwise bit 0 indicates that it will support window operations (i.e. it is a screen device), bit 1 indicates that it will support file positioning operations (i.e. it is a file).

```
100 a% = DEVTYPE (#3)           :REMark find the type of device open as #3
110 IF a% < 0: PRINT '#3 not open' :REMark negative is not open
120 SELECT ON a% && %11         :REMark ensure we only look at bits 0 and 1
130 = 0: PRINT '#3 is a purely serial device'
140 = 1: PRINT '#3 is a windowing device'
150 = 2: PRINT '#3 is a direct access (filing system) device'
160 = 3: PRINT '#3 is totally screwed up'
170 END SELECT
```

Error Reporting and Statement Numbering

SBASIC will, usually, report error in the form:

At line 250:3 end of file

The number after the colon is the statement number within the line.

N.B. SBASIC generates a small number of additional statements (jumps round DEF PROCs, jumps to END SElect before each ON and END statements on inline clauses) which are not visible in the SBASIC program. If you like piling up structures and statements into a single line, you may find that the statement number in the error report is larger than you would expect!

Extended SuperBASIC Commands and Functions

File Keywords

LOAD LRUN MERGE MRUN

LOAD, LRUN, MERGE and MRUN have been extended to accept Liberation Software's _SAV file format. In addition, if the filename supplied is not found, SBASIC will try first with _BAS and then _SAV added to the end of the filename (it will try .BAS or .SAV if the given device contains a DOS-formatted medium).

SAVE SAVE_O

If no filename is given, the name of the file that was originally loaded will be used (if necessary substituting _BAS for _SAV at the end or vice versa). The file will be saved with a version number one higher than the file version when it was LOAded. (Repeated SAVEs do not, therefore, keep on incrementing the version number).

If a filename is given, the version number is set to 1.

QLOAD QLRUN

The extension of the SBASIC LOAD command makes the real QLOAD and QLRUN commands (which require a copy or near copy of QDOS ROMs to function at all) nearly redundant. QLOAD and QLRUN are implemented in SBASIC as versions of LOAD and LRUN that ensure that there is a _SAV at the end of the filename.

QMERGE QMRUN QSAVE QSAVE_O

These are versions of MERGE, MRUN, SAVE and SAVE_O which work with _SAV files.

If there are 4 SBASIC programs in the data default directory called FRED, JOE, ANNE and CLARA with either _BAS or _SAV at the end of the names.

FRED
JOE_BAS
ANNE_SAV
CLARA_BAS
CLARA_SAV

QLOAD fred	<i>Fails as there is no FRED_SAV</i>
LOAD fred	<i>Loads FRED</i>
SAVE	<i>Saves the program as FRED</i>
QSAVE	<i>Saves the program as FRED_SAV (quickload format)</i>
SAVE junk_bas	<i>Saves the program as JUNK_BAS</i>
QSAVE	<i>Saves the program as JUNK_SAV (quickload format)</i>
MERGE joe	<i>Merges the file JOE_BAS into the program</i>
MERGE anne	<i>Quick merges the file ANNE_SAV into the program</i>
SAVE	<i>Saves it as JUNK_BAS (MERGE does not change the name)</i>
LOAD clara	<i>Loads CLARA_BAS</i>
QLOAD clara	<i>Quick loads CLARA_BAS</i>
LOAD clara_sav	<i>Also quick loads CLARA_BAS</i>

RESET

RESETs the computer. Using this command could result in loss of data (e.g. when you RESET while sectors are being written to your floppy disk or harddisk), therefore much care should be taken if this command is used without the control of the user.

LBYTES SBYTES SBYTES_O SEXEC SEXEC_O

All accept a channel number in place of a name. This can improve efficiency.

nc = FOP_IN ('file')	<i>Open file once only</i>
base = ALCHP (FLEN(#nc))	<i>... to allocate bit of heap</i>
fdt = FUPDT (#nc)	<i>... get the update date</i>
LBYTES #nc,base	<i>... and load it</i>
CLOSE #nc	

EPROM_LOAD

The EPROM_LOAD (filename) command is a special trick for loading the image of a QL EPROM cartridge. Most EPROM cartridges are programmed so that the cartridge may be at any address. Some require to be at exactly \$C000, the QL ROM port address. The first time the command is used after reset, the EPROM image will be loaded at address \$C000. Subsequent images may be loaded at any address. Fussy EPROM images must, therefore, be loaded first. An EPROM image file must not be longer than 16 kilobytes.

To make an EPROM image, put the EPROM cartridge (for example the Prospero PRL cartridge) into your QL and turn on. SBYTES the image to a suitable file with the magic numbers 49152 (\$C000) for the base address and 16384 (16 kilobytes) for the length.

SBYTES flp1_prl, 49152, 16384 ***Save Prospero PRL image***

On your SMSQ machine copy the file to your boot diskette or disk and add the EPROM_LOAD statement to your "boot" file.

EPROM_LOAD flp1_prl ***Load Prospero PRL image***

QL Based Hardware

SMSQ on QL based hardware recognises plug-in ROM cartridges and copies them to fast memory when the system is booted. EPROM_LOAD can still be used, however, to load ROM images. If the ROM slot is vacant,

then the first EPROM load will load to the QL ROM Port address. Otherwise, all EPROM images will be loaded to arbitrary addresses.

Peeking and Poking

PEEK\$ POKE\$

PEEK\$ (address, number of bytes) returns a string with the number of bytes starting from address. The bytes need not, of course, be text.

POKE\$ (address, string) pokes the bytes of the string starting from the address.

PEEK\$ and POKE\$ can be used for copying memory.

a\$ = peek\$ (base1,1000) *Peek 1000 bytes from address base1*
poke\$ base2,a\$ *... and poke them back to base2*

PEEK\$ and POKE\$ can accept all the extended addressing facilities of PEEK and POKE. Indeed, POKE\$ is identical to POKE which can now accept string parameters.

PEEK PEEK_W PEEK_L PEEK_F

POKE POKE_W POKE_L POKE_F

The standard PEEK functions and POKE procedures have been extended to provide compatibility with the Minerva versions. There are three main changes.

1. The address may be specified relative to the base of the system variables or the (current) SBASIC variables.
2. The contents of the memory at the address may itself be used as a base address with a second value providing an offset for this address.
3. More than one value may be POKEd at a time.
 - For POKE_W and POKE_L, the address may be followed by a number of values to poke in succession.
 - For POKE the address may be followed by a number of values to poke in succession and the list of values may include strings. If a string is given, all the bytes in the string are POKEd in order. The length is not POKEd.

Absolute PEEK, POKE

The standard forms of PEEK and POKE are supported even though the use of PEEK and POKE is best regarded as a form of terrorism.

a=RESPR (2000)
LBYTES myfile,a *Load myfile*
PRINT PEEK (a), *Prints the value of the byte of myfile*
POKE_L a+28, DATE,0 *Set the 28th to 35th bytes to the DATE (4 bytes) and 4 zeros*
POKE a+8, 0,6,'My_Job' *Set the standard string (word length followed by the chars)*

An additional form to handle floating point values has been introduced. PEEK_F and POKE_F function like the existing forms, but handle 6-byte floating point values.

v = 1.23 : POKE_F a, v *Set the 6 bytes at address a to the value of the variable v*
v = PEEK_F(a) *Read the 6 byte floating point value at address a*

Peeking and Poking in the System Variables

If the first parameter of the peek or poke is preceded by an exclamation mark, then the address of the peek or poke is in the system variables or referenced via the system variables. There are two variations: direct and indirect references.

- For direct references, the exclamation mark is followed by another exclamation mark and a an offset within the system variables.
- For indirect references, the exclamation mark is followed by the offset of a pointer within the system variables, another exclamation mark and an offset from that pointer.

```
ramt = PEEK_L (!!$20)      Find the top of RAM $20 bytes on from the base of sysvars
POKE_W !!$8e,3          Set the auto-repeat speed to 3
job1 = PEEK_L (!$68!4)   Find the base address of Job 1 (4 on from base of Job table)
POKE !B0!2, 'WIN'       change the first three characters of DATA_USE to WIN
```

There is slightly more parameter checking than in the Minerva versions. Nevertheless, errors and deliberate abuse are not likely to be detected and may have different effects on SMSQ and Minerva.

Peeking and Poking in the SBASIC Variables

If the first parameter of the peek or poke is preceded by an backslash, then the address of the peek or poke is in the SBASIC variables or referenced via the SBASIC variables. There are two variations: direct and indirect references.

- For direct references, the backslash is followed by another backslash and an offset within the SBASIC variables.
- For indirect references, the backslash is followed by the offset of a pointer within the SBASIC variables, another backslash and an offset from that pointer.

```
dal = PEEK_W (\\$94)      Find the current data line number
n6 = PEEK_W (\$18\2+6*8)  Find the name pointer for the 6th name in the name table
nl6 = PEEK (\$20\n6)     . . . and the length of the name
n6$ = PEEK$ (\$20\n6+1, nl6) . . . and the name itself.
```

Screen Functions

SCR_BASE SCR_LLEN

The SCR_BASE (channel) and SCR_LLEN (channel) functions are provided for those who wish to start peeking and poking in the display. They return the base address of the screen and the line length (in bytes). The channel numbers are optional (default is #0), and, in current versions, the values returned are the same for all screen channels.

SCR_XLIM SCR_YLIM

The SCR_XLIM (channel) and SCR_YLIM (channel) return the maximum pixel (+1) for the channel. This is not the same as the current window size, but it defines the maximum size that a window can be. SCR_XLIM and SCR_YLIM should only be called for a primary window (usually #0 for and SBASIC job). #0 is the default channel.

```
ssz = SCR_LLEN * SCR_YLIM    Screen size is number of lines * line length in bytes
SBYTES s1, SCR_BASE, ssz    . . . so we can save the screen
WINDOW SCR_XLIM,SCR_YLIM,0,0 Set window (#1) to cover the whole of the screen
```

File I/O

BPUT BGET

BPUT will accept string parameters to put multiple bytes. BGET will accept a parameter that is a sub-string of a string array to get multiple bytes.

```
BPUT #3,27,'R1'           Put ESC R 1 to channel #3
DIM a$(10): a$(10)='     ' Get 6 bytes from #3 into a$
':BGET #3, a$(1 to 6)
```

WGET, WPUT, LGET, LPUT

Works like BGET and BPUT, but they always read a word or longword instead of a byte.

HGET, HPUT

For reading and writing the first parts of a file header. Both commands accept up to 5 parameters, which are of the type floating point. The first parameter is the file length (long), followed by the access byte (byte), followed by the file type (byte), then comes the dataspace (long) and finally the extra-information (long).

OPEN#3,datei

HGET#3,length,access,type,space,extra

HPUT#3,length,access,1,1024,extra

CLOSE#3

converts a file into an executable file with 1kByte dataspace.

UPUT

Works as BPUT, but will never translate the character. Very useful to send translated text to a channel which does use TRA, as well as sending printer control codes using UPUT to the same channel.

Maths

ATAN

The ATAN function has been extended to provide 4 quadrant result by taking two parameters. If x is greater than 0, ATAN (x,y) give the same results as ATAN (y/x). Otherwise it returns values in the other quadrants (>p/2 and <-p/2).

Date Keywords

PROT_DATE

Where the system has a separate battery backed real time clock. The date is read from the clock when the system is reset. Thereafter, the clock is kept up to date by the SMSQ timer. (Thus the impressive speed gains made by some accelerator software: slowing the clock down by disabling interrupts can do wonders for your benchmark timings).

In general, the system real time clock is updated whenever you adjust or set the date. As some QL software writers could not resist the temptation of setting the date to their birthday (or other inconvenient date) this can play havok with your file date stamps etc.

PROT_DATE (0 or 1) is used to protect (1) or unprotect (0) the real time clock. If the real time clock is protected, setting the date affects only SMSQ's own clock, the real time will be restored then next time the computer is reset.

PROT_DATE 1 *protect the RTC (should never be required)*

PROT_DATE 0 *unprotect the RTC (normal)*

YEAR% MONTH% DAY% WEEKDAY%

These functions complement the DATE and DATE\$ functions, by providing extensions to return the year, month, day and weekday numbers corresponding to a given date stamp. WEEKDAY returns the day number of the week (0...6 Sunday...Saturday).

datestamp = DATE[(year, month, day, hour, minute, second)] *returns the number of seconds since 1st January 1961. If no parameters are supplied to the DATE function, the current time in seconds is returned.*

yr% = YEAR%[(datestamp)] *Return year number (1961...2097) of the date value supplied. If no datestamp is supplied, the current year is returned.*

m% = MONTH%[(datestamp)] *Return month number (1...12) of the date value supplied. If no datestamp is supplied, the current month is returned.*

d% = DAY%[(datestamp)] *Return day of the month (1...31) of the date value supplied. If no datestamp is supplied, the current day is returned.*

All windows which are opened now will use the new system fonts (except they define their own fonts, of course).

Channels already open will not use the new fonts automatically for various reasons: the most obvious is, that if the font file did not contain any font data, you will not be able to correct this as all characters printed will look like complete rubbish.

CHAR_USE

It is possible to attach the new fonts to channels already open:

CHAR_USE [#channel,] font1,font2 (you know it from Toolkit II)

which allows three parameters:

address of a valid QL-fonts (as usual)	or
0 (to use the current system font)	or
-1 (to leave it as it is)	

For SuperBASIC the following line would change the fonts of the channels:

```
FOR ch=0 TO 2:CHAR_USE #ch,0,0
```

Program Editing

ED

Offers a new feature: if you press F10 (or SHIFT F5) while the cursor is over a program line, then this line is put (without line number) into the HOTKEY Buffer. It can easily be retrieved by pressing ALT SPACE in any program where input is expected. In order to work, the HOTKEY System has to be going (use HOT_GO to activate).

Just a quick reminder: F9 (or SHIFT F4) toggles between insert and overwrite mode.

The SuperBASIC commands AUTO and EDIT are retained for compatibility, but now function like the ED command and no longer have their original actions.

Command Line History

Basic has a new command line history: if you press the up/down arrows, you get the latest commands entered.

Stuffer Buffer

HOT_GETSTUFF\$

A function which returns the content of the hotkey stuffer buffer. If given a parameter of 0, or no parameter, it returns the current content of the stuffer buffer, like ALT-SPACE. A parameter of -1 gets the previous content, like ALT-SHIFT-SPACE.

result\$ = HOT_GETSTUFF\$	get current content of stuffer buffer
result\$ = HOT_GETSTUFF\$(0)	get current content of stuffer buffer
result\$ = HOT_GETSTUFF\$(-1)	get previous content of stuffer buffer

Outlining

OUTLN

If you have not used OUTLN yet, then do not worry about this command and ignore it. If you have written BASIC programs using the Window Manager, then you have to be familiar with OUTLN. Older versions of the OUTLN command provided by various toolkits need a channel (or default to #0) and a window definition, and usually resize the window. This new OUTLN accepts all parameters as before, to maintain compatibility, but there is a special feature:

If OUTLN is used without parameter, then it will declare the smallest area which outlines all windows currently opened for the job to be the Outline for that job without changing the primary window.

Job ID Function

JOBID

`id = JOBID[({nr,tag} | <name>)]`

JOBID returns the 32-bit ID of the given job details as a decimal value. The optional parameters may be either a job number and job tag (as displayed by the JOBS command), or the job name. If no parameters are supplied, the Job ID number of the current job is returned.

`id = JOBID (job_number, job_tag)` *returns the Job ID of the job specified by job_number and job_tag*

`id = JOBID(job_name$)` *returns the Job ID of the job specified in job_name\$*

`id = JOBID` *returns the Job ID of the current job*

EX command extensions

The S*Basic extensions FEX (and synonym EXF), FEW, FET and FEP have been added to SMSQ/E V3.00 and later. These are function calls corresponding to the procedures EX (EXEC), EW (EXEC_W), ET and EXEP.

FEX EXF

`job_id = FEX(filename)`

`job_id = EXF(filename)`

Executes and returns the ID of the job filename. This ID can be used to manipulate the job in various ways by using the other job control extensions, such as SPJOB, MOB, RIOB, etc. The full syntax using input and output channels, as well as filters, is supported. See the TK2 documentation, section 8.xx for details.

Note: In the event of filters being set up, only the ID of the first job is returned.

Note: The name FEX clashes with the eponymous keyword from FileInfo2. For this reason, the synonymous function EXF has been introduced to avoid this clash. By the time you read this a later version of F12 may be available, otherwise you will need to patch one or the other of the keywords to access both.

FET

As for FEX above, except the job is not activated.

FEW

`error_code = FEW(filename)`

Returns the error code returned by the (first) job. Syntax as for FEX above.

Note: FEW tries to open the channels of files supplied in the parameter list before executing the job(s). Any errors arising from this, including erroneous parameters, are returned to the caller as "hard" errors.

FEP

`job_id = FEP(thingname)`

Executes and returns the ID of the job thingname. FEP is the implementation of EXEP as a function. Refer to your Qpac2 manual for details.

EX_M FEX_M

This behaves a bit like EX in that the calling job continues executing (like EX and contrary to EW) but the job created is owned by the calling job (like EW). This means that if you get rid of the calling job, you will also get rid of the created job(s). FEX_M is a function version.

Medium Information - DMEDIUM_xxx

The following set of functions can be used to obtain information about a device driver or a medium which is currently driven by this driver, which could not be obtained easily in the past (or not at all). These functions should be used on directory devices (RAM, FLP, WIN etc.) only. The parameter passed to these functions can either be a channel number (#channel) or a \directory or \file (as with most other file-functions known from Toolkit II, e.g. FDAT, FLEN).

DMEDIUM_NAME\$

Returns the medium name of the specified device.

```
OPEN #3,flp1_boot
PRINT DMEDIUM_NAME$(#3)      what's the name of the disk in flp1_?
CLOSE #3
```

```
PRINT DMEDIUM_NAME$(\win1_)  returns the name of WIN1_?
```

DMEDIUM_DRIVE\$

Returns the real device name of the specified file or device. This is the only way to check if the access is done to the device it is intended to be done, as devices may be renamed using RAM_USE, FLP_USE, WIN_USE etc. This function also allows to discover the "real" device which may be hidden behind "DEV".

```
DEV_USE 1,win1_              DEV1_ accesses WIN1_
OPEN_NEW #3,dev1_test        let's open a new file
PRINT DMEDIUM_DRIVE$(#3)    really, it's on WIN!
CLOSE #3
```

DMEDIUM_RDONLY

Returns 1 if the medium is write-protected, otherwise 0. It checks the various possibilities of write protection, even the software write-protection which is possible for harddisks and removable harddisks.

DMEDIUM_REMOVE

Returns 1 if the specified device is a removable harddisk.

DMEDIUM_DENSITY

Returns the density: 1=DD, 2=HD etc. RAM-Disks return -1, as they have no density.

DMEDIUM_FORMAT

Returns the logical format of the medium or partition: 1=QDOS/SMSQ, 2=DOS/TOS.

DMEDIUM_TYPE

Returns information about the physical drive: 0=RAM-Disk, 1=Floppy Disk, 2=Harddisk, 3=CD-ROM.

DMEDIUM_TOTAL DMEDIUM_FREE

returns the total number and number of free sectors respectively (in 512 bytes sectors).

EOFW

1. Job 0 is the "guardian" of SBASIC extensions, permanent memory allocation and channel 0.
2. SBASIC "daughter jobs" may be created with the SBASIC command. These may be created with the same set of 3 windows as the initial Job 0 windows. Alternatively, they may be created with a single channel #0 or even no windows open at all.
3. SBASIC source files (ending in _bas) may be executed by EX, EXEC, EW, EXEC_W.
4. SBASIC may be invoked as a Thing which may either operate within the context of an invoking Job, or, once set up, operate as an independent daughter Job.

SBASIC Daughter Jobs

Having a number of SBASIC jobs which completely cover each other may not be very useful. SBASIC daughter jobs may, therefore, either be created either with the full set of standard windows (in which case they all overlap) or they may be created with only one small window (#0).

SBASIC Command

The **SBASIC** command, which creates SBASIC daughter jobs, has an optional parameter: the x and y positions of window #0 in a one or two digit number (or string).

- If no parameter is given, the full set of standard windows will be opened. Otherwise, only window #0 will be opened: 6 rows high and 42 mode 4 characters wide within a 1 pixel wide border (total 62x256 pixels).
- If only one digit is given, this is the SBASIC "row" number: row 0 is at the top, row 1 starts at screen line 64, row 4 is just below the standard window #0.
- If two digits are given, this is the SBASIC "column, row" (x,y) position: column 0 is at the left, column 1 starts at 256 pixel in from the left.

SBASIC *create an SBASIC daughter with the 3 standard windows*
SBASIC 1 *create an SBASIC daughter with just channel #0 in row 1*
SBASIC 24 *create an SBASIC daughter to the right of and below the standard windows (a 800x600 display is required)*

Because it is quite normal for an SBASIC job to have only #0 open, all the standard commands which default to window #1 (PRINT, CLS etc.) or window #2 (ED, LIST etc.) will default to window #0 if channel #1 or channel #2 is not open. This may not apply to extension commands.

WTV WMON

If you have a screen larger than 512x256 pixels, it is useful to be able to re-position the SBASIC windows. The TK2 WMON and WTV commands have been extended to take an extra pair of parameters: the pixel position of the top left hand corner of the windows. If only one extra parameter is given, this is taken to be both the x and y pixel positions.

WMON 4,50 *reset windows to standard monitor layout displaced 50 pixels to the right and 50 pixels down.*

If the mode is omitted, the mode is not changed, and, if possible, the contents are preserved and the outline (if defined) is moved.

WMON ,80,40 *reset windows to standard monitor layout displaced 80 pixels to the right and 40 pixels down, preserving the contents*

A border has been added to window #0 to make it clearer where an SBASIC Job is on the screen.

JOB_NAME

The procedure JOB_NAME (job name) can be used to give a name to an SBASIC Job. It may appear anywhere within a program and may be used to reset the name whenever required. This command has no effect on compiled BASIC programs or Job 0.

JOB_NAME Killer *sets the Job name to "Killer"*
JOB_NAME "My little Job" *sets the Job name to "My little Job"*

Executing SBASIC Programs

SBASIC program files (ending in `_BAS`, `_bas`, `_SAV` or `_sav`) may be executed using the `EX` (`EXEC`) and `EW` (`EXEC_W`) commands.

EX my_little_prog_bas *executes the SBASIC program "my_little_prog_bas"*

Just as for "executable" programs, if file or device names (or channels) are given after the program name, the first file device or channel will be #0 within the program, the second will be #1 etc.

A simple program for "uppercasing" could be

```
100 JOB_NAME UC
110 REPEAT
120 IF EOF(#0): QUIT
130 BGET #0,a%
140 SELECT ON a% = 97 TO 122: BPUT #1, a% ^^ 32: = REMAINDER BPUT #1, a%
150 END REPEAT
```

Saved as "uc_bas", this can be used for printing a file in upper case:

EX uc_bas, any_file, par

It can also be used as a filter to uppercase the output of any program sending its output to the "standard output".

EX my_prog TO uc_bas, par

The command **QUIT** should be used to get rid of an SBASIC job whether it has been created by the SBASIC command, `EX` or any other means.

Channel #0

There are some oddities in the handling of channel #0 which have been introduced to make the use of SBASIC a little easier.

- On normal completion of a program, if #0 is not open. SBASIC will die naturally. If #0 is open, SBASIC will wait for a command.
- In case of error, if #0 is not open, a default window #0 will be opened for the error message.
- Likewise, if an operation is requested on a default channel (#0, #1 or #2) and neither the default channel nor #0 are open, a default window #0 will be opened for the operation.

SBASIC and Resident Extensions

Resident extensions linked into Job 0 (the initial SBASIC) are available to all SBASIC jobs. If extension procedures and functions are linked into other SBASIC Jobs (using `LRESPR`), they are local to those Jobs and will be removed when the Jobs die or are removed.

Note that, because of this feature, `LRESPR` cannot be used from a Job, other than Job 0, to load files which include system extensions (i.e. `MENU_REXT`, `QTYP` etc.).

SBASIC Executable Thing

The SBASIC executable Thing is called "SBASIC". The provision of an SBASIC executable Thing enables the diehard QDOS fanatic to go well beyond the facilities provided by the SBASIC and `EX` commands.

On being invoked, SBASIC expects to find some channel IDs and a string on the stack (standard QDOS conventions). Because, however, SBASIC requires some BASIC source code in order to be able to execute, the treatment these channel IDs and the string on the stack are slightly unconventional.

If SBASIC is invoked without any channel IDs on the stack, SBASIC will behave either as a normal SBASIC interpreter, with the standard set of windows, or as an interpreter with no windows initially opened.

- If the string on the stack is null, the standard set of windows is opened and SBASIC waits for a command. (This is what happens when you give an SBASIC command without parameters or when you start SBASIC from the QPAC2 EXEC menu without a command string.)
- If the string on the stack is not null, no windows are opened and the string is treated as a command line. (This is what happens when you start SBASIC from the QPAC2 EXEC menu after specifying a command string.)

If there are one or more channel IDs on the stack, SBASIC will normally treat the first ID as the SBASIC program source file, the next ID as channel #0, the next ID as channel #1 and so on. The string defines the initial value of the CMD\$ variable within the SBASIC program. (This is what happens when EX executes an SBASIC program.)

There is a special "trick" for setting up an SBASIC program with just window #0 open. The x,y coordinates of the top left hand corner of the required window #0 are complemented and put on the stack in place of a channel ID.

- If there is only one channel ID on the stack, and this is a "false" ID (i.e. the ID is negative), a 6 line by 42 column channel #0 is opened with the origin at NOT the MSW (x) and NOT the LSW (y) of the false ID. The string is treated as a command line. (This is what happens when you give a SBASIC command specifying the position of window #0.)
- If there are two channel IDs on the stack and the second is a "false" ID, first is used as the SBASIC program source file and the second ID is used to define window #0. The string defines the initial value of the CMD\$ variable. (This could be useful.)

The SBASIC Interface Things

Two interface Things are provided for the interface to the SBASIC extension which are compatible with two of the established executable program interfaces. The first is called "SBAS/QD" which provides a QD5 compatible F10 interface (Jochen Merz). The second is a "FileInfo" Thing (Wolfgang Lenerz) which recognises and executes files starting with `_sav` or `_bas`.

If QD (version 5 or later) is configured to use the SBAS/QD thing, then you can create (line numbered or unnumbered) SBASIC programs with QD and execute them by pressing F10 (SHIFT F5). QD may be temporarily configured to do this by executing it with the appropriate command string.

EX QD;'T SBAS/QD' Execute QD using SBAS/QD Thing

The FileInfo Thing is used by the QPAC2 Files Menu (amongst others) to determine how to "Execute" a file. With the default FileInfo Thing incorporated into SMSQ, files ending with `_sav` or `_bas` may be executed directly from the Files menu and any other utility program which uses the FileInfo Thing.

Terminate An SBASIC Program

QUIT

QUIT [value]

Terminates an SBASIC program. Please note that QUIT cannot terminate JOB 0, the main SBASIC interpreter.

The "Quit" keyword takes an optional parameter (long integer) that is passed to the calling job. For example, you could have two BASIC programs, the first calling the second with:

return_code = FEW (your_second_program)

Input Line Editing

The range of standard input line editing keystrokes is now much wider, and has been made consistent for INPUT, ED and the Window Manager. The move to start of word and delete start of word have been made reasonably intelligent and are particularly useful for editing filenames (QPAC2 Files) and SBASIC source (ED).

Key	With	Operation
←		move left one character
→		move right one character
TAB	SHIFT	move left eight characters
TAB		move right eight characters
←	SHIFT	move left one word
→	SHIFT	move right one word
←	ALT	move to start of line
→	ALT	move to end of line
←	CTRL	delete left one character
→	CTRL	delete right one character
←	CTRL SHIFT	delete left one word
→	CTRL SHIFT	delete right one word
←	CTRL ALT	delete to start of line
→	CTRL ALT	delete to end of line
↓	CTRL	delete whole line

Some keyboards have Delete and Backspace keys.

Bspace		delete left one character
Delete		delete right one character
Bspace	SHIFT	delete left one word
Delete	SHIFT	delete right one word
Bspace	ALT	delete to start of line
Delete	ALT	delete to end of line

Language Facilities

SMSQ/E incorporates several language variations and extra variations may be add "at run time".

Language Specification

A language may be specified either by an international dialling code or an international car registration code. These codes may be modified by the addition of a digit where a country has more than one language.

Language Code	Car Registration	Language and Country
33	F	French (in France)
44	GB	English (in England)
49	D	German (in Germany)
1	USA	USA (in USA)

Language Control Procedures

There is a set of procedures and functions which allow the language of the messages, the keyboard layout and the printer translate tables to be set. Where a language is to be specified, the parameter may be an integer value (the telephone dialing code), a string (the car registration letters) a variable or expression which yields an integer or string result, or a variable name.

It is not necessary for the car registration letters to be in upper case.

LANG_USE

The language of the messages is set by the LANG_USE lang command. This sets the OS language word, and then scans the language dependent module list selecting modules and filling in the message table.

LANG_USE 33	<i>set language to French</i>
LANG_USE D	<i>set language to German</i>
LANG_USE 'g'&'b'	<i>set language to English</i>

WARNING: if you assign a value to a variable, then you will not be able to use that variable name to specify the car registration letters.

D=33: LANG_USE D *set language to French (dialing code 33) rather than German (car registration D)*

LANGUAGE LANGUAGE\$

The LANGUAGE and LANGUAGE\$ functions are used to find the currently set language, or to find the language that would be used if a particular language were requested. They can also be used to convert the language (dialing code) into car registration and vice versa.

PRINT LANGUAGE *the current language*
PRINT LANGUAGE\$ *the car registration of the current language*
PRINT LANGUAGE (F) *the language corresponding to F*
PRINT LANGUAGE\$ (45) *the car registration corresponding to 45*
PRINT LANGUAGE (977) *the language that would be used for Nepal*

KBD_TABLE

The keyboard tables are selected by the KBD_TABLE lang command.

KBD_TABLE GB *keyboard table set to English*
KBD_TABLE 33 *keyboard table set to French*

Private keyboard tables may also be loaded.

i = RESPR (512): LBYTES "kt",i: KBD_TABLE i *keyboard table set to table in "kt"*

For compatibility with older drivers, a "private" keyboard table loaded in this way should not be prefaced by flag word.

TRA

The SBASIC TRA command differs very slightly in use from the QL JS and MG TRA. The differences are quite deliberate and have been made to avoid the unfortunate interactions between functions of setting the OS message table and setting the printer translate tables. If you only wish to set the printer translate tables, the only difference is that TRA 0 and TRA 1 merely activate and deactivate the translate. They do not smash the pointer to the translate tables if you have previously set it with a TRA address command.

If you wish to change the system message tables, then the best way is to introduce a new language: this is done by LRESPRing suitable message tables.

Language dependent printer translate tables are selected by the TRA 1,lang command. If no language code or car registration code is given, the currently defined language is used.

Language independent translate tables are set by the TRA n command where n is a small odd number. Private translate tables are set by the TRA addr command where addr is the address of a table with the special language code \$4AFB.

TRA 0 *translate off, table unchanged*
TRA 0, 44 *translate off, table set to English*
TRA 0, F *translate off, table set to French*

TRA 1 *translate on, table unchanged*
TRA 1, GB *translate on, table set to English*
TRA 1, 33 *translate on, table set to French*

TRA 3 *translate on, table set to IBM graphics*
TRA 5 *translate on, table set to GEM VDI*

A = RESPR (512): LBYTES "tratab",A: TRA A *translate on, table set to table in "tratab"*

To use the language independent tables, your printer should be set to USA (to ensure that you have all the # \$ @ [] { } \ | ^ ~ symbols which tend to go missing if you use one of the special country codes (thank you ANSI)), and select IBM graphics or GEM character codes as appropriate.

For the IBM tables, QDOS codes \$C0 to \$DF are passed through directly and QDOS codes \$E0 to \$EF are translated to \$B0 to \$BF to give you all the graphic characters in the range \$B0 to \$DF. QDOS codes \$F0 to \$FF are passed through directly to give access to the odd characters at the top of the IBM set. For the GEM tables, QDOS codes \$C0 to \$FF are passed through directly.

The Home Thing

The Home Thing implements "home directories". A home directory in this context is defined as meaning the directory from which an executable file was executed. A home filename is also supplied by the HOME thing, which is the combination of the filename and the home directory. Once set up, the home directory and home filename may not be changed (with the sole exception of the SBASIC interpreter, which can load BASIC programs from more than one location, or with different filenames).

The Home Thing also implements a "current directory". This is inherited from the job that is setting up the home directory (in most cases the parent job). If the calling job does not have a current directory, a copy of the home directory is used instead.

HOME_xxx Extensions

HOME_DIR\$

result\$ = HOME_DIR\$ [(job_id)]

This function returns the home directory for the job given as job_id. The job ID is optional, in that case -1, meaning the current job, will be assumed. To avoid programs stopping with an error if the home directory cannot be found for some reason, this function returns an empty string if that error happens.

result\$=HOME_DIR\$

return the Home Directory for the current job (job's own Home Directory)

result\$=HOME_DIR\$(-1)

return the Home Directory for the current job (job's own Home Directory)

result\$=HOME_DIR\$(JOBID('launchpad'))

returns the Home Directory for job called 'Launchpad', using the JOBID function to provide the job ID of 'Launchpad'

HOME_FILE\$

result\$ = HOME_FILE\$ [(job_id)]

This function returns the home filename for the job given as job_id. The job ID is optional, in that case -1, meaning the current job, will be assumed.

result\$=HOME_FILE\$

return the Home Filename for the current job

HOME_CURR\$

result\$ = HOME_CURR\$(job_id)

This function returns the current directory for the job given as job_id. The job ID is optional, in that case -1, meaning the current job, will be assumed.

result\$=HOME_CURR\$

return the Current Directory for the current job

HOME_DEF

HOME_DEF job_name\$, file_name\$

This sets a default filename for a job with the name given as first parameter. This is useful for "executable things", where no filename is readily available, or for file managers that haven't integrated calls to the home thing. With this keyword, you set up the default job name and filename that is to be used for the home/current file/dir.

Please note that the file_name\$ parameter must indeed be a FILENAME, not a directory name.

HOME_DEF "Sbasic", "dev1_sbasic_test_bas" *set default filename for Sbasic to dev1_sbasic_test_bas*

HOME_VER\$

Function to get the version number of the HOME thing.

result\$ = HOME_VER\$ *get the HOME thing version number into the string result\$*
PRINT HOME_VER\$ *display the version number of the HOME thing*

HOME_CSET

HOME_CSET [job_ID],directory\$

Set the current directory for the job indicated. The job ID is optional, in that case -1 (meaning the current job), will be assumed if no job_ID is given.

HOME_CSET 262148,'Win1_Launchpad_' *set Current Directory for job with ID of 262148 (\$00040004) to Win1_Launchpad_*

HOME_SET

HOME_SET job_id,device_directory_and_filename\$

Normally, jobs should not try to set up a home directory for themselves. This should be left to the system/filemanager. When a job is started with EX, EW or any of the similar commands, this is done automatically. However, filemanager writers may be interested in this information.

The HOME_SET command can be used to set the home directory, home filename and current directory. You pass the thing the job ID of the job for which this is to be set up and the entire filename, including the device and directory. The thing extracts the home directory from the filename. If you want to set up the home directory for the current job, you may pass -1 as parameter.

Since there can only be one home directory for a job and since that can only be defined once, the keyword will give an 'in use' error if the home directory is already set for this job. Otherwise, this keyword will set the home directory, the home file and the current directory.

This keyword exists mainly for testing purposes.

HOME_SET -1,'win1_dir_myprog_exe' *set job's own home directory, home file and current directory*

The Recent Thing

The Recent Thing maintains lists with the names of recently opened files so that you can find out what program recently opened files, and so that application programs may propose a list of the files the user recently opened :

- There is one general list, which contains the name of files recently opened, irrespective of the job which opened them.
- Then there is a list for each job that opened one or several files and which only contains the files opened by this job.

The RECENT Thing is an "extension thing" in the usual SMSQ/E meaning.

Various ways are provided to obtain the list(s) from the thing. There is an assembler interface to the thing and the extensions, and various SBASIC keywords that map onto the extensions.

Concepts

The RECENT Thing is called directly from the system's open file trap, without any user intervention. Whenever a file is opened, its name is added to the general list and to the job's list, and then becomes the first element of these lists.

There is no provision to delete files from the lists. However, since every list only has a finite size, when it is full and a new file is added to it, this will push the most ancient file off the list and the newest on it. There is also the possibility to remove an entire list for a job.

The system's open file call tries to filter out calls to open a directory, so that a directory open call does not cause the name of the directory to be added to the list. The same is true for the SAVE file. You can configure the size of the lists (i.e. how many files it should contain).

The lists

Each list is implemented as a LIFO (Last In First Out) buffer : the last (most recently) opened file will be the first in the list. There is one exception to this rule:

The thing makes sure that a file only exists once in a list. So it checks the general list and the job's list and, if it detects that a file is already in a list, it will not be put in again, NOR WILL IT MOVE TO THE FIRST POSITION.

There is one general list and as many job lists as there are jobs that opened files, or even more than that if lists were LOADED.

The general list is immediately adjacent to the thing itself. Its size is of: $rcnt_end + xx * rc_entryl$ bytes (see `dev8_keys_recent_thing` in the SMSQ/E sources) where `xx` is the number of files configured by the user. The general list always exists.

Job lists are in heaps, i.e. memory allocated on the common heap, one per job that opens a file. The memory is allocated for job 0 and doesn't go away when the job is removed. Heap size is: $rcnt_hdr + xx * rc_entryl$ bytes (see `dev8_keys_recent_thing` in SMSQ/E sources) again, `xx` is the number of files as configured by the user.

Job IDs

The primary way of identifying which list goes with which program is, of course, the job Id. Each list contains the ID of the job that opened it, and when the same job tries to open a new file, its name is added to the list of the job with the same Job ID. However, as a general rule, when trying to work with the RECENT Thing and it requires a Job ID, it is better to pass it a job name:

Over the course of a session, a user will typically launch several programs which will open a variety of files. Many of these programs will really be transient and will be removed from the system when they are done. (Note jobs started from Hotkeys are also created and removed, just as if they were loaded from disk). When a program is removed, its list stays in the system, for several reasons.

First it is to speed up the system - constantly removing and adding new lists (which are allocated on the common heap) would just slow the system down (see performance penalty, below).

Second, the information should be saved when the RECENT Thing lists are saved to disk, to be re-loaded in a later session.

Third, and most importantly, a mechanism is provided for jobs with the same name but different job Ids to use only one list.

Note that this scheme only works with jobs that keep the same name. QD, for example, changes its name when you load a file, and Xchange also changes its name sometimes. In that case, if the job must be found via a hash, it will not be possible to find the previous list.

The same problem also arises when LOADING the lists at boot time (or whenever): The lists are stored with the Job IDs as they were when the list was saved.

In a nutshell, when trying to use the RECENT Thing, it is better to pass it a job name rather than a Job ID. The mechanism to do that is explained below (see JobIDs and Name pointer for the INFO extension). It is important to understand that, if two jobs have the same name, they will be using the same list (e.g. several instances of SBASIC, unless you changed their name).

Buffers

Whenever a buffer is required, this means an area of memory starting at an even address. The thing does not check that the address is even, if it isn't, mayhem may ensue.

The Thing Interface In Assembler

See the QDOS / SMS Reference Manual, section 23.2.

SBASIC Keywords

The following keywords allow use of the Thing from SBASIC:

RCNT_INFO	A function to get some information on a list.
RCNT_JOBS	A function to get some info on the jobs the thing holds lists for.
RCNT_ADDF	A keyword to add a file to the list. Should not be used.
RCNT_GFFA\$	A function to get the first (=most recent) file name in the general list.
RCNT_GFFJ\$	A function to get the first (=most recent) file name in the list for a certain job.
RCNT_GALL	A function to get all filenames from the general list.
RCNT_GALJ	A function to get all filenames from the list for a certain job.
RCNT_GARR	A keyword to get all filenames from the general list into an array.
RCNT_GARJ	A keyword to get all filenames from the list for a certain job into an array.
RCNT_SAVE	A keyword to save the lists to a preconfigured file
RCNT_LOAD	A keyword to load the lists from a preconfigured file
RCNT_REMV	A keyword to remove a list from the thing.
RCNT_SYNC	A keyword to synchronize job ids with those in the lists.
RCNT_HASH\$	A function to get a hash from a string.

RCNT_INFO

length = RCNT_INFO ([job_id,] str_nbr%,str_len%,max_nbr%)

Get information on a list of files, where:

length = space needed for getting all strings, including length word

job_id = optional id of job the info is about

EITHER as a long int where

0 means get the general list,

-1 means get the list for myself (= default if omitted)

OR as a string with the name of the job

str_len% = RETURN parameter, max length of string

str_nbr% = RETURN parameter, number of strings currently held

max_nbr% = RETURN parameter, max number of strings in lists

This gets some information about the lists of files maintained by the thing, either the general list (job_id) = 0 or the list for a certain job. The Job ID may be passed as a long word, or, preferably, as a string with the entire name of the job.

On return the function returns the size for using the "RCNT_GALL" or "RCNT_GALJ" keywords. The size is the size necessary to store all strings + a length word for each string + a possible byte necessary to even out each individual string length.

The other three parameters are filled in on return of the function:

- The str_len% parameter contains the length of the longest filename currently being stored by the Recent list for this job, on in the general list. This length may vary, though, if a new file with a longer name is later opened. It will never exceed 41 characters, though.
- The number of files in the list, returned in the str_nbr% parameter, may also vary, if a new file is later opened.
- Finally, the max_nbr% is the maximum number of files a list may hold (as configured by the user).

RCNT_JOBS

result% = RCNT_JOBS (length,buffer)

Get a list of all jobs into a buffer:

length = length of buffer, in bytes

buffer = space for the list, preferably a space allocated with ALCHP

result% = 0 or +ive: number of jobs in the list

else negative error code (e.g. "buffer full" if the buffer was too small)

= -1 means get the list for myself (= default if omitted)

if there is an error, as much as possible is filled in the buffer

This gets a listing of all jobs for which the thing holds lists of files.

For each job, the listing in the buffer holds the Job ID in a long word followed by a standard string with the job name (which may be 0 if the job has no name).

The list is terminated by a long word of -1. If the buffer is too small to hold all job names, the buffer will be filled in as much as possible, and the error **err.buf1** will be returned.

There is no guarantee that any of the jobIDs returned are still valid : if the job with that ID has been removed, the jobID will no longer be valid.

The return in value holds the number of jobs in the buffer, unless it is a negative error code.

RCNT_ADDF

RCNT_ADDF [job_ID,] filename\$

adds a file name to the list

filename is the name of the file to add

job_id is the optional jobID of the job supposed to have opened the file
(defaults to -1, i.e. myself)

This adds a file to the list. **USE OF THIS KEYWORD IS STRONGLY DISCOURAGED.**

Normally, a program should not call this, the adding of file is handled by the system whenever a file is opened.

The JobID MUST be passed as a long word.

RCNT_GFFA\$

file\$ = RCNT_GFFA\$ ()

Returns the name of the first (i.e. most recently opened) file from the general list. If the list is empty, this will be a null length string.

RCNT_GFFJ\$

file\$ = RCNT_GFFJ\$ (job_ID)

Gets the name of the first (i.e. most recently opened) file for the job passed as parameter. If the parameter is omitted, it will default to -1, i.e. the current job. If the list is empty, the result will be a null length string.

RCNT_GALL

result% = RCNT_GALL (length,buffer)

Get ALL file names from the general list into a buffer.

length = length of buffer - this should be at least as much as that returned by the RCNT_INFO keyword

buffer = space for list

result% = 0 or +ive: number of files got if all went ok else negative error code:

err.bffl Buffer too small
err.ipar Wrong number of parameters
err.ijob Wrong job id
Any error from the thing use routine

If the error is err.bffl, as much as possible is filled in the buffer

This gets all filenames of the general list into a buffer. The filenames will be copied one after the other, the name of the most recently opened file being the first one to be copied. If the filenames don't all fit, as many as possible will be copied and the error "buffer full" is returned.

Filenames are typical SMSQ/E strings, with a length word in front and evened out to start at an even address. This might be used as follows:

```
str_len%=0
str_nbr%=0
str_max%=0
blength=RCNT_INFO(0,str_nbr%,str_len%,str_max%)      get info on size
buffer=ALCHP(blength)                               get buffer
result%=RCNT_GALL (blength,buffer)
```

Perhaps a better way to get the filenames for the basic programmer is the RCNT_GARR function.

RCNT_GALJ

result% = RCNT_GALJ ([jobID,] length, buffer)

Get ALL file names for a job into a buffer.

length = length of buffer - this should be at least as much as returned by the RCNT_INFO keyword for this jobs

buffer = space for list

job_id = (optional) id of job:

EITHER as a long int where -1 means get the list for myself (=default)

OR as a string with the name of the job

result% = 0 or +ive: number of files got if all went ok
else negative error code:
err.bffl buffer too small
err.ipar wrong number of parameters
err.ijob wrong Job ID
any error from the thing use routine

if the error is err.bffl, as much as possible is filled in the buffer

This gets all filenames of the list for a job into a buffer.

The filenames will be copied one after the other, the name of the most recently opened file being the first one to be copied. If the filenames do not all fit, as many as possible will be copied and the error "buffer full" is returned.

Filenames are typical SMSQ/E strings, with a length word in front and evened out to start at an even address.

This might be used as follows:

```
str_len%=0
str_nbr%=0
str_max%=0
blength=RCNT_INFO("Prowess",str_nbr%,str_len%,str_max%)
buffer=ALCHP(blength)
result%=RCNT_GALL (blength,buffer)
```

*get info on size
get buffer
data info buffer*

RCNT_GARR

RCNT_GARR array\$

Get all filenames from the general list into an ARRAY

array\$=a 2 dimensional string array.

This is similar to the GALL call, in that all, or as many as possible, filenames will be copied. Here however, they will be copied into what must be a two-dimensional string array (i.e. DIM a\$(xx,yy). If the filenames do not all fit, as many as possible will be copied, and no error is returned.

An error bad parameter will however be returned if:

- The array isn't a two-dimensional string array
- The second dimension of the array is too small for the longest element in the list.

Note that filenames will not be longer than 41 characters, so a DIM a\$(x,41) will guarantee that that error won't happen.

The first array element to be filled in will be element 0.

This might be used as follows:

```
str_len%=0
str_nbr%=0
blength=RCNT_INFO(0,str_nbr%,str_len%,str_max%)
DIM files$(str_nbr%,str_len%)
RCNT_GARR files$
```

*get info on size
or better DIM files\$(str_nbr%,41)*

RCNT_GARJ

RCNT_GARJ array\$

Get all filenames for a job into an ARRAY. Array\$ is a 2-dimensional string array. The array will be filled in starting at element 0.

This is similar to the GALJ call, in that all, or as many as possible, filenames will be copied. Here however, they will be copied into what must be a two-dimensional string array (i.e. DIM a\$(xx,yy). If the filenames don't all fit, as many as possible will be copied, and no error is returned.

An error bad parameter will however be returned if :

- The array isn't a two-dimensional string array
- The second dimension of the array is too small for the longest element in the list.

Note that filenames will not be longer than 41 characters, so a DIM a\$(x,41) will guarantee that that error won't happen.

The first array element to be filled in will be element 0.

This might be used as follows:

```
str_len%=0
str_nbr%=0
blength=RCNT_INFO("Prowess",str_nbr%,str_len%,str_max%)      get info on size
DIM files$(str_nbr%,str_len%)                                or better dim files$(str_nbr%,41)
RCNT_GARJ files$
```

RCNT_HASH\$

hash\$=RCNT_HASH\$(string\$)

Returns the hash from the string
string\$ = a normal string to turn into a hash

This returns the hash, as used by the RECENT Thing for job names, from the string passed as parameter. The hash algorithm used is a very simple one, the consideration was speed over anything else. So this hash is certainly very easy to break and probably not very collision proof....

That said, running it over an entire qxl.win file with about 10.000 files did not give any collision for any of the filenames.

RCNT_SAVE

RCNT_SAVE

SAVE lists to configured file : no parameters

This saves the lists for all jobs currently held in the thing, into the file configured by the user. The file is overwritten. You can't specify another file. The general list is NOT saved. The name of the SAVE file is NOT added to any list of files, not even the general one, when SAVEing or LOADING.

RCNT_LOAD

RCNT_LOAD

LOAD lists from configured file : no parameters.

This loads the lists as saved by the RCNT_SAVE extension. All lists existing in the thing, except for the general list, will be removed prior to loading. The file from which the lists are loaded is as configured by the user, you can not specify another file.

Thus, if you LOAD the lists as the very first thing in your boot file, they will also fill up with the files opened up during your normal boot.

If you LOAD the lists at the end of your boot file, they will replace all lists generated up to that time (except for the general list).

When SAVEing or LOADing, the name of the SAVE file is NOT added to any list of files, not even the general one.

It is possible to save the lists, re-configure SMSQ/E to use lists with a different size, and load the lists after a reboot with the newly configured SMSQ/E. In that case:

- If the new list size is smaller than the saved size, only some files will be copied to the new list. THERE IS NO GUARANTEE THAT THESE will include the newest files opened.
- If the list size is larger than the saved size, all filenames will be copied.

In the latter case, and also when the sizes stay the same between saving and loading, the order of the filenames will be preserved.

RCNT_REMV

RCNT_REMV [jobid]

REMoVe a list for a job. This removes the list for the job passed as parameter. If no such job exists, it returns an error.

RCNT_SYNC

RCNT_SYNC

Tries to give current Job IDs to jobs in heap

As explained above, the Job IDs stored in the RECENT Things may not correspond to the Job IDs of the jobs currently executing, for example after loading the lists. The SYNC runs through the list of all iobs currently executing in the system and if a list exists for a job with that name, it sets the Job ID of that list to that name.

Configuration

Using the usual standard config program, you can configure:

- Whether SMSQ/E should use the RECENT Thing at all. If not, neither the thing nor the SBASIC extensions for it will be initialised/usable.
- The size of the lists (i.e. how many files they should contain):
The maximum allowed size is 255. The minimum allowed size is 1.
The longer the list, the higher the performance penalty (see below).
All lists have the same size. The default list size is 20.
- The name of the SAVE file if you want to be able to save/load the lists between sessions.

Performance penalty

There is, of course, a performance penalty involved when opening files, since the RECENT Thing must be used and the lists searched through, but the time necessary to check and add the file to the list is small. As an indication, compiling all of SMSQ/E, under SMSQmulator, in a version of SMSQ/E 3.23 without the

RECENT Thing takes about 118 seconds. The same with the RECENT Thing takes about 125 seconds. This is with a list size of 250 files.

Under QPC, these were 58 seconds without the RECENT Thing and 63 seconds with the Recent thing.

Machine Type Functions

Two standard functions to determine the machine type are supplied. MACHINE returns a number (based on the value held in the system variable sys_mtyp at offset \$A7, decimal 167) which identifies the machine or emulator type. PROCESSOR returns a number (based on the value held in the system variable sys_ptyp at offset \$A1, decimal 161) which identifies the type of processor and if any floating point unit is available.

MACHINE

The MACHINE function returns the machine type.

0	Atari ST / STM / STF / STFM.
1	ditto, with blitter.
2	Mega ST (without blitter) or ST etc. with real-time clock.
3	Mega ST (with blitter) or ST etc. with RTC and blitter.
4	Stacy
6	Atari STE
8	Mega STE (without blitter!).
9	Mega STE.
10	Gold Card
11	Gold Card with Hermes
12	Super Gold Card
13	Super Gold Card with Hermes
16	Atari Falcon
17	Q40
20	SMSQmulator
24	TT 030
28	QXL
30	QPC
31	QLay emulator

PROCESSOR

The PROCESSOR function returns the 680x0 family member.

0	– 68000 or 68008
10	– 68010
20	– 68020
30	– 68030
40	– 68040
60	– 68060

IF MACHINE = 12 : PRINT "Super Gold Card fitted"
IF PROCESSOR = 60 : PRINT "I have a 68060 processor!"

Display Extensions

As of version 2.98 of SMSQ/E, the DISP_xxx command set has been extended to allow the colour depth to be specified. The DISP_COLOUR command follows the same principles as the other DISP_xxx commands. These commands may vary from hardware to hardware – please check the notes for the various hardware platforms.

DISP_xxx Keywords

DISP_BLANK

DISP_BLANK x blank [, y blank] sets the size of the blank area to the sides of and above and below the image for the QVME card on Atari only: it is ignored for all other Atari display cards and other hardware systems. If the blank is too small, you will lose some of your image, if it is too large, the image will be too small.

DISP_BLANK 128,64 *set horizontal blank to 128 pixels and vertical to 64 lines*

As the display size is altered, the blank is automatically adjusted to maintain the proportion of blank. The DISP_BLANK command will not usually be required.

If preferred, the parameters for the DISP_RATE and DISP_BLANK commands may be tacked on to the DISP_SIZE command.

DISP_SIZE 640,480,60 *set standard VGA*
DISP_SIZE 800,480,80 *set 80 Hz refresh rate, squashed VGA.*
DISP_SIZE 800,600,70,,128,60 *set all of size, frame scan rate and x and y blank*

Note that if you specify both frame and line rates, as well as the number of blank lines, the line rate is over-specified: it will be determined by the frame rate and the total number of lines (visible + blank) and the line rate will be ignored.

DISP_COLOUR

DISP_COLOUR colour depth

Specifies the colour depth to be used - 0 for QL, 2 for 8-bit, 3 for 16 bit (also 1 for 4 bit, and 4 for 24 bit - but these do not exist).

DISP_COLOUR 0 *QL mode display*
DISP_COLOUR 1 *16 colour (4-bit) display mode – not currently implemented*
DISP_COLOUR 2 *256 colour (8-bit) display mode, currently used on Aurora and QPC2*
DISP_COLOUR 3 *65,536 colour (16-bit) display mode*
DISP_COLOUR 4 *24-bit colour mode – not currently implemented*

It is possible to specify the display size immediately after the colour depth.

DISP_COLOUR 3, 800, 600 *specifies a 800x600 16 bit display*

Naturally, since the DISP_SIZE size definition can also be followed by the frame and line rates, the DISP_COLOUR definition can also specify the frame rate, the line rate and the x and y blank.

DISP_COLOUR colour depth [,xsize [,ysize [,framerate [,linerate [,xblank [,yblank]]]]]]]
DISP_SIZE xsize [,ysize [,framerate [,linerate [,xblank [,yblank]]]]]
DISP_RATE framerate [,linerate [,xblank [,yblank]]]
DISP_BLANK xblank [,yblank]

Any parameter can be left undefined, thus

DISP_SIZE , , 72, , , 30

specifies that the frame rate will be 72 Hz and the y (frame) blanking period will be 30 lines - leaving all the other parameters unchanged. Note that on most machines, most parameters will have no effect at all!

DISP_INVERSE

The DISP_INVERSE (0 or 1) command is used to invert the monochrome display from the normal (black background) to inverse (white background) state. On hardware with no monochrome display, this is ignored.

DISP_INVERSE 1 *Invert black and white*
DISP_INVERSE 0 *Restore normal*

DISP_RATE

DISP_RATE (frame rate, line rate) is used to specify the frame and line scan rates for the QVME card on the Atari ST only: it is ignored for all the other Atari display cards and other hardware. It would be usual to specify only the frame rate: the line rate is equal to the frame rate multiplied by the total number of lines.

DISP_RATE 75 *set the frame rate to 75 Hz*
DISP_RATE 70,48000 *set the frame rate to 70 Hz and line rate to 48 kHz (686 lines)*

DISP_SIZE

DISP_SIZE (xpixels, ylines) is used to set the display size. The nearest feasible size will be selected by the driver.

It is best not to change the display size when the pointer sprite is visible, or you may get some spurious blobs left on the display. There should be few other problems changing from a smaller size to a larger size. You should, however, avoid changing from a larger size to a smaller if there are any windows outside the smaller screen.

Note that, for the QVME card on Atari, the width and height are set in increments of 32 pixels and 8 lines respectively, while for the extended QL mode 4 card on Atari, any width of 512 or less will select the standard resolution mode while any width greater than 512 pixels will select the extended mode.

Certain hardware may only support specific display sizes, e.g. the Q40 and Q60 may only support 512x256 and 1024x512 pixels, while the Aurora card supports only a range of sizes in 4:3 and 2:1 aspect ratios.

DISP_SIZE 1 is a special form, which resets the a QL-sized 512x256 display, originally for use on the Atari extended Mode 4 emulator card.

DISP_SIZE 1024,768 *change to SVGA size on a PC*
DISP_SIZE 1024,512 *change to Q40/Q60 resolution display*
DISP_SIZE 800,600 *change to 800x600 (Atari QVME) or 768x280 (Atari extended mode 4)*
DISP_SIZE 1 *change to 512x256 (extended mode 4) (ignored by QVME)*

DISP_TYPE

The DISP_TYPE function is used to find the type of display. For standard QL style displays in MODE 4 (any resolution) DISP_TYPE returns 0. The value returned on other display systems may vary according to the hardware and colour depth. In general, on SMSQ/E versions supporting higher colour modes, and on Atari emulator cards, the following values may be returned.

- 0 – QL style display (MODE 4)
- 1 - Extended mode 4 emulator (standard and extended display sizes) on Atari.
- 2 - QVME mode 4 emulator on Atari.
- 3 - Aurora LCD
- 4 - Monochrome display on Atari.
- 5 - Aurora QL mode
- 8 – QL MODE 8 display
- 16 – 8-bit (256 colour) mode
- 32 – 16-bit colour mode on QPC, QXL and SMSQmulator
- 33 – 16-bit colour mode on Q40 and Q60
- 64 – 24-bit colour mode (no hardware supports this at the time of writing)

IF DISP_TYPE > 0 THEN PRINT"Not a standard QL display."
IF DISP_TYPE <> 8 : PRINT"Sorry, this game only runs in MODE 8."
IF DISP_TYPE = 4 THEN PRINT"Monochrome display."

REMark test how many colours this system can display
ncol = 4 : REMark assume 4 colours
dt = DISP_TYPE : REMark check display type
SElect ON dt
=0,1,2 : ncol=4 : REMark 4 colours
=4 : ncol = 2 : REMark monochrome on Atari
=8 : ncol = 8 : REMark 8 colours in MODE 8
=16 : ncol = 256 : REMark 256 colour mode

=32,33 : ncol = 65536 : REMark 16-bit colour modes 32 and 33
=64 : ncol = 2^24 : REMark 16,777,216 colours, 24-bit system
END SElect
PRINT "This system can display ";ncol;" colours."

Graphic Device Interface Version 2

This part describes the use of the extended colours introduced from version 2.98 of SMSQ/E

Limitations

The modifications limit the colour depth for normal colour stippled colour definitions to 16 bit. Plain colours are limited to 32 bits.

The modifications limit the colour depth for stippled borders to 8 bit. Plain border colours are limited to 16 bits.

The calls to specify the colours can only handle

- QL 8 (or 4 of 8) colour definition,
- 256 palette mapped colour definition,
- true colour (24 bit),
- native colour.

Sprites (patterns and blobs) can be handled in

- QL 8 (or 4 of 8) colour definition,
- 256 palette mapped colour definition,
- 256 grbgrbgm colour definition,
- native colour.

The operating system mode call does not change the display mode.

Extended Colour SBASIC Procedures.

All the normal SBASIC procedures that set or use colours can work with any of the three "standard" SBASIC colour definitions.

1. QL colour: a value from 0 to 7.
2. Palette mapped colour: a value from 0 to 255.
3. True colour: red (0-255) * 65536 + green (0-255) * 256 + blue (0-255).

They can also work with the "native" colour definition. Note that, for ease of programming, the true colour definition used in SBASIC is not the same as used for the device driver interface.

The BGCLOUR_xx, BGIMAGE, COLOUR_xx and PALETTE_xx procedures described below all require a valid window channel ID. The default is the same as PRINT: #1 or #0 for mini SBASICs that have only #0 open.

Wallpaper

A plain or stippled background can be defined using either QL colours or true colours.

BGCLOUR_QL

BGCLOUR_QL QL colour

sets the background to the QL colour (0-255).

BGCLOUR_24

BGCLOUR_24 full colour

sets the background colour to the plain true colour.

100 BGCLOUR_QL 255 *set background to black / white check*
110 BGCLOUR_QL 0,7 *set background to black / white check*

120 BGCOLOR_QL 0,7,3 *set background to black / white check*
130 BGCOLOR_24 40 *set the background to deep blue*

You can get stippled extended colours by cheating. Set two of the QL palette entries (see below) to the colours you require before calling BGCOLOR_QL.

BGIMAGE

BGIMAGE filename

loads a background image from file.

150 BGIMAGE win1_wallpaper *load my wallpaper*

Background images must be in the form of a screen snapshot. It is relatively simple to create background images.

500 WINDOW SCR_XLIM, SCR_YLIM, 0, 0 : REMark whole screen window

510 ... draw the wallpaper on the screen

520 SBYTES_0 win1_wallpaper, SCR_BASE, SCR_LLEN * SCR_YSIZE

Palette Maps

The colours used to display the QL colours 0 to 7 are not necessarily the boring old black, blue, red, magenta, green, cyan, yellow and white. They can be set to other colours if you wish. The palette mapped colours can also be changed although they have been pre-defined to put the most useful colours first.

PALETTE_QL

PALETTE_QL start, true colour 1, true colour 2, ...

sets QL palette entries starting with the start entry.

PALETTE_8

PALETTE_8 start, true colour 1, true colour 2, ...

sets 256 colour (8 bit) palette entries starting with the start entry.

On hardware that does not have a true palette map, palette map changes do not affect the information already drawn on screen.

There is a practical reason for changing the QL palette map entries. Many programs define some of the colours displayed as "white-colour" on a 4 colour QL display, white-red appears as green. White-red, however, is really cyan, not green. As a result, many QL mode 4 programs take on rainbow hues when displayed on a 256, 65536 or full colour display.

This can be "fixed" by redefining the colours so that colour 2 is a bright crimson and colour 4 is a bright sea green. This will ensure that colour 2 + colour 4 = colour 7. We also need to ensure that colour 0 = colour 1, colour 2 = colour 3, etc.

600 crimson = 255 * 65536 + 100

crimson is red + a bit of blue

610 sea = 255 * 256 + 155

sea green is green + rest of blue

620 white = crimson + sea

630 PALETTE_QL 0, 0, 0, crimson, crimson, sea, sea, white, white *set 8 colours*

The following program can be used to display the current 256 colour palette using the up and down arrow keys. If new colours are required, they should replace colours towards the top of the table so that the low colours remain unchanged. You change palette entry 0 at your own risk.

100 OPEN #0,con: out = 0

110 WINDOW #out, 16*10+2,16*10+2,50,50

120 COLOUR_PAL: BORDER #out,1,0,1

```

130 bottom=-16
140 FOR i = 1 TO 16: up
150 REPEAT
160 BGET #0,a
170 IF a=$D0: IF bottom < 255-16: up
180 IF a=$D8: IF bottom > 0: down
190 END REPEAT
200 :
210 DEFINE PROCEDURE up
220 bottom = bottom+1
230 PAPER bottom+15 : SCROLL -10
240 I = bottom+1015 : I$ = I
250 PAPER #out, I&&1 : INK #out, (I+1)&&1
260 AT #out, 15,0 : PRINT #out; I$(2 TO 4);
270 END DEFINE
280 :
290 DEFINE PROCEDURE down
300 bottom = bottom-1
310 PAPER bottom : SCROLL 10
320 I = bottom+1000 : I$ = I
330 PAPER #out, I&&1 : INK #out, (I+1)&&1
340 AT #out, 0,0 : PRINT #out; I$(2 TO 4);
350 END DEFINE

```

SBASIC Colour Definition Selection

SBASIC has a new set of procedures for selecting colour definition used by INK, PAPER, STRIP, BORDER, BLOCK.

COLOUR_QL

selects the standard QL colour definitions (the QL colours can be mapped to colours other than the standard black, blue, red, magenta, green, cyan, yellow and white).

COLOUR_PAL

selects the 256 colour palette mapped definition.

COLOUR_24

selects the true colour (24 bit) definition.

COLOUR_NATIVE

selects the native colour definition - the significance of the colour numbers specified by INK, PAPER, etc. depends on the hardware.

```

200 COLOUR_24 select true colour mode
210 BORDER 2, 128*65536 + 128*256 +128 grey border
220 BORDER 2,$808080 grey border for hexadecimal hackers

```

The commands have no effect on any other programs executing. When an SBASIC program starts executing, it is set to QL colour definition.

Alpha Blending

ALPHA_BLEND

Alpha Blending is the process of combining a translucent foreground colour, with a background colour, thereby producing a new blended colour. The degree of the foreground colour's translucency may range from

completely transparent to completely opaque. It takes two parameters, a channel and an alpha weight from 0 to 255 with 0 being transparent and 255 being opaque.

So, after executing for example ALPHA_BLEND #1,128 all future graphics commands on channel 1 including BLOCK, CIRCLE, LINE and PRINT will draw their contents half-transparent over the existing background until alpha blending is disabled again (by setting the weight to the default of 255: ALPHA_BLEND #1,255).

100 PAPER 0 : CLS	
110 ALPHA_BLEND 128	<i>half-transparent</i>
120 FILL 1 : INK 2 : CIRCLE 40,50,20	<i>overlapping circles</i>
130 FILL 1 : INK 4 : CIRCLE 65,50,20	
140 FILL 1 : INK 1 : CIRCLE 50,75,20	
150 CSIZE 2,0 : AT 10,4	
160 PRINT "Alpha blending!"	<i>superimpose some text</i>
170 ALPHA_BLEND 255	<i>back to normal</i>

The System Palette and Window Manager 2

Colours List

The new Window Manager introduced by SMSQ/E v3.00 maintains a table of colour settings for programs to use as "standard colours". This is called the System Palette, also known as a 'colour theme'. Four system palette tables, or themes, are currently supplied with the operating system and more may be designed using software such as Wolfgang Uhlig's Q-CoCo (Colour Configurator) program.

The list includes colour values to be used for display items such as window background, border, loose items and so on. The items are referenced by a 4-digit hex number (16-bit value) as per the list below, or the decimal number equivalent. These numbers should not be used in standard INK, PAPER and BORDER statements – they are not colour values, merely an index to an entry in a list of colour values. They should be used with the WM_x equivalent commands below, which will look up the colour values to be used for the item numbers in the list.

Number	Meaning
\$0200	Window border
\$0201	Window background
\$0202	Window foreground
\$0203	Window middleground
\$0204	Title background
\$0205	Title text background
\$0206	Title foreground
\$0207	Loose item highlight
\$0208	Loose item available background
\$0209	Loose item available foreground
\$020a	Loose item selected background
\$020b	Loose item selected foreground
\$020c	Loose item unavailable background
\$020d	Loose item unavailable foreground
\$020e	Information window border
\$020f	Information window background
\$0210	Information window foreground
\$0211	Information window middleground
\$0212	Subsidiary information window border
\$0213	Subsidiary information window background
\$0214	Subsidiary information window foreground
\$0215	Subsidiary information window middleground
\$0216	Application window border
\$0217	Application window background
\$0218	Application window foreground
\$0219	Application window middleground

\$021a	Application window item highlight
\$021b	Application window item available background
\$021c	Application window item available foreground
\$021d	Application window item selected background
\$021e	Application window item selected foreground
\$021f	Application window item unavailable background
\$0220	Application window item unavailable foreground
\$0221	Pan/scroll bar
\$0222	Pan/scroll bar section
\$0223	Pan/scroll bar arrow
\$0224	Button highlight
\$0225	Button border
\$0226	Button background
\$0227	Button foreground
\$0228	Hint border
\$0229	Hint background
\$022a	Hint foreground
\$022b	Hint middleground
\$022c	Error message background
\$022d	Error message foreground
\$022e	Error message middleground
\$022f	Shaded area
\$0230	Dark 3D border shade
\$0231	Light 3D border shade
\$0232	Vertical area fill
\$0233	Subtitle background
\$0234	Subtitle text background
\$0235	Subtitle foreground
\$0236	Menu index background
\$0237	Menu index foreground
\$0238	Separator lines etc.

Colour Commands

The WM_xxx commands allow access to the System Palette colours. They take a 4 digit hexadecimal colour value for the item in question from the table above. The parameters to these commands are otherwise exactly the same as for the “normal” commands as their corresponding command names without the WM_ prefix (INK, PAPER, BORDER, STRIP, BLOCK). The channel number is optional. If the command is to be compiled using a compiler which does not allow the \$number notation, please use the HEX function instead.

WM_INK

Sets the ink colour for the channel indicated to the colour for the specified item number from the table above.

WM_INK #0,\$0210	<i>set channel 0 ink colour to information window foreground ink colour specified in the System Palette</i>
WM_INK #2,HEX('0202')	<i>set channel 2 ink colour to main window foreground ink colour specified in the System Palette</i>
WM_INK \$0218	<i>set default channel (1) ink colour to application window foreground ink colour specified in the System Palette</i>

WM_PAPER

Sets the paper colour for the channel indicated to the colour for the specified item number from the table above. WM_PAPER also sets the STRIP colour as is the case with the normal PAPER command. But there is also the WM_STRIP colour command to set the strip colour only.

WM_PAPER #2,\$020F	<i>set the paper colour for channel 2 to the information window background colour specified in the System Palette</i>
---------------------------	--

WM_STRIP

Sets the strip colour for the channel indicated to the colour for the specified item number from the table above.

WM_STRIP #ch,\$0203 *set the strip colour for channel ch to the window middleground colour specified in the System Palette.*

WM_BORDER

Sets the border colour for the channel indicated to the colour for the specified item number from the table above.

WM_BORDER #0,\$0200 *set the border colour for channel 0 to the main window border colour specified in the System Palette.*

WM_BLOCK

Draw a block in the channel indicated in the colour for the specified item number from the table above.

WM_BLOCK #1,100,40,0,0,\$0201 *draw a 100x40 block of colour at 0,0 in the window background colour*

System and Job Palette Handling

There are commands to set/get the system palette and commands to set/get the "per job" palettes.

a - System palette keywords:

SP_RESET

SP_RESET [#channel] [,number]

This resets the colour palette given in number to the original values (as configured). Default is number 0.

SP_GETCOUNT

result% = SP_GETCOUNT

Gets the number of elements contained in a system palette. Each system palette, of course, has the same number of elements.

SP_GET

SP_GET [number,] address, first, count

This gets the colours from a system palette and puts them somewhere. The optional "number" parameter tells us which system palette we want (0 to 3, default = 0). "address" is the address of the space for the information, "first" is the number of the first system palette colour to get (starting from 0) and "count" is the number of colours to get.

The space pointed to by "address" MUST have enough space for the number of colours! This is NOT checked by the keyword and it is the programmer's responsibility to make sure that this is so.

As an example, you could use the following code to get ALL of the colours of a system palette:

```
totcol%= SP_GETCOUNT            get number of colours in system palette
address= ALCHP(totcol%*2)+4       enough space for colours + security
first=0
SP_GET #1,0,address,first,totcol%
```

SP_SET

SP_SET [#channel,] [number,] address, first, count

Sets the system palette entries, the address pointing to a space containing the colours. The parameters are similar to those for SP_GET.

b - Job palette keywords

SP_JOBPAL

SP_JOBPAL [#channel], jobID/Job_name, number

Set the system palette for the job given to the number. The job is given either as a string or as a standard Job ID number.

SP_JOBOWNPAL

SP_JOBOWNPAL [#channel],jobID/Job_name, pal_pointer

Set the job palette to the palette given in pal_pointer. Of course, the palette must have the format of a standard system palette.

Window Move

As of version 3.01 of SMSQ/E, new ways of moving a window about the screen have been added.

There are now three ways a window be moved:

0 - the old way - the pointer changes to the "move window" sprite which is moved about the screen.

1 - "Outline": click on the move icon with the MOUSE - KEEP HOLDING THE BUTTON DOWN, an outline of the window appears which you can move around and position where you want it. Release the mouse button and the window positions itself correctly. Please note that you cannot use this move mode with anything but the mouse – the keyboard (cursor keys) will not work.

2 - "Full window". This is the same as 1 above, but instead of an outline, the entire window is moved. For Q40/Q60 users, switching on the Cache is advisable... Please note that you cannot use this move mode with anything but the mouse – the keyboard (cursor keys) will not work.

3 - "Full window with transparency" (implemented in SMSQ/E v. 3.16). This is the same as 2 above, but the window to be moved is made "transparent" : one can "see through" it. This is done via "alpha blending". Alpha blending requires A LOT of computing power. So, even if your machine can theoretically handle this type of move, in practice it might not be feasible. For Q40/Q60 users, switching on the Cache is advisable...

This type of move is only implemented for display modes where alpha blending actually makes sense, i.e. modes 16, 32 and 33. In other display modes, such as the QL screen modes, or Atari mono modes, this will be redirected to move mode 2.

Please note that you cannot use this move mode with anything but the mouse – the keyboard (cursor keys) will not work.

The move modes are configured on a system-wide basis - you cannot have one job moving in mode 0 and the other in mode 1.

Thus, all jobs are affected by the move mode, even those written a long time ago (unless, such as Qlib, the job doesn't use the WMAN move routine).

The move mode can be changed in two ways:

1. Configure SMSQ/E (WMAN) to a mode of your liking.
2. Use the new WM_MOVEMODE keyword

WM_MOVEMODE

This takes one parameter, an integer from 0 to 2:

WM_MOVEMODE 0	<i>the old way, using the "move window" sprite</i>
WM_MOVEMODE 1	<i>the "outline" move</i>
WM_MOVEMODE 2	<i>the "full window" move</i>
WM_MOVEMODE 3	<i>the "full window with transparency" move</i>

The degree of transparency can be set with the keyword WM_MOVEALPHA. This defines the amount of transparency the window should have when moved about, from 1 (nearly transparent) to 255 (totally opaque). A value of 0 is allowed, but this would make the window completely transparent and you could only see the background, so a value of 255 will actually be used. Note that no check is made on the value of this keyword – only the lower byte is used.

WM_MOVEALPHA 1	<i>window move is almost completely transparent</i>
WM_MOVEALPHA 128	<i>window move is half way between transparent and opaque</i>
WM_MOVEALPHA 255	<i>window move is opaque</i>

Background drawing

PE_BGON PE_BGOFF

Even when a window is partially covered, printing into this window continues. This goes with two new BASIC commands: PE_BGON to turn this feature on, PE_BGOFF to turn this feature off. By default, this feature is TURNED OFF, so use the PE_BGON command in your boot file if you want to keep it on.

PE_BGOFF	<i>turn off background window drawing</i>
PE_BGON	<i>turn on background window drawing</i>

Cursor Extensions

From version 3.06 onwards, SMSQ/E allows you to use a sprite for a cursor. The sprite to be used as a cursor:

- MUST be of size 6x10 (WxH), else it will not be used.
- MUST be the one set at position 36 in the system sprites
- MUST be showable in the current screen resolution

If any of the above conditions is not met, then the normal cursor is shown.

How to load a cursor sprite

CURSPRLOAD

CURSPRLOAD "filename"

This loads "filename" and uses it as a cursor sprite. Please make sure that this file only contains the sprite data for a valid cursor sprite. The command does NOT check this. If this command seems to fail, i.e. the cursor sprite doesn't change to what you want it to be, the data contained in this file is perhaps not a valid cursor sprite for the current screen resolution.

How to use a sprite as cursor.

On a system-wide basis:

Configure your system. As of version 3.06 of SMSQ/E, a new configuration item lets you configure whether you want to use sprites as cursor or not.

On a per job basis

Independently of your system-wide configuration, you may switch the use of a sprite to be used for the cursor on a per job basis.

CURSPRON CURSPROFF

The keywords CURSPRON and CURSPROFF may be used to switch using the sprite cursor on/off.

CURSPRON job_name or job_number, job_tag
CURSPROFF job_name or job_number, job_tag

Example: Let us suppose you have Xchange running on your machine. Typing 'jobs' will tell you more about this job, something like this:

Job	Tag	Owner	Priority	Job-Name
9	8	0	8	Xchange V3.90J

You can now use:

CURSPRON "Xchange V3.90J" **Turn sprite cursor on for Xchange 3.90J**
CURSPROFF 9,8 **Turn sprite cursor off for job with job number 9 and job tag 8**

Load A Sprite And Set As System Sprite Number

SYSSPRLOAD

SYSSPRLOAD system_sprite_number,file_name\$

load the file and sets it as the system sprite with the given number.

This file must contain the sprite data for a valid sprite. The command does NOT check this. If this command seems to fail, i.e. the corresponding system sprite doesn't change to what you want it to be, the data contained in this file is probably not a valid sprite for the current screen resolution.

Common keyboard driver

The keyboard drivers have been rationalised. This means that some special keystrokes may have moved on some versions and some "special features" have disappeared.

Pause / break on IBM keyboards has been made equivalent to Undo on the Atari keyboards (it is in the same place).

NUMLOCK on IBM keyboards has no effect - the keypad is always a keypad!

Special actions

SCROLL LOCK (IBM)	freeze screen
CTRL F5	freeze screen
CTRL SCROLL LOCK (QXL)	freeze QXL PC communications
CTRL SPACE	break
CTRL BREAK (IBM)	break
CTRL UNDO (Atari)	break
CTRL SHIFT ALT TAB	soft reset (restarts current SMSQ)
CTRL SHIFT ALT BREAK (IBM)	hard reset (restarts host system)
CTRL SHIFT ALT UNDO (Atari)	hard reset (restarts host system)

CTRL-C Action

A new job switching behaviour has been introduced. Instead of the bottom-most window being picked to the top when you press CTRL-C (original behaviour on QDOS and older versions of SMSQ/E), the window just below the one you've currently worked with will be picked. This is more logical behaviour as the window at the bottom of the pile is often at that place for a good reason: you just don't currently need it.

Then, if you keep CTRL pressed down and tap C again, the picker will work its way towards the bottom of the pile of windows. But if you release CTRL, then press CTRL-C again, the game will start again at the top. When you get used to it, the new behaviour becomes easier and more logical. If you can't get used to it, disable it using MenuConfig (dependent on implementation in a given version of SMSQ/E).

SERIAL IO Devices

The range and number of serial IO devices depends on the hardware on which SMSQ/E is being used. The interface to these devices is kept consistent.

SMSQ/E has serial (SER) and parallel (PAR) port drivers which are just about recognisable as great-great-grandchildren of the QL SER driver. Output sent to any serial or parallel port can be buffered dynamically (that is the output buffer is allocated automatically and expanded as required. In addition, several channels may be open to one output port at any time: the data is buffered and will be sent to the port in the order in which the channels are opened.

Any serial or parallel port can be referred to using the pseudonym PRT (printer) and for compatibility with ancient software, PAR ports can be referred to as SER and vice versa. The PRT_ABORT, PRT_BUFF and PRT_CLEAR commands are included for compatibility.

Serial and Parallel Port Names

The serial and parallel ports are accessed through devices called SER, SRX, STX or PAR with a variety of optional characters following the name.

SER n p f t c e	Serial Port receive and transmit
SRX n p f t c e	Serial Port receive only
STX n p f t c e	Serial Port transmit only
PAR n t c e	Parallel Port (transmit only)
PRT	Printer Port (either SER or PAR)

Parameter	Characteristic	Possible Values	Meaning
n	port number	1, 2, 3 or 4	
p	parity	O E M S	7 bit + odd parity 7 bit + even parity 7 bit + mark=1 7 bit + space=0 default is none
f	flow control	H I X	Hardware CTS/DTR Ignore flow control XON/XOFF default is H
t	translate	D T	Direct output Translate default is use TRA setting
c	<CR>	R C A	Raw, no effect <CR> is end of line <CR><LF> is end of line <CR><FF> is end of page default is R
e	end of file	F Z	<FF> at end of file CTRL Z at end of file default none

Usually the only options that will be required are the "F" for form feed, the "D" and "T" options for character translation and the "C" or "A" option for daisywheel printers. If you are only going to use the SER port for output, it is better to use the STX name as this will enable the serial input port to be used by another program.

**OPEN_IN #3, SRX2X
COPY myfile TO PARF**

**OPEN a channel to the serial port 2 receiver with XON/XOFF
COPY myfile to parallel port and put a form feed at the end**

Serial Port Control

In general, the serial port control commands require a port to be specified. If no port number is given, SER1 is assumed.

Standard BAUD Command

BAUD

The effect of the standard BAUD command depends on the history of the hardware.

For the QL based versions, the baud rate is applied to both SER1 and SER2 as, historically, the baud rates for the two ports were generated by the same hardware.

For the QXL, the standard BAUD command mimics the QL BAUD command.

For the Atari ST series, the baud rate only applies to SER1, which, historically, was the only port available.

BAUD 4800	<i>Set SER1 and SER2 to 4800 baud</i>	<i>Gold Card / QXL</i>
	<i>Set SER1 to 4800 baud</i>	<i>Atari ST / TT</i>

Extended BAUD Command

Both the SuperBASIC BAUD command and the OS baud trap have been extended to support independent baud rates for each serial port. The baud rates are now calculated, which allows the use of non standard rates where this is supported by the serial controller chip. The rate must, however, be a multiple of 10. If the baud rate is specified as zero, the highest baud rate available is used.

BAUD 1,19200	<i>Set SER1 to 19200 baud</i>
BAUD 2,0	<i>Set SER2 to 153600 baud</i>

SER_FLOW

SER_FLOW (port number, H, X or I) specifies the flow control for the port: "Hardware", "XON/XOFF" or "Ignored". It usually takes effect immediately. If, however, the current flow is "Hardware" and handshake line CTS is negated and there is a byte waiting to be transmitted, the change will not take effect until either the handshake is asserted, or there is an output operation to that port.

The default flow control is hardware unless the port does not have any handshake connections, in which case XON/XOFF is the default.

The flow control for a port is reset if a channel is opened to that port with a specific handshaking (H, X or I) option.

SER_FLOW X	<i>XON/XOFF on SER1</i>
SER_FLOW 2,H	<i>Hardware (default) handshaking on SER2</i>

SER_ROOM

SER_ROOM (port number, spare room) specifies the minimum level for the spare room in the input buffer. When the input buffer is filled beyond this level, the handshake (hardware or XOFF as specified by SER_FLOW) is negated to stop the flow of data into the port. Some spare room is required to handle overruns (not all operating systems can respond as quickly as SMSQ). For hardware handshaking, a few spare bytes are all that is required. For connection to a dinosaur using XON/XOFF handshaking, up to 1000 spare bytes may be required.

SER_FLOW 2,X: SER_ROOM 2,1000	<i>connect SER2 to a UNIX system</i>
SER_FLOW 1,H: SER_ROOM 1,4	<i>hardware handshaking on SER1</i>

SER_ROOM will not usually be required as SER_BUFF (see below) also sets SER_ROOM to one quarter of the buffer size. You will not succeed in setting SER_ROOM to greater than SER_BUFF, however, as SER_ROOM will always ensure that the buffer is at least twice the size of the spare room.

SER_BUFF

SER_BUFF (port number, output buffer ,input buffer) specifies the output buffer size and, optionally, the input buffer size. The output buffer should be at least 5 bytes to avoid confusion with the port number. If the output buffer is specified as zero length, a dynamic buffer is used.

SER_BUFF 200 *200 byte output buffer on SER1*
SER_BUFF 4,0,80 *dynamic output buffer, 80 byte input buffer on SER4*

SER_CLEAR SER_ABORT

SER_CLEAR (port number) and SER_ABORT (port number) clear the output buffers of any closed channels to the port. Channel still open are not affected. SER_ABORT also sends the "ABORTED" message to the port.

SER_ABORT 3 *abort output to SER3*

SER_CDEOF

SER_CDEOF (port number, ticks to eof) specifies a timeout from CD being negated to the channel returning an end of file. The timeout should be at least 5 ticks to avoid confusion with the port number. If the timeout is zero, CD is ignored. This command is ignored on the QXL and QL.

SER_USE

SER_USE (name) specifies a name for the serial ports. The name can be SER or PAR. SER_USE is provided for compatibility, its use is not recommended.

SER_USE PAR *From now on, when you open PAR, you open a serial port*
SER_USE SER *Sets you back to normal*
SER_USE *. . . as does this*

Parallel Port Control

There are no implementations with more than one parallel port. Software writer should not assume that this will always be true. In general, the parallel port control commands allow a port to be specified in the same way as the serial port commands.

PAR_BUFF

PAR_BUFF (port number, output buffer) specifies the output buffer size. The output buffer should be at least 5 bytes to avoid confusion with the port number. If the output buffer is specified as zero length, a dynamic buffer is used.

PAR_BUFF 200 *200 byte output buffer on PAR*
PAR_BUFF 0 *dynamic output buffer on PAR*

PAR_CLEAR PAR_ABORT

PAR_CLEAR (port number) and PAR_ABORT (port number) clear the output buffers of any closed channels to the port. Channel still open are not affected. PAR_ABORT also sends the "ABORTED" message to the port.

PAR_ABORT *abort output to PAR*

PAR_USE

PAR_USE (name) specifies a name for the parallel ports. The name can be SER or PAR. PAR_USE is provided for compatibility, its use is not recommended.

PAR_USE SER *From now on, when you open SER, you open a parallel port*
PAR_USE PAR *Sets you back to normal*
PAR_USE *. . . as does this*

PRT_USE

The PRT_USE (port name) command differs from the implementation in the old QJUMP RAMPRT operating system extension included in QRAM and the GOLD card and QXL card software. As all output ports incorporate dynamic buffering so an "add-on" printer buffer is not required.

The SMSQ/E version of PRT_USE is identical to that of the Atari ST drivers for QDOS. It merely specifies which port will be opened if you open the device PRT.

PRT_USE PAR
COPY fred to PRT *COPY fred to PAR*
PRT_USE SER4XA
OPEN #5,PRT *OPEN a channel to SER4 with XON/XOFF and <CR><LF>*

Virtual Devices

Virtual devices are not associated with any physical hardware. NUL devices are complete dummy (very useful for benchmarking: SMSQ/E has one of the fastest, if not the fastest, fully functional NUL device in the world). PIPEs and HISTORY devices are buffers for storing information or passing it from one task to another. The PIPE is double ended: what goes in one end, comes out the other in the same order (FIFO - first in first out). The HISTORY device is single ended, what goes in one end, comes out the same end in the reverse order (LIFO - last in first out).

NUL Device

The NUL device may be used in place of a real device. The NUL device is usually used to throw away unwanted output. It may, however, be used to provide dummy input or to force a job to wait forever. There are five variations.

NULP waits (forever or until the specified timeout) on any input or output operation.

NUL, **NULF**, **NULZ** and **NULL** ignore all operations (the output is thrown away).

NUL, **NULF**, **NULZ** and **NULL** return a zero size window in response to window information requests. Pointer Information calls (IOP.PINF, IOP.RPTR) return an invalid parameter error.

NUL is an output only device, all input operations return an invalid parameter error.

NULF emulates a null file. Any attempt to read data from NULF will return an End of File Error as will any file positioning operation. Reading the file header will return 14 bytes of zero (no length, no type).

NULZ emulates a file filled with zeros. The file position can be set to anywhere. Reading the file header will return 14 bytes of zero (no length, no type).

NULL emulates a file filled with null lines. The file appears to be full of the newline character (10). The file position may be set to anywhere. Reading the file header will return 14 bytes of zero (no length, no type).

PIPE Device

There are two variations on the PIPE driver: named and unnamed pipes. Both of these are used to pass data from one program to another. Unnamed pipes cannot be opened with the SBASIC OPEN commands but are opened automatically by the EX and EW commands when these are required to set up a "production line" of Jobs. Whereas, if a pipe is identified by a name, any number of Jobs (including SBASIC) can open channels to it as either inputs or outputs.

If, using named pipes, matters become confused, then that is a problem to be solved by the Jobs themselves. This is not as bad as it sounds. Unlike other devices, named pipes transfer multiple byte strings atomically unless the pipe allocated is too short to hold the messages. This means that provided the messages are shorter than the pipe, many jobs can put messages into a named pipe and many jobs can take messages out of a named pipe without the messages themselves becoming scrambled.

If a PIPE is shared in this way, there are two simple ways of ensuring that the messages are atomic. The first, using fixed length messages, is not available to SBASIC programs. The second, using "lines" terminated by the newline character, works perfectly. N.B. the standard PRINT command will not necessarily send a line as a single string for each item output.

PRINT #3,a\$ \ b\$	<i>Bad, sends 4 strings: the newline characters are separate</i>
PRINT #3,a\$ & CHR\$ (10);	<i>Good, sends 1 string, including the newline</i>
INPUT #4,b\$	<i>Good, reads a single line from the pipe</i>

Named pipes should be opened with OPEN_NEW (FOP_NEW) for output and OPEN_IN (FOP_IN) for input. A named pipe is created when there is an open call for a named pipe which does not exist. It goes away when there are no longer any channels open to it and it has been emptied. As well as the name, it is possible to specify a length for a named pipe. If the pipe already exists, the length requested is ignored.

OPEN_NEW #4, PIPE_xp1	<i>Open named output pipe of default length (1024 bytes)</i>
OPEN_NEW #5, PIPE_frd_2048	<i>Open named output pipe of length 2048 bytes</i>
OPEN_IN #6, PIPE_xfr	<i>Open named input pipe</i>

HISTORY Device

A HISTORY device is much simpler than a PIPE as it only has one end. It is used to store a number of messages which may then be retrieved in reverse order: if it becomes full, the oldest messages are thrown away. The messages are separated by newline characters.

There are two types of history devices: private and public. Private HISTORY devices are for use within a particular application and may only have one channel open to them. Public HISTORY devices are named and so may be accessed by many applications at the same time, or at different times. A public HISTORY device may even be used as a "mailbox".

A HISTORY device is opened by name, just like any other device. The name starts with "HISTORY" which is, for a public HISTORY device, followed by public name and then, optionally, the HISTORY device size. If no size is given, 1 kilobyte of message space is assumed. If a public HISTORY device already exists, then the size is ignored!

HISTORY	<i>A private HISTORY, 1024 bytes total space</i>
HISTORY_512	<i>A private HISTORY, 512 bytes total space</i>
HISTORY_thoughts	<i>A public HISTORY for thoughts</i>
HISTORY_box_80	<i>An 80 byte small mailbox called BOX</i>

Single character names should not be used: these are reserved as keys for special variations which may be made available in the future.

HISTORY_U_FILES ***A public HISTORY with all entries unique???***

Messages may be put into a HISTORY device by either using PUT or PRINT. If the HISTORY device becomes full, the oldest message(s) are thrown away.

Messages may be taken out using GET or INPUT. But which message?

For a private HISTORY it is fairly simple. The first GET or INPUT after a message has been put into the HISTORY will get the most recent message. The next GET or INPUT will get the previous message until there are either no messages left (in which case GET or INPUT return null strings) or another message is put in. Note that GETting or INPUTting messages does not take them out of the HISTORY.

OPEN_NEW #4, HISTORY_512	<i>Open a private HISTORY device to hold 512 bytes</i>
PRINT #4, msg1\$	<i>For a private HISTORY, the message need not be atomic</i>
PUT #4, msg2\$	<i>... but this also puts a message in.</i>
INPUT #4, a\$	<i>Inputs msg2\$ into a\$</i>
GET #4,b\$	<i>Gets msg1\$ into b\$</i>

For a public HISTORY, the channels are fairly independent. A channel being used to read messages would continue to fetch messages in reverse order even if new messages are being added through other channels. In order to get the most recent message, a channel being used for read operations only needs to be able to

DEV_LIST#2 *lists the current DEVs in #2*

DEV_USE\$ DEV_NEXT

The DEV_USE\$ (number) function returns the usage for the specified DEV.
The DEV_NEXT (number) function returns the next DEV after the specified DEV.

PRINT DEV_USE\$(3) *prints the usage for DEV3*
PRINT DEV_NEXT(1) *prints the next DEV in the chain after DEV1*

Interaction between DATA_USE, PROG_USE and DEV

If you are going to use the DEV defaults, it makes sense to set the DATA_USE and PROG_USE defaults to use DEV, and when moving from directory to directory change the DEV definition rather than the DATA_USE.

DATA_USE dev1_ *data default directory is DEV1_*
DEV_USE 1, flp2_myprogs_ *... which is myprogs on FLP2*
PROG_USE dev2_ *programs from DEV2_*
DEV_USE 2, flp1_ex_, 1 *... which is flp1_ex or my data default!*

DEV_USEN

Allows renaming of the DEV device. Both DEV_USE or DEV_USEN with one parameter will rename the DEV device, DEV_USEN without parameter will reset the name of DEV back to DEV.

DEV_USEN mdv *DEV is now called MDV*
DEV_USEN *and now its name is DEV again*

Directory Devices

The devices which handle individual files, organised in directories (with at least one root directory) will behave as before, i.e. the drive RAM is used to access the RAM-disk, FLP is used to access the floppy disk, and WIN is used to access the harddisk. More details can be found in the hardware-dependent sections of this manual. SMSQ/E will read and write from and to QL floppy disk (DD and HD, if your hardware permits).

In addition, SMSQ/E comes with inbuilt drivers to recognise TOS harddisk partitions, DOS floppy disks, and TOS floppy disks (DD and HD).

The SBASIC command DIR has been extended to show density and format of a medium. There are new functions which allow you to fetch this information, see the DMEDIUM_xxx range of functions.

If you insert a QDOS 720k floppy disk into flp1_ and type:

DIR flp1_

then you will see the following (or similar) output on the screen:

```
diskname QDOS DD  
720/1440 sectors  
... directory ...
```

If you insert a DOS high-density disk and ask for the directory again, you should see:

```
DISKNAME MSDOS HD  
720/2880 sectors  
... directory ...
```

DOS disks

You can load files from DOS disks as if they were QL disks. You can save files to DOS disks, but you have to make sure that the filename does match the DOS naming convention, i.e. up to eight characters, full stop, up to three characters for the extension.

All the filing system calls will work on DOS disks, you can create subdirectories, delete files. You cannot, however, use the FORMAT command to format a floppy disk to DOS format - it will always be the preferred (QDOS) format.

The DOS filing system does not have the concept of different filetypes. Different filetypes are distinguished by their filename extension. Therefore, QDOS "executable" programs (filetype 1) cannot be handled the way they are handled on a QDOS disk. From SMSQ/E version 2.87 on, you can copy executable files onto DOS disks, which can later be executed from this disk. They will get a special extension '.EXn' where n is the number which specifies the dataspace (which is usually held invisible to the user in the file header): it is $512 \cdot 2^n$. This extension will be invisible in SMSQ/E, but will be seen in DOS. Example (assuming flp1_ contains a DOS disk):

COPY win1_CLOCK, flp1_CLOCK

will create a file flp1_CLOCK.EX1 on the DOS disk. You can still refer to it as flp1_CLOCK, it will be shown in the directory as flp1_CLOCK only, but if you look at this disk on a DOS computer, then you will see the real name. Extensions of executable files will be removed automatically, e.g.

COPY win1_PROGRAM_bin, flp1_PROGRAM.bin

will not create a file flp1_PROGRAM.bin, it will create a file flp1_PROGRAM.EX3, but you have to refer to it as **flp1_PROGRAM** only, e.g.

EX flp1_PROGRAM

As the filename extension is lost anyway even if you copy the file back, we suggest that you do not specify an extension. This will also make sure that you do not end up with files having the same filename.

SMSQ/E Event Handling

Principles

V2.71 of SMSQ/E introduces facilities for event handling which can be either used as an extension to the Extended Environment window events or independently.

An event is notified from one task to another.

A job may wait for one or more events. If one of the events has already occurred, then the wait will terminate immediately, otherwise the operating system will suspend the job until one of the events has occurred.

SBASIC Implementation

WAIT_EVENT

The WAIT_EVENT (event mask, timeout) function is used to wait for one or more events. 8 events are defined; they are numbered 1, 2, 4, 8 . . . 256. The timeout is an optional 9th event.

The function returns the event or events that have occurred. The events that are returned are removed from the job's "event accumulator". Note that, if WAIT_EVENT is called to wait for events 2 or 4 and events 2 and 8 have occurred, only event 2 is returned: event 8 remains pending and can be checked on another call.

evt = WAIT_EVENT (6)	<i>Wait for event 2 or 4 (2+4=6)</i>
	<i>Events 2 and 8 are notified by another job so the wait is terminated and evt is set.</i>
PRINT evt	<i>Prints 2</i>
PRINT WAIT_EVENT (15)	<i>Wait for event 1, 2, 4, or 8, prints 8 as event 8 is pending</i>
PRINT WAIT_EVENT (15)	<i>Wait for event 1, 2, 4, or 8, wait as no events now pending</i>

If a timeout is specified, then, if no event of interest has occurred before the end of the timeout, the call will return the value 0 (no events). A timeout 0 can be used to check for events.

evt = WAIT_EVENT (6,50) *Wait for event 2 or 4 (2+4=6) for no more than 1 second
No events are notified by another job so the wait
is terminated after one second and evt is set to 0.*

PRINT evt *Prints 0*

PRINT WAIT_EVENT (3,0) *Test for event 1 or 2 without waiting*

SEND_EVENT

The SEND_EVENT job ID, events procedure is used to notify events to another job. The job ID can be the whole number, the job number and tag or the job name.

SEND_EVENT 'fred',9 *Send events 1 and 8 (1+8=9) to job fred*

SEND_EVENT 20,4,8 *Send event 8 to job 20, tag 4*

SEND_EVENT OJOB(-1),2 *Send event 2 to my owner*

Utility Programs

DRVCHK and DRVLINK Hard Disk Utilities

DRVCHK and DRVLINK are two hard disk utilities. In an ideal world you should need neither, and if all is well there should be no harm done if you try them. The programs will work on the Miracle Harddisk, all ACSI and SCSI harddisks connected to ATARIs, and the QXL. We have no experience with the Falkenberg Harddisk interface (it might trash your harddisk, we don't know), but it will not work on the QUBIDE.

DRVCHK is rather like a soft format which checks the readability of the free sectors on the drive. It does not check the sectors which have been allocated to files. If you find that reading some files is becoming unreliable, you should copy the contents to a new file and then delete the old file. This returns the sectors to the free space list. Executing DRVCHK will check all the free sectors and eliminate unreadable sectors. Unreliable sectors may not get eliminated and it might be useful to execute DRVCHK more than once. If you have a rather unreliable drive, you may find it worthwhile executing DRVCHK after a hard disk format as an additional check.

DRVLINK is intended to repair the hard disk map of contents when this has been corrupted. (Note that as the hard disk map is in the form of linked lists similar to those used by MSDOS and other low grade operating systems, continuing to create, delete or modify files on the disk when you suspect that it may be corrupted is very unwise. It is safe to copy files to new backup disks, but **DO NOT OVERWRITE** old backup disks, or you may find that your backups are corrupted as well!) The hard disk map can be corrupted by a variety of software: the main culprits are probably the GST Linker (old version, not the one supplied by Quanta) and any software which draws arcs or uses ATAN, ASIN or ACOS (QDOS only, not SMSQ/E!).

The most obvious symptoms of corrupted maps are "drive full" messages when the drive is not full or "bad or changed medium" when accessing files. In the latter case, execute DRVLINK first, then delete the bad files, and finally execute DRVCHK to check the freed sectors.

DRVLINK may not completely repair the hard disk map, but it should put it into a state where it will not get any worse. **BEWARE:** although DRVLINK is believed to be safe, there could possibly be circumstances where the cure could be worse than the disease. Corrupted maps are quite rare, so there has not been much opportunity to exercise DRVLINK.

SERNET V3

SERNET provides you with low-cost networking like the Toolkit 2-Network. SERNET allows you to connect two machines together via the serial ports. SERNET V3 has been significantly improved over previous versions. The configuration is easier, you can control more than one SERNET link on one machine (previously, modifications applied to the most recently loaded SERNET only), and it is even possible to use a SERNET via modem between two machines.

To connect two machines, use a standard Null-Modem-Cable (note: **NOT** a laplink cable!).

SERNET has to be configured so that it knows which port to use as its communication port (default is SER1), and it needs to know its device name (default is S). Use MenuConfig to configure SERNET.RXT or SERNET_REXT (depending on your disk format) and define the port. Please note that the serial port needs to support independent channels (SRX and STX), hardware handshake and direct, untranslated data flow (parameters "hd"). You need to have SMSQ/E in order to use SERNET!

You can run differently configured SERNETs at the same time to form different circular networks, just by giving a different port number and a different device name.

The BASIC commands which correspond to a SERNET driver start with the same character which is configured as a device name. Therefore, with more than one SERNET being loaded into the same machine, you have independent control of the net by specifying the corresponding BASIC command. For example, if your net is configured to be "S" (default), then all commands will start with S (e.g. SNET, SNET_START, SNET_STOP). If its device name is, for example, N, then the commands will be NNET, NNET_START, NNET_STOP etc.

BEFORE you LRESPR the SERNET driver you have to set the port to the correct BAUD rate. Naturally, all machines in the SERNET circle require to have their SERNET ports set to the same baudrate.

The default setting is that, when you LRESPR the SERNET, it is set up fully functional with the server being started (default configuration, but it can be turned to off to start with).

The following commands exist, replace the "x" by the configured SERNET device name letter:

xNET_STATION

xNET_STATION n *a procedure to set the SERNET station number. Default is to station 1 - does not normally need to be changed.*

xNET_STATION%

xNET_STATION% *is a function which returns the current SERNET station number.*

xNET_TEST%

xNET_TEST% (s) *is a function which informs whether another station with station number s is on the net.*

xNET_START

xNET_START *is a procedure to open the channels for SERNET and to start the SERNET server job. Unless you configured it off, SERNET will start with fully working with the server job running. You can invoke this command after you accidentally removed the server job or closed SERNETs channels "from outside", or, of course, after a xNET_STOP.*

xNET_STOP

xNET_STOP *is a procedure which closes the channels used by SERNET and removes the SERNET server job - in case you need to use the serial ports for other reasons.*

xNET_BAD%

xNET_BAD% *is a function which returns the total number of bad packages received since SERNET has started.*

xNET_RETRIES%

xNET_RETRIES% *is a function which returns the number of retries to re-send packages.*

SERNET via Modem

It is also possible to use SERNET between two machines as a client/server relationship via modem. The server is the machine which is sitting somewhere remotely, waiting for the client to dial in and initiate the connection. You should be sitting in front of the client. You need to configure SERNET to be used with a modem, and you need to have two configurations, one SERNET being the server, one being the client. Make sure both versions have the same password!

To properly configure the modem init string, refer to the modem's manual. We suggest, you add an instruction to turn the modem's compression off, because this will speed up transferring small packages (which is, what SERNET does). Modify modem dial and modem hangup strings only if required.

You can configure up to 10 destinations to dial to. Simply insert the phone numbers here.

Please note that the whole protocol is not very error-proof, line drops of either side etc. may not be detected so follow the exact route of initiating a transfer and closing it. Some systems (hardware-dependent) allow the loss of carrier detection, so try to issue a SER_CDEOF command for the SER port to which SERNET connects.

Get the server-SERNET running on the remote machine.

Get the client-SERNET running on the machine in front of you. You will see a new button appearing, saying "CONNECT xxx" where xxx is the phone number #0. To select any of the other numbers, press the keys 0 to 9 while having the mouse over the SERNET button. To dial, press SPACE or ENTER. SERNET will not try to dial out to the other modem, and after success, you will hear a beep and the button will display "DISCONNECT". Only disconnect via this button, do not turn the modem etc. otherwise one or both machines will not react to future SERNET calls until reset.

As soon as you see the DISCONNECT, the connection is established and you can access the remote machine over the modems in exactly the same way as with "standard" SERNET.

It is even possible to make the button automatically dial out. Send an event to the SBASIC Button job, which is called "x_SERNET Client" (of course, x needs to be replaced by the SERNET name character). The event should be the number to dial (0 to 9)+16. Example:

SEND_EVENT "S_SERNET Client",2+16

will dial phone number #2. You should then check the function

xNET_CONNECT%

xNET_CONNECT% *is a function which returns true if you are connected*

until it becomes true (put a PAUSE of 25 or 50 between every check), transfer the required files, and send the same event to disconnect.

SERNET File Protection

Files beginning with (or in directories beginning with) *H or *h will be treated as Host Only, and cannot be read over the net. Any attempt to use these files will return 'not found'.

Files beginning with *R will be classed as Read Only, and can be read, but not written to, as if the device is write protected.

Files beginning *D will return 'not implemented' to prevent hackers accessing disallowed files by direct sector techniques.

These facilities allow you to keep sensitive files on a hard disc without anyone on the network being able to access them. However, these can cause problems with some software which does not expect access to be denied.

SERNET Batchfile Execution

It is possible to invoke an SBASIC job on a remote machine and instruct it to execute a given SBASIC program. With this facility, you can do everything you like on the remote machine because you can provide SBASIC programs which do whatever you want them to do. To start an SBASIC program on a remote machine, use

EX "n1_*dev1_program_bas"

where "n1_" can be any kind of network name and station number, e.g. s2_, m1_ etc. and "dev1_program_bas" can be any program on any device on the remote machine.

Example: You would like to see what kind of jobs are running on another machine. Create the following short program first, and save it to, say n1_ram1_jobs_bas

```
10 OPEN#3,n1_con           this is OUR machine, seen from the remote!
20 BORDER#3,1,4:CLS#3
30 JOBS#3
40 INPUT#3,"Press ENTER"!a$   Wait for an ENTER press
```

Then, after having it transferred to the remote machine, start it there with

EX "n1_*ram1_jobs_bas"

Please note, that the SBASIC filename specified must be the full filename, including device and extension. The server will not check PROG_USE settings, check for _BAS or _SAV endings because the remote machine can have totally different default devices than your machine, possibly resulting in an execution of a different program.

SMSQ/E Troubleshooting

I get a "not found" error message when trying to write a file to a TOS or DOS format diskette.

There are three problems to watch out for:

- The first is that it is obligatory to create directories on a DOS or TOS format disk before you put files into them. You cannot just use any name you like as you have been accustomed to do on QDOS format disks.
- The second is that the filing system does not automatically attempt to convert files which end in, for example, _bas to files ending in .bas.

Files which I intended to write to a DOS format floppy disk were copied instead to my data default directory with "FLP1_" in front of the name.

The same problem as above.

When I try to QMON a file, I end up tracing Job 0 in a rather bizarre way.

Unlike SuperBASIC, SBASIC initialises all variables to zero or null string.

In order to distinguish a name (which would be a filename) from a number (which would be a Job number) QMON, and a small number of other programs, made the assumption that a file name would not have a value. This is not necessarily true for SuperBASIC, it is never true for SBASIC.

Either put the file name in quotes or
upgrade your QMON.

I have some software which works in the initial SBASIC but does not work when I try to use it from an SBASIC daughter.

The initial SBASIC is 99.9% compatible with SuperBASIC. SBASIC daughter Jobs are only 99% compatible with SuperBASIC. In particular

they are not Job 0 and
the channel IDs for #0, #1 and #2 are not \$00000, \$10001 and \$20002.

Some naughty software cannot cope with this difference.

Old versions of QMON cannot, but old versions of JMON can.
Turbo cannot, but QLiberator can.

Either update the software or
use this software in the initial SBASIC only.

I only get the end of the error message when I use the SBAS/QD F10 Thing.

Some of the SBASIC error messages are longer (hopefully more helpful) than the old SuperBASIC error messages. Older versions of the Menu extensions cannot cope with these long messages. Update your MENU_REXT.

When I try to use the SuperBASIC channel table from another Job I find that it is empty.

As you can have many SBASIC Jobs, you can have many SBASIC channel tables: one in each set of SBASIC variables. From within an SBASIC Job, these look just the same as the SuperBASIC channel table. The tricks that can be used with QDOS to find the SuperBASIC variables area will, in SMSQ, find a dummy variables area which holds only the global name table. This is the only part of the SuperBASIC environment which is common to all SBASIC jobs.

To find any other part of a SuperBASIC variables area from another Job, you must define which copy of SBASIC you wish to poke about in. To do this you need to go to supervisor mode and find the value of A6 for the particular SBASIC Job you are about to interfere with: the channel table and most other parts of the SuperBASIC variables area will be found at their usual offsets from A6.

Sysmon runs at 200 times its normal speed on the TT.

Until the authors manage to update Sysmon to cope with the TT Fast RAM, process your copy with the program SYSMON_BAS.

Not all of my programs run on the TT.

Configure SMSQ to ignore Fast RAM: it will be much more QL compatible.

QREF crashes when I use it with a program which has binary or hexadecimal constants

Much "poke around in SuperBASIC" Software, including QREF, does not recognise binary (%1010) or hexadecimal (\$4AFB) constants. In general, avoid using these types of constants if you intend to use old SuperBASIC analysers, reformatters or compilers.

QREF (and QLOADREF) may be processed by the QREF_BAS program, which is believed to be harmless, but keep a spare copy of your original QREF or QLOADREF just in case. After processing, they happily accept binary or hexadecimal constants.

My System does unexpected Things right from the start, e.g. crash, does not recognise SBASIC commands anymore, does not remove windows, Sysmon wails immediately etc.

You should first check the extensions which you load in your BOOT file. Try putting STOPs into your BOOT file and see how far you get until your system falls over, to track down the offending system extension or command. We have put a list of system extensions together which you should first check - extensions in the list will either be marked as bad or good. Ignore the good ones and remove the bad ones and be suspicious about extensions which are not in the list.

After loading my BOOT file, my BASIC does not recognise procedures like PRINT.

One or more of the extensions which you load in your BOOT file overwrite part of the memory which is used for storing the name table (where all BASIC names are stored). A good candidate is QPTR V0.06 or earlier. REMark suspicious extensions and re-boot again, until you find the one(s) which cause the trouble. Please notify us about faulty extensions, so that other users can be warned.

I get an error when I try to load EASYPTR extensions

For some reason, versions of EASYEXT before V3.02 checks for the position where it is loaded. A copy of EASYEXT V3.02 is included on the SMSQ/E disk.

The Archive Runtimes don't work anymore

They were never designed to multitask properly. ARCHRTM grabs all but a few Kbytes of RAM. ARCHRTM can be modified, so that you can tell it how much memory it shall get. ARCHRTM_bas will modify it, so that it will find the variable RTMEM% again. As it is not possible to specify more than 32k to be left, this isn't very useful. However, if you type the following line (where max_space is the maximum amount that ARCHRTM can take) before you execute it, then things will happily multitask:

```
POKE_L !!$24,max_space
```

DATES in Archive/Abacus fails

If you find that, when you try to access the DATE in Psion programs, the program crashes, becomes very slow or returns silly dates like 31/-7/8995 then the language you're using on your system does not seem to be the same as the language in which the Psion software runs. If you want to run an English XChange, then you need to set the language of your system to English too (LANG_USE GB). As Archive and Abacus

convert the Month to a month number by comparing the names (e.g. Mar = 3), it cannot find the right name if you set the system language to German or French (it might work on Jan, but not on Mar/Mär or Oct/Okt).

C-compiled programs crash on the QXL

Some versions of C68 have own 68030 and 68040 cache handlers which are faulty. Fortunately, the code checking for the processor is faulty too, so that the 68030 cache handler is never called. Bad news for the 68040 on the QXL: it is called! As SMSQ/E handles the cache (very well) itself, there is no need for the C68 programs to do that. You can completely patch the cache handling in the programs out by using the C68_40.BAS program. This does not recognise all versions of C68, but it does work on common programs like BlackKnight. It is better to recompile programs which were compiled with earlier versions of C68.

QLiberators EXTERNals do not work

If you have compiled own procedures and functions using QLiberator, which you want to load using LRESPR, then you have to patch QLIB_RUN and QLIB_OBJ first to make them work. You will find two BASIC programs with the same name which will do this for you. You should also patch files with already inbuilt EXTERNals.

QLOADED files look strange - the numbers are gone

If you QLOADED files which were saved with Minerva Integer tokens, then you will see funny effect like WINDOW , < , , , then you have to go back to a Minerva machine, QLOAD it there and SAVE it back in ordinary ASCII. Then you can load it into SMSQ/E. If you QSAVE it here, you can QLOAD it into any system.

TRA does not seem to work anymore

As you have probably noticed by reading this manual, there are various new translating features like the "D" parameter in the device name, UPUT for untranslated output etc. The way TRA is handled is different, much more logical and consistent on SMSQ/E. When you open a channel to, say PAR or SER, then the current TRA setting for this port stays active as long as the port is open. So, if you open PAR with TRA 0 being active and you active TRA 3 later on, the open port is not affected. Two operations affect open ports: changing the BAUD rate and changing the translation table to channels with activated translates. Changing TRA from 0 to an address or vice versa is ignored on open channels.

The program stops after "OK to overwrite.. Y or N" has been answered "N"

Save did not overwrite on QDOS anyway, therefore this is no compatibility problem. We think it is better to stop because the action did not finish properly, and you still have the choice to trap it using WHEN ERROR in your program.

ALTKEYs and Last Line Recall (ALT ENTER) do not work anymore

Type the command HOT_GO (or better add it to your BOOT file) and both ALTKEYs and ALT ENTER will work again. Both functions have been integrated into the much more powerful HOTKEY System II. Separate documentation for the HOTKEY System II is available.

Hints on various extensions and files

ATR_rext	not required, as DV3 are more flexible anyway. Don't load!
ATARI_rext	not required. Versions before V2.37 might crash on SMSQ.
ATARIDOS_rext	not required, as DV3 are more flexible anyway.
DEV_rext	not required, as DEV is inbuilt into SMSQ. Don't load!
EASYEXT	before V3.02 creates problems, use copy enclosed.
HOT_rext	not required, as HOTKEY System II is inbuilt into SMSQ. Don't load!
JMON	safe. Better use V2.10 or higher on SMSQ for proper parameter handling.
LIGHTNING	not required anymore. SMSQ/E's screendriver is very fast already. Will refuse to load.
MENU_rext	safe. Better use V5.08 or higher on SMSQ for proper error report in SBAS/QD F10 Thing.
MIDINET_rext	safe.
Pointer Tools	(from W.Lenerz) - if you loose some SBASIC Procedures, this version is too old.
PTR_GEN	not required, as it is inbuilt into SMSQ. Don't load!
PTRMENR_cde	safe.
QBASIC_rext	not really required, as SBAS/QD is better. Can safely be used for QLiberator.
QD	safe.
QLIB_bin	safe.

QLIB_run	safe, as SMSQ makes sure the faults are cured.
QLIB_ext	safe.
QLOADREF_bin	not required, as QLOAD is inbuilt into SMSQ. Use QREF_bin instead.
QMON	should be safe. Better use V2.10 or higher on SMSQ for proper parameter handling and proper channel use in SBASIC daughter jobs.
QPAC2	safe.
QPTR	From V0.09 onwards safe. Versions before should be upgraded (smashes some SBASIC commands).
QTYP_SPELL	safe.
SDUMP	safe.
SPEEDSCREEN	not required anymore. SMSQ/E's screendriver is faster and more compatible anyway. Don't load it, as it may crash the system.
THING_rext	safe.
TRA_rext	safe, but check if it is still required, as SMSQ's TRA has been extended.
WMAN	not required, as it is inbuilt into SMSQ. If you essentially need a more recent than the inbuilt version, you may re-load it, but some features of the inbuilt WMAN may not work.

SMSQ/E for Atari ST and TT

Introduction

From the point of view of the hardware dependent features, SMSQ/E as implemented on the Atari ST and TT series computers is very similar to the latest E level drivers for QDOS. There are two main changes. Firstly, monochrome monitors are supported. Secondly, the incorporation of the DV3 disk driver subsystem, which replaces the V2 disk driver used by the E level drivers means that Atari GEMDOS partitions of hard disks and GEMDOS (as well as IBM) format floppy disks may be read and written.

Machine Type

The two standard functions to determine the machine type are, of course, supported.

MACHINE

The MACHINE function returns the machine type.

0	ST / STM / STF / STFM.
1	ditto, with blitter.
2	Mega ST (without blitter) or ST etc. with real-time clock.
3	Mega ST (with blitter) or ST etc. with RTC and blitter.
8	Mega STE (without blitter!).
9	Mega STE.
24	TT 030

PROCESSOR

The PROCESSOR function returns the 680x0 family member - 0 or 30 for the Atari ST and TT series. The PROCESSOR function is provided in addition to the MACHINE function as it is possible to fit an MC68030 accelerator card in the lesser ST machines.

IF MACHINE < 24 AND PROCESSOR = 30: PRINT "68030 accelerator fitted"

Memory Protection

One feature of the ST series of computers is its memory access control. This causes a system error (access fault) if a program attempts to access memory which does not exist or which can only be accessed in supervisor mode (the vector area, the TOS system variables and the IO hardware).

Early versions of SMSQ on the ST series of computers detected legitimate accesses to the QL vector area but trapped all other memory access faults. This provided a certain measure of protection against the worst excesses of QL software. While this policy provided compatibility with well written, fault free, QL software, not much of the other 99% would work at all. A new policy has, therefore, been introduced.

1. All legitimate read operations from the QL vector area are allowed.
2. All other read operations from protected areas read 0.
3. All write operations to protected areas are ignored.

This policy can be applied to all Jobs or just to Job 0. If an access fault is trapped. The job goes into a state of hibernation with the fault program counter on the stack and all other registers preserved. The Job may, therefore, be examined by a debugger.

PROT_MEM

The PROT_MEM (level) procedure sets the level of the memory protection. All legitimate accesses to the vector area are always allowed. Other access faults may be trapped or ignored depending on the level. The default level is 3 which will trap common faults in C programs, but allows certain famous system extensions to be LRESPRed. Cautious users should change this to level 7. Devil-may-care users should change it to level 0.

There are five levels: 0, 1, 2, 3 and 7.

Colour Displays

SMSQ/E supports the old QL emulator card, in its original form and modified for MODE 8, the extended QL mode 4 card and the QVME card.

The extended QL mode 4 card may be switched from normal to extended display, and the display size of the QVME card may be changed at will.

DISP_SIZE

DISP_SIZE (xpixels, ylines) is used to set the display size. The nearest feasible size will be selected by the driver. It is best not to change the display size when the pointer sprite is visible, or you may get some spurious blobs left on the display. There should be few other problems changing from a smaller size to a larger size. You should, however, avoid changing from a larger size to a smaller if there are any windows outside the smaller screen. Note that, for the QVME card, the width and height are set in increments of 32 pixels and 8 lines respectively, while for the extended QL mode 4 card, any width of 512 or less will select the standard resolution mode while any width greater than 512 pixels will select the extended mode.

DISP_SIZE 800,600 *change to 800x600 (QVME) or 768x280 (extended mode 4)*
DISP_SIZE 1 *change to 512x256 (extended mode 4) (ignored by QVME)*

DISP_RATE

DISP_RATE (frame rate, line rate) is used to specify the frame and line scan rates for the QVME card only: it is ignored for all the other display cards. It would be usual to specify only the frame rate: the line rate is equal to the frame rate multiplied by the total number of lines.

DISP_RATE 75 *set the frame rate to 75 Hz*
DISP_RATE 70,48000 *set the frame rate to 70 Hz and line rate to 48 kHz (686 lines)*

DISP_BLANK

DISP_BLANK (x blank, y blank) sets the size of the blank area to the sides of and above and below the image for the QVME card only: it is ignored for all the other display cards. If the blank is too small, you will lose some of your image, if it is too large, the image will be too small.

DISP_BLANK 128,64 *set horizontal blank to 128 pixels and vertical to 64 lines*

As the display size is altered, the blank is automatically adjusted to maintain the proportion of blank. The DISP_BLANK command will not usually be required.

If preferred, the parameters for the DISP_RATE and DISP_BLANK commands may be tacked on to the DISP_SIZE command.

DISP_SIZE 640,480,60 *set standard VGA*
DISP_SIZE 800,480,80 *set 80 Hz refresh rate, squashed VGA.*
DISP_SIZE 800,600,70,,128,60 *set all of size, frame scan rate and x and y blank*

Note that if you specify both frame and line rates, as well as the number of blank lines, the line rate is over-specified: it will be determined by the frame rate and the total number of lines (visible + blank) and the line rate will be ignored.

DISP_SIZE Experimenter

The QVME card does not have an infinite choice of pixel rates. Some combinations of size and display rates may not be acceptable to your monitor. A small experimenter program can be used to change the size and frame rate in small intervals.

This program starts off with the standard VGA settings and adjusts the width when you press the W key, the height when you press the H key and the frame rate when you press the F key. Because you cannot see the display when you have struck an unsatisfactory combination, you can save a satisfactory setting with the S key and restore it later with the R key.

If, for example, you are increasing the width (SHIFT W) and the display dissolves, DONT PANIC. Pressing the key a few more times may shift you past a bad patch. Alternatively, adjusting the frame rate up or down may improve matters. It is for you to find out what your monitor will accept.

The true hackers can add code to this program to adjust the blank as well.

```

100 REMark - This is an experimenter for the QVME display size and frame rate.
110 REMark
120 REMark - w reduces the width           - SHIFT W increases the width.
130 REMark - h reduces the height          - SHIFT H increases the height.
140 REMark - f reduces the frame rate      - SHIFT F increases the frame rate.
150 REMark - s saves the current settings
160 REMark - r restores the saved settings
170 REMark
180 REMark - ESC finishes
190 REMark
200 REMark - Set initial values for standard VGA
210 sw=640: sh=480: sf=60
220 a%=CODE('r')
230 :
240 REPEAT
250  SElect ON a%
260  =27: STOP
270  =CODE('w'): dw=dw-32
280  =CODE('W'): dw=dw+32
290  =CODE('h'): dh=dh-16
300  =CODE('H'): dh=dh+16
310  =CODE('f'): df=df-1
320  =CODE('F'): df=df+1
330  =CODE('s'): sw=dw: sh=dh: sf=df
340  =CODE('r'): dw=sw: dh=sh: df=sf
350  END SElect
360  DISP_SIZE dw,dh,df: REMark - Set width, height and frame rate.
370  PRINT #1,dw,dh,df
380  BGET #1,a%
390  END REPEAT

```

This program demonstrated that a perfectly legible 1600x496 (266 column) display was obtainable using a standard monochrome VGA monitor (cost about DM 200).

Serial (RS232) Ports on the Atari ST and TT Series

The number of serial ports depends on the model.

SER1	MODEM 1	ST/STE Mega STE	TT
SER2	MODEM 2	Mega STE	TT
SER3	SERIAL 1		TT
SER4	SERIAL 2	Mega STE	TT

The ports themselves are connected to three different serial controllers of two different types. The communications speeds are, therefore, a bit special.

SER1

The rates available on this port are sub-multiples of 19,200. All the standard rates from 300 to 19,200 are available except 7,200.

SER2

The rates available on this port are sub-multiples of 250,000. 19,200 is very close to 250,000/13. All the standard rates from 300 to 19,200, including 7200 (within 1%) are supported. In addition it supports 1x and

2x MIDI speeds as well as 38,400, 76,800, 83,333 and 125,000 baud. If the rate is specified as 0, the rate used is 153,600 (19,200x8).

SER3

The rates available on this port are sub-multiples of 19,200. All the standard rates from 300 to 19,200 are available except 7,200. Hardware handshaking is not available on this port.

SER4

The rates available on this port are sub-multiples of 114,750. All standard rates from 300 to 38,400 are supported (within 0.4%) as well as 57,600 (19,200x3). If the rate is specified as 0, the rate used is 230,000.

Atari ST Printer Port

The Atari ST (and TT) printer port (the SMSQ/E PAR device) is notionally "centronics compatible", unfortunately a combination of very substandard drive capability on the part of the ST computers, excessive drive requirements of some printers (notably Canon) and long cables can significantly reduce the reliability of the printer connection. The problem can be reduced by extending the length of the strobe pulse.

PAR_PULSE

PAR_PULSE (pulse length) sets the notional pulse length in microseconds. The time will depend on the processor and the clock speed.

PAR_PULSE 50 *drive a Canon printer from a standard ST*
PAR_PULSE 500 *... or from a HyperCache 030*

Atari ST and TT Hard Disks

ACSI and SCSI Drives

Hard disks for the Atari ST and TT series computers come in two varieties: ACSI and SCSI. Although most drives attached to the ACSI bus will be full standard SCSI devices, the SMSQ/E drivers assume that any drive connected to the ACSI bus does not necessarily conform to the SCSI CCS specifications so, normally, no attempt is made to do anything other than read or write sectors or read the error status on these devices. This means that, for example, the drivers cannot detect whether an ACSI disk drive has a removable cartridge.

On the other hand, the SMSQ/E drivers assume that all drives connected to the SCSI bus (TT only) conform to the minimum CCS specifications for hard disk operations. Any disk drive which responds "OK" to a request to lock the door is considered to have a removable cartridge.

If a file is open on a removable cartridge, the door is locked. It will be unlocked automatically later.

WIN Drive Numbers and Name

ACSI and SCSI drives are identified by a whole series of numbers: the "target" number, the "unit" number and the "partition" number. The target number is the identification number of the disk drive controller. For internal drives, this is 0. For external drives, this is the number (0 to 7) that you set on the little switches on the back of the box. The unit number selects one of a number of drives controlled by a single controller. It is possible, but rare in the Atari world, for a controller to have up to 8 units. In general, there is only one unit per controller, and 99% of Atari hard disk utility software assumes that you can only have one unit per controller, so the unit number is usually 0. Finally, the partition number defines a section of the disk reserved for a particular purpose (e.g. GEM partitions, QDOS partitions etc.).

GEMDOS numbers its target, unit and partitions from 2 (=C) as it finds them. This is a superficially attractive scheme which collapses completely if you have removable media with different numbers of partitions or if the medium is not in the disk drive when you boot the computer.

SMSQ/E adopts a more cumbersome approach which is, however, much more precise. Unless you configure SMSQ/E to boot from a target and partition other than 0,0, the initialisation code will attempt to find a file

called "BOOT" on any partition on target 0. (For the TT, SMSQ/E will try SCSI 0 first and then try ACSI 0). WIN1 will be set to this partition. Thereafter, you must define your own WIN drives for any other target, unit and partition you wish to access.

WIN_DRIVE

WIN_DRIVE (drive, target, unit, partition) is used to select a particular target, unit and partition combination to be accessed using a particular WIN drive.

If an SCSI drive is to be accessed, 8 should be added to the target number. The unit number may be omitted or both the unit and partition numbers may be omitted.

WIN_DRIVE 2,1,0,2	WIN2 is ACSI target 1, unit 0, partition 2
WIN_DRIVE 3,9	WIN3 is SCSI target 1, unit 0, partition 0
WIN_DRIVE 4,3,1	WIN4 is ACSI target 3, unit 0, partition 1

Issuing a WIN_DRIVE command for a particular drive will cause the drive map to be re-read the next time the disk is accessed. It can, therefore, be used to force the drivers to recognise a disk change.

WIN_DRIVE\$

WIN_DRIVE\$ is a function which returns a string giving the target, unit and partition used by a particular WIN drive.

WIN_DRIVE 2,1,0,2	WIN2 is ACSI target 1, unit 0, partition 2
WIN_DRIVE 3,9	WIN3 is SCSI target 1, unit 0, partition 0
PRINT WIN_DRIVE\$(2)	Prints 1,0,2
PRINT WIN_DRIVE\$(3)	Prints 9,0,0
PRINT WIN_DRIVE\$(4)	Prints nothing if WIN4 has not been set

WIN_USE

WIN_USE may be used to set the name of the WIN device. The name should be 3 characters long and in upper or lower case.

WIN_USE MDV	The WIN device is renamed MDV
WIN_USE win	The WIN device is restored to WIN
WIN_USE	The WIN device is restored to WIN

Handling ACSI Adapter Timing Faults

Certain ACSI adapters exhibit a timing fault. If commands are issued too quickly one after the other, the adapter fails. The SMSQ/E ACSI driver can be slugged to bring its interval between commands down to GEMDOS levels.

WIN_SLUG

The WIN_SLUG (value) command sets the minimum time that must elapse between operations on the ACSI bus (in units of 80 μ s). ICD recommend 1 ms for their adapters. As an interval of 2.5 ms between operations has proved adequate for most adapters, this is the default. As the typical access times for ACSI hard disks are of the order of 20 ms to 30 ms, this does not represent a large overhead.

WIN_SLUG 12	Wait at least 12*80 μs between ACSI operations
WIN_SLUG 30	Wait at least 30*80 μs between ACSI operations (default)

Format WIN

As SMSQ/E is "hosted" on the Atari ST and TT computers, it only takes control of and formats partitions on the hard disk which you have previously marked as being reserved for QDOS compatible disk drivers. We know that you would not destroy all your GEM desktop publishing files by formatting a QDOS disk on top of them, but someone else might do it.

Before formatting a QDOS compatible partition, therefore, you will need to use your favourite GEM utility to make a suitable partition available, marking it as "QWA" (GEMDOS partitions are identified by the letters "GEM" or "BGM").

Before formatting a WIN drive with SMSQ/E, it is necessary to define the ACSI or SCSI target number (and the unit number if it is not 0) and partition.

WIN_FORMAT

The next step is to allow the drive to be formatted. SMSQ/E has a two-level protection scheme, to make sure you (or somebody else) cannot format your harddisk accidentally. All drives are protected by default, so you have to declare them to be formattable before you issue the FORMAT command.

WIN_DRIVE 2,1	<i>Set WIN2 to ACSI target 1, unit 0, partition 0</i>
WIN_FORMAT 2	<i>allow WIN2_ it to be formatted</i>
FORMAT win2_Fred	<i>and FORMAT it</i>
	<i>... you have to echo the two characters displayed ...</i>
WIN_FORMAT 2,1	<i>protect WIN2_ again</i>
WIN_DRIVE 1,8,2	<i>Set WIN1 to internal TT drive, partition 2</i>
WIN_FORMAT 1	<i>allow WIN1_ it to be formatted</i>
FORMAT win1_BOOT	<i>and FORMAT it</i>
	<i>... you have to echo the two characters displayed ...</i>
WIN_FORMAT 1,1	<i>protect WIN1_ again</i>

WIN Control Commands

The rest of the commands specific to the Atari ST and TT WIN device control or set the characteristics of a specific WIN drive.

WIN_WP

WIN_WP (drive, 0 or 1) is used to software write protect a WIN drive.

WIN_WP 1,1	<i>Set the "write protect" flag for the drive accessed by WIN1</i>
WIN_WP 1,0	<i>Clear the "write protect" flag for the drive accessed by WIN1</i>

WIN_START WIN_STOP

The WIN_START (drive) and WIN_STOP (drive) commands may be used to start and stop a drive. If you issue one of these commands for an ACSI drive, the drivers may assume that the drive will accept other SCSI control commands.

WIN_STOP 2	<i>Stop the drive accessed by WIN2</i>
WIN_START 2	<i>Start the drive accessed by WIN2</i>

WIN_REMV

WIN_REMV (drive, 0 or V) is used to notify that the target accessed by the WIN drive has a removable medium. It is usually detected automatically, unless you turned the auto-detection off (see configuration). Drives connected to the SCSI ports are detected automatically, so it is only required on the ACSI port, provided, auto-detection is off. No parameter is required to mark the drive as being a standard removable device. A "V" marks the drive as a VORTEX naughty drive. A "0" cancels the removable medium flag.

WIN_REMV 2	<i>Set the "removable" flag for the drive accessed by WIN2</i>
WIN_REMV 2,0	<i>Clear the "removable" flag for the drive accessed by WIN2</i>
WIN_REMV 3,V	<i>Set the VORTEX flag for the drive accessed by WIN3</i>

Atari ST and TT Floppy Disks

Most of the models in the ST and TT range are equipped with a single DD 3.5" floppy disk drive. Some of the later models are equipped with an HD drive. The SMSQ/E FLP driver can read or write QL5A, QL5B, TOS and MSDOS format diskettes. It can format QL5A (DD) and QL5B (HD) format diskettes.

Floppy Disk Driver Name

The default name of the floppy disk driver is FLP. The internal drive is FLP1. The external drive (if any) is FLP2.

FLP_USE

FLP_USE may be used to set the name of the FLP device. The name should be 3 characters long and in upper or lower case.

FLP_USE mdv	<i>The FLP device is renamed MDV</i>
FLP_USE FLP	<i>The FLP device is restored to FLP</i>
FLP_USE	<i>The FLP device is restored to FLP</i>

Format FLP

The SMSQ/E FLP driver will usually format a diskette to the highest density it can. The density may, however, be set using the FLP_DENSITY command or by adding a special code to the end of the medium name in the format command.

FLP_DENSITY

The SMSQ/E format routines will usually attempt to format a disk to the highest density possible for a medium. The FLP_DENSITY (code) is used to specify a particular recoding density during format. The density codes are "S" for single sided (double density), "D" for double density and "H" for high density.

FLP_DENSITY S	<i>Set the default format to single sided</i>
FLP_DENSITY H	<i>Set the default format to high density</i>
FLP_DENSITY	<i>Reset to automatic density selection</i>

The same code letters may be added (after a *) to the end of the medium name to force a particular density format. (For compatibility with older drivers, if the code letter is omitted after the *, single sided format is assumed.)

FORMAT 'FLP1_Disk23'	<i>Format at highest density or as specified by FLP_DENSITY</i>
FORMAT 'FLP1_Disk24**'	<i>Format single sided</i>
FORMAT 'FLP1_Disk25*S'	<i>Format single sided</i>
FORMAT 'FLP1_Disk25*D'	<i>Format double sided, double density</i>

FLP_TRACK

The FLP_TRACK (number of tracks) is used to limit the number of tracks formatted.

FLP_TRACK 23	<i>Only format 23 tracks</i>
---------------------	-------------------------------------

FLP Control Commands

FLP_SEC

FLP_SEC (level) was used to set the security level. The security of the data stored on the diskettes can be seriously compromised if you change diskettes while there are files open. The security level affects the amount of time the FLP driver spends maintaining the data on the diskette up to date with the internal copies of the data in memory. In principle, a lower level is more efficient, but more risky. With the increasing use of hard disks, the security level of the FLP has been fixed at level 2: the most secure. FLP_SEC is ignored.

FLP_START

The FLP_START (ticks) command specifies the number of ticks (1/50th of a second) that the FLP driver waits after starting the drive before writing to it. This allows the diskette to get up to speed before the write

operation. The default value is 24, which is a wait of about 0.5 s. There should not be any reason to use this command.

FLP_STEP

In the days when QLers used scrap 5¼" disk drives with 30 ms step rates, FLP_STEP allowed the disk drive step rate to be set. In the 5 years that the Atari drivers for QDOS were distributed, no-one ever complained that FLP_STEP was completely ignored. It still is ignored in the SMSQ/E drivers.

Configuration

It is possible to configure the file SMSQ.PRG to pre-define various settings. For doing that, you require the Menu-Extension to be present in your machine, and you need the program MenuConfig to be able to configure the SMSQ.PRG file. Both files (the extension and the config program) can be found on nearly every commercial program disk (QD, QSpread, QSUP, QMAKE etc.), but if you do not happen to find them on any of your commercial program then it is advisable that you get a copy of the QMenu package, which contains both files you need.

You can pre-define the boot partition of the harddisk to be WIN1_ (0 to 7 for ACSI, 8 to 15 for SCSI and the partition number). If both values are set to 0, then it is "automatic", i.e. SCSI 8 and ACSI 0 are searched from partition 0 onwards until it finds a file called WIN1_BOOT. It then sets WIN1_ to that partition and LRUNs the BOOT file. This means, that you could run your BOOT file from a TOS partition if you wish. Default is 0,0.

Next comes the language code. You can enter here the numerical values explained in LANG_USE. Default is English.

The next setting allows you to disable the use of TT Fast RAM (if it exists). We have not found programs so far which refuse to run in Fast RAM, but it is here, just in case.

You can pre-define the display adaptor, but there is no reason not to leave it in "automatic" mode unless you happen to have more than one QL emulator installed in your machine.

Then you can pre-define all six parameters for the QVME DISPlay, so that you immediately get a picture even if your monitor cannot handle the default rates (50 Hz, 15.625kHz).

Finally, you can turn off the auto-detector of removable harddisks on the ACSI port. You should disable this feature only in case your harddisk controller crashes during the first access (we had no controller yet who did it).

SMSQ/E for Gold and Super Gold Cards

Introduction

SMSQ/E for the GOLD and Super GOLD Cards has a number of important improvements in the handling of the serial and parallel ports. In addition, the V2 disk driver supplied with the GOLD and Super GOLD cards has been replaced by the DV3 disk driver subsystem. This means that IBM format floppy disks may be read and written as easily as QL format disks.

Loading SMSQ/E

SMSQ/E for the GOLD and Super GOLD Cards is supplied as an executable file (SMSQ_GOLD) which may be loaded at any time using the LRESPR command or by executing it. Note that you cannot LRESPR a version of SMSQ_GOLD if that using the same version of SMSQ (you can, however, execute it). This means that the LRESPR command for SMSQ_GOLD can safely be put within (preferably at the start of) a normal BOOT file.

100 PRINT VER\$	<i>VER\$ will be printed by QDOS and then by SMSQ</i>
105 TK2_EXT	<i>required on a GoldCard only</i>
110 LRESPR SMSQ_GOLD	<i>QDOS will load SMSQ, SMSQ will ignore this</i>
120 LRESPR QPAC2	<i>QDOS will not get this far, SMSQ will load QPAC2</i>

Note that SMSQ incorporates the latest versions of the pointer environment (PTR_GEN, WMAN and HOT_REXT) so these should not be loaded. Lightning cannot be used when the Pointer Environment is already installed, but this does not matter too much as the CON driver of SMSQ/E is, under most circumstances, within a few percent of that speed.

Machine Type

The two standard functions to determine the machine type are, of course, supported.

MACHINE

The MACHINE function returns the machine type:

10	GOLD Card.
11	GOLD Card with HERMES.
12	Super GOLD Card.
13	Super GOLD with HERMES.

PROCESSOR

The PROCESSOR function returns the 680x0 family member - 0 for the GOLD card or 20 for Super GOLD Card.

```
IF MACHINE = 11 OR MACHINE = 13 : PRINT "HEY! I've got Hermes!"  
IF MACHINE = 12 AND PROCESSOR <> 20: PRINT "Where's my 68020 gone!!"
```

GOLD Card Display

DISP_TYPE

The DISP_TYPE function is used to find the type of display. For the Gold and Super GOLD card, this is the standard QL display so DISP_TYPE always returns 0.

```
IF DISP_TYPE : PRINT "This is not a QL display"
```

Serial (RS232) Ports on the GOLD & Super GOLD Card

Unlike the QL serial ports drivers, the SMSQ serial port drivers are dynamically buffered. There is, therefore, no need to use the PRT device.

There are two serial ports on the outside of standard QL although there is only one serial port inside which is shared between the two external ports. This sharing places serious limitations on the capabilities of these ports.

In addition, the implementation of the IPC, which provides serial input on the QL, left a lot to be desired. The Hermes replacement chip provides a number of major improvements. Apart from general improvements in reliability, the Hermes chip also permits the receive baud rate to be different for each external port and to be different from the transmit baud rates.

BAUD

The Baud rates supported by the GOLD and Super GOLD Card are

19200	
9600	
4800	
2400	
1275	1200 receive 75 transmit (Hermes only)
600	
300	
75	75 receive 1200 transmit (Hermes only)

Note that, if different baud rates are be used for transmitting on the two ports, you are unlikely to be able to receive any data without the Hermes chip.

BAUD 19200	<i>set both ports to 19200 / 19200</i>
BAUD 2,1275	<i>reset SER2 to 1200 receive, 75 transmit (V23)</i>

STX

Because the internal receive hardware is shared between the two input ports, having an input port open unnecessarily can reduce the performance of the other port considerably. For example, if you are using SER2 to connect your QL to a modem for accessing a bulletin board, opening SER1 to print a log file will seriously affect the performance of SER2. If, on the other hand, you open the transmitter side of the SER1 port only (using the device name STX1) the receive performance of SER2 will not be affected.

OPEN #3, ser2	<i>receive and transmit on SER2</i>
OPEN #4, stx1	<i>transmit only on SER1</i>

XON XOFF

Although it has been stated by Sinclair that hardware handshaking is required for serial communication with the QL, the XON XOFF protocol is supported by SMSQ/E. The problem is that whether the main flow of data is from the QL or to the QL, the loss of any data on reception by the QL can completely screw up the protocol. Test have shown, however, that the SMSQ/E implementation of XON / XOFF allows heavy flows of data at up to 4800 baud from the QL, and, more surprisingly, heavy flows of data at up to 2400 baud to the QL. With Hermes fitted, higher speeds should be possible.

SER_PAUSE

This procedure allows you to define the length of the stop bits in microseconds independently for both serial ports. The higher the value, the longer the stopbit. This might be helpful if characters sent by the serial port get lost or the device connected, e.g. printer, prints undefined characters. The longer the pause, the slower is the transfer rate.

Super GOLD Card Printer Port

The PAR device (parallel printer port) is only available on the Super GOLD card. By default output is dynamically buffered: the PRT devices is not required.

GOLD Card Floppy Disks

SMSQ/E for the GOLD card and Super GOLD card supports up to 4 disk drives which may be single, double, high or extra high density. The SMSQ/E FLP driver can read or write QL5A, QL5B, TOS and MSDOS format diskettes. It can format QL5A (DD) and QL5B (HD, ED) format diskettes.

Floppy Disk Driver Name

The default name of the floppy disk driver is FLP.

FLP_USE

FLP_USE may be used to set the name of the FLP device. The name should be 3 characters long and in upper or lower case.

FLP_USE mdv	<i>The FLP device is renamed MDV</i>
FLP_USE FLP	<i>The FLP device is restored to FLP</i>
FLP_USE	<i>The FLP device is restored to FLP</i>

Format FLP

The SMSQ/E FLP driver will usually format a diskette to the highest density it can. The density may, however, be set using the FLP_DENSITY command or by adding a special code to the end of the medium name in the format command.

FLP_DENSITY

The SMSQ/E format routines will usually attempt to format a disk to the highest density possible for a medium. The FLP_DENSITY (code) is used to specify a particular recoding density during format.

The density codes are "S" for single sided (double density), "D" for double density, "H" for high density and "E" for extra high density.

FLP_DENSITY S	<i>Set the default format to single sided</i>
FLP_DENSITY H	<i>Set the default format to high density</i>
FLP_DENSITY	<i>Reset to automatic density selection</i>

The same code letters may be added (after a *) to the end of the medium name to force a particular density format. (For compatibility with older drivers, if the code letter is omitted after the *, single sided format is assumed.)

FORMAT 'FLP1_Disk23'	<i>Format at highest density or as specified by FLP_DENSITY</i>
FORMAT 'FLP1_Disk24**'	<i>Format single sided</i>
FORMAT 'FLP1_Disk25*S'	<i>Format single sided</i>
FORMAT 'FLP1_Disk25*D'	<i>Format double sided, double density</i>

FLP_TRACK

The FLP_TRACK (number of tracks) is used to limit the number of tracks formatted.

FLP_TRACK 23	<i>Only format 23 tracks</i>
---------------------	-------------------------------------

FLP Control Commands

FLP_SEC

FLP_SEC (level) was used to set the security level. The security of the data stored on the diskettes can be seriously compromised if you change diskettes while there are files open. The security level affects the amount of time the FLP driver spends maintaining the data on the diskette up to date with the internal copies of the data in memory. In principle, a lower level is more efficient, but more risky. With the increasing use of hard disks, the security level of the FLP has been fixed at level 2: the most secure. FLP_SEC is ignored.

FLP_START

The FLP_START (ticks) command specifies the number of ticks (1/50th of a second) that the FLP driver waits after starting the drive before writing to it. This allows the diskette to get up to speed before the write operation. The default value is 24, which is a wait of about 0.5 s. There should not be any reason to use this command.

FLP_STEP

Some drives require step rates slower than the 3ms which is standard in the SMSQ/E FLP driver. For these, the FLP_STEP command may be used to set the step rate either for all drives or for a particular drive.

FLP_STEP 6 *set all drives to 6 ms step rate*
FLP_STEP 2,4 *set FLP2 to 4 ms step rate.*

GOLD Card Microdrives

This version does not support the QL microdrives.

SER Mouse

Copyright 1992-1995 Albin Hessler Software. Thank you very much, Albin!

SERMouse is a software driver to connect a serial PC mouse to one of the serial ports SER1 or SER2 of a QL. Therefore a specially wired cable interface is necessary. The driver exists both, in a 2-button mouse (Microsoft mode compatible) and a 3-button mouse (PC mouse systems compatible) version.

Most 3-button mice without mode switch are switched into 3-button mode by pressing the left button during power-on. Mice switching automatically (by software) between 2-button or 3-button mode may only work in 2-button mode on a QL.

If the serial ports are used for a mouse and a serial printer only, the power for the mouse can be drawn from the QL without any problem.

The mouse is then supplied through pin 6 (pin 9 on a QL with SUB-D9) of the serial port which nominally has +12V. Not more than 10mA should be drawn, as else, through a resistor in the QL, the voltage would fall below +5V.

The negative voltage comes from the receive line (RxD), while the mouse sends data over the send line (TxD).

If the other serial port shall also be connected to a device which draws power from the +12V pin (i.e. a serial to parallel converter), then pin 6 (pin 9 SUB-D9) of each ports should be connected separately through a resistor (680 Ohm) to +12V on the QL board.

Loading the driver

The driver code is loaded residently. New SuperBASIC commands (described below) are initialised and available. If the driver is configured to initialise on startup, it is immediately installed and active, else only after SERMON.

For testing purposes the code can be started as a job too. Then the driver is installed directly, but the SuperBASIC commands are not available. Removing the job will remove the driver automatically.

Function

The mouse is driven at 1200 baud at one of the serial ports SER1 or SER2. The driver receives the signals from the mouse and passes them to the Pointer Interface or the keyboard driver.

Printer

Unfortunately, on a standard QL the baud rate affects both ports. SERMouse saves the actual baud rate before initialisation, then sets the baud rate to 1200. If a channel to the other serial port is opened, the mouse is automatically suspended and the baud rate set back to its previous value.

If the channel is closed again, the mouse is reactivated automatically.

If the old baud rate coincides with the mouse baud rate (i.e. 1200) then the mouse is still working, even if the other port is used.

Cable Connector

Some mice may even require a different wiring!

Mouse with SUB D25	pin name or function	QL SER1 SUB D9	QL SER2 SUB D9	QL SER1 BT	QL SER2 BT
2	TxD	3	2	3	2
3	RxD	2	3	2	3
4	+12V	9	9	6	6
7	GND	7	7	1	1

Mouse with SUB D9	pin name or function	QL SER1 SUB D9	QL SER2 SUB D9	QL SER1 BT	QL SER2 BT
2	TxD	2	3	2	3
3	RxD	3	2	3	2
5	GND	7	7	1	1
7	+12V	9	9	6	6

or

Mouse with SUB D25	pin name or function	QL SER1 SUB D9	QL SER2 SUB D9	QL SER1 BT	QL SER2 BT
1	GND	1	1	1	1
2	TxD	3	2	3	2
3	RxD	2	3	2	3
4	GND	1	1	1	1
7	GND	1	1	1	1
20	+12V	9	9	6	6

Mouse with SUB D9	pin name or function	QL SER1 SUB D9	QL SER2 SUB D9	QL SER1 BT	QL SER2 BT
2	TxD	2	3	2	3
3	RxD	3	2	3	2
4	+12V	9	9	6	6
5	GND	7	7	1	1
7	+12V	9	9	6	6

Focussing

Resolution, speed, acceleration and wake up speed are all configurable through the config block. They can also be controlled through the SuperBASIC commands SERMSPEED and SERMAWS at run-time. SERMSPEED directly alters the data delivered by the mouse, while SERMAWS determines how these are processed by the Pointer Interface.

Hermes

The SERMouse driver is fully compatible with Hermes, the replacement IPC 8749 for the QL. Hermes allows separate baud rates, e.g. the mouse can be driven on SER2 at 1200 Baud, while SER1 can be set to 19200 baud for a printer. The automatic control of the baud rate by the mouse driver as described above is no

longer necessary. The SERMouse driver detects Hermes on initialisation if the suspend options in the config block are disabled.

If you have Hermes installed in your QL, then please set:

```
Set mouse baud rate on initialisation > yes
Suspend driver if baud rate changed > no
Suspend driver if other serial port open > no
```

Then, and only then, Hermes is detected and only the receive baud rate for the mouse is set. The system baud rate is not changed. Subsequent changes of the system baud rate will not affect the mouse.

Attention: on a QL with a standard 8049 IPC all the above options must be set to yes.

Configuration

The SERMouse driver can be configured with the standard config program of the Pointer Environment. Before you make changes to the preset values, you should try to find out the best values with the SuperBASIC commands SERMSPEED, SERMAWS and BLS. The configuration is widely self-explaining. Here are the recommended default values:

Baud rate		1200
Set baud rate on initialisation		yes
Port		ser2
Suspend driver if baud rate changed without	Hermes	yes
	with Hermes	no
Suspend driver if other serial port open	without Hermes	yes
	with Hermes	no
Pointer Speedup		0
Pointer Slowdown		0
Acceleration Mouse		4
Acceleration Pointer Interface		6
Cursor Speedup		1
Cursor Slowdown		1
Double click delay (50=1 sec)		10
Double HIT=DO?		no
Time to blank screen		5
Initialise on		startup
Save working copy as		file

(A working copy of the SERMouse driver is saved to the given file. This copy does contain the configured data only but not the configuration block with the descriptive text.)

Mouse Buttons

All mouse buttons are configurable. Therefore three separate config blocks are present. Changing the mouse buttons should be done with great care. It is possible to assign any control code and SPACE to a button (\$00 - \$20 and \$E8 - \$FF). Some codes can not be entered through the keyboard (e.g. ENTER and ESC), but a translate option exists:

Button:	NULL	HIT	DO	Cancel	SPACE	ENTER	ESC	ALT
Number:	0	1	2	3	6	7	8	9

When such a number was entered, the corresponding key is shown immediately in MenuConfig, while the standard config program shows the keys on a second run only.

Please notice: the IPC reset is performed from the code 255=\$FF=ALT (type number 9) - (all three buttons pressed simultaneously by default).

The mouse hotkey is performed from the code 254=\$FE=SHIFT ENTER (left and right button pressed simultaneously by default).

The Pointer Interface cancel (code 3) does work in pointer programs only and does not generate an ESC in other programs! On the other hand, an ESC character (27=\$1B) is translated by the Pointer Interface to a

cancel (code 3) and always works. Therefore we have set an ESC for the middle button. The 3-button reset can be switched off easily by setting another code (e.g. NULL) to do nothing.

BASIC Commands

BAUDRATE%

bd%=BAUDRATE

returns the actual baud rate of the system.

BLS

BLS time%

time%	0	off
time%	1-20	minutes
time%	21-59	seconds

The screen is blanked after the time elapsed if no key was pressed on the keyboard and the mouse was not moved. Any keypress or mouse movement will bring the screen contents back.

SERMAWS

SERMAWS acc%,wup%

acc% 0-9 mouse acceleration (Pointer Interface)

Sets the mouse acceleration and wakeup speed as processed by the Pointer Interface. These are the same values as in Sysdef of QPAC2. They take global effect, i.e. for all programs. See configuration.

SERMCUR SERMPTR

SERMCUR switches to cursor mode if the driver is in the pointer mode and the cursor is visible (waiting for keyboard input). In cursor mode the cursor can be moved with the mouse. The cursor speed can be set through the configuration and can be altered with the SERMSPEED parameters at runtime.

If a program waiting for keyboard input, the driver can also be switched to cursor mode by a double-click on the left button.

SERMPTR resets to pointer mode if the driver is in cursor mode. The driver can also be switched back to pointer mode from cursor mode with a double click on the left button. The driver is automatically switched to pointer mode if a job reading the pointer is picked on top.

SERMOFF

Removes the SERMouse driver.

SERMON

Installs and activates (or re-activates after SERMWAIT) the SERMouse driver.

SERMRESET

Resets the coprocessor (IPC 8049) which controls the serial ports. To be used if the internal buffer of the coprocessor is desynchronised (uncontrolled mouse movements).

SERMSPEED

SERMSPEED mul%,div%,acc%[,cursormul%,cursordiv%]

mul%	0-127	Speedup factor	0=off
div%	0-127	Slowdown factor	0=off
acc%	0-8	Acceleration factor	0=off
cursormul%	0-127	Cursor mode speedup factor	
cursordiv%	0-127	Cursor mode slowdown factor	

The step rate sent by the mouse is multiplied with the speedup and divided through the slowdown factor. This changes the mouse resolution linearly. The recommended values have the effect that only two third of the step rate is passed to the Pointer Interface, i.e. the physical resolution of the mouse is decreased slightly.

The accelerator factor determines a progressive speed up, i.e. on a slow movement nothing is changed, but the faster the mouse is moved, it is accelerated more and more. See configuration.

The recommend values (see configuration) should only be changed if changing the mouse acceleration factor of the Pointer Interface (see SERMAWS or Sysdef in QPAC2) does not lead to a satisfactory mouse movement.

The alternative parameters cursormul% and cursordiv% take effect in cursor mode only.

SERMWAIT

Suspends the SERMouse driver. See SERMON.

Configuration

It is possible to configure the file SMSQ_GOLD to pre-define various settings. For doing that, you require the Menu-Extension to be present in your machine, and you need the program MenuConfig to be able to configure the SMSQ_GOLD file. Both files (the extension and the config program) can be found on nearly every commercial program disk (QD, QSpread, QSUP, QMAKE etc.), but if you do not happen to find them on any of your commercial program then it is advisable that you get a copy of the QMenu package, which contains both files you need.

First comes the language code. You can enter here the numerical values explained in LANG_USE. Default is English.

Next, specify if you have an ABC keyboard. The "maybe" setting tries to determine automatically whether an ABC keyboard interface is connected or not. "No" will not check, "Yes" assumes it is connected.

SMSQ/E for the Aurora

Introduction

The Aurora card is a QL-compatible motherboard, developed by Zeljko Nastasic, originally available from Qubbesoft P/D. It supports QL-compatible screen modes, plus a 16-colour mode (unsupported in current versions of SMSQ/E) and a 256-colour mode (compatible with QPC2 256-colour mode) when the Aurora is used with a Super Gold Card. This section lists the minor differences between the Aurora and QL/Gold Card version. See **SMSQ/E for Gold and Super Gold Cards** for other details.

Loading SMSQ/E

The loading procedure is similar to that for the standard Gold Card version, except that the filename of the version downloaded from the SMSQ/E Registrar's website is AURORA.BIN

100 PRINT VER\$	<i>VER\$ will printed by QDOS and then by SMSQ/E</i>
105 TK2_EXT	<i>Required oon a Gold Card only</i>
110 LRESPR Aurora.bin	<i>QDOS will load SMSQ, SMSQ will ignore this</i>
120 LRESPR QAPC2	<i>QDOS will not get this far, SMSQ will load QPAC2</i>

Note that SMSQ incorporates the latest versions of the pointer environment (PTR_GEN, WMAN and HOT_REXT) so these should not be loaded. Lightning cannot be used when the Pointer Environment is already installed, but this does not matter too much as the CON driver of SMSQ/E is, under most circumstances, within a few percent of that speed.

Machine Type

The two standard functions to determine the machine type are, of course, supported.

MACHINE

The MACHINE function returns the machine type:

10	GOLD Card.
11	GOLD Card with HERMES.
12	Super GOLD Card.
13	Super GOLD with HERMES.

PROCESSOR

The PROCESSOR function returns the 680x0 family member - 0 for the GOLD card or 20 for Super GOLD Card.

```
IF MACHINE = 11 OR MACHINE = 13 : PRINT "HEY! I've got Hermes!"  
IF MACHINE = 12 AND PROCESSOR <> 20: PRINT "Where's my 68020 gone!!"
```

GOLD Card Display

DISP_TYPE

The DISP_TYPE function is used to find the type of display. For the Gold and Super GOLD card, this is the standard QL display so DISP_TYPE always returns 0 on a QL.

Additional modes available on the Aurora mean that the following values can be returned:

3	Aurora LCD
5	Aurora QL mode
16	8-bit (256 colour) mode

```
IF DISP_TYPE = 16 : PRINT "This is a 256 colour (8-bit) display"
```

DISP_COLOUR

DISP_COLOUR depth specifies the colour depth to be used.

DISP_COLOUR 0	<i>QL mode display</i>
DISP_COLOUR 1	<i>16 colour (4-bit) display mode – not currently implemented</i>
DISP_COLOUR 2	<i>256 colour (8-bit) display mode</i>

It is possible to set the display size immediately after the colour depth, although only a limited range of display sizes are available in the 256-colour mode due to the limited amount of screen memory available.

DISP_SIZE

DISP_SIZE xpixels, ypixels is used to set the display size. The nearest feasible size will be selected by the driver. Only a limited range of resolutions, based on 2:1 or 4:3 aspect ratios, are available on Aurora with Super Gold Card, as listed in the Aurora manual.

DISP_SIZE 640,480	<i>switch to VGA resolution of 640x480 pixels</i>
DISP_SIZE 512,256	<i>restore QL 512x256 display resolution</i>

SMSQ/E for the QXL

Introduction

SMSQ/E for the QXL is similar to the basic SMSQ operating system supplied with the QXL. The principal differences lie in the compatibility of the facilities. Whereas the basic SMSQ version shipped with the QXL is designed to be a continuation of the line of QL extensions starting with the first Miracle Trump card, SMSQ/E follows the line which started with the first QL clones (the Futura and others which were never put into production) and passed through the Atari ST series and which will, hopefully, continue to develop.

This line includes more flexible serial device drivers, additional "virtual" devices and the Pointer Interface integrated into a "lightning fast" console driver.

Loading SMSQ/E

SMSQ/E for the QXL is supplied as an IBM PC executable file - SMSQE.EXE (or SMSQEQXL.EXE, if downloaded from the SMSQ/E Registrar's website). This should be copied to your PC hard disk. When it is executed, SMSQE.EXE will create a small file (QXL.DAT), in the current directory, which holds the default address of the QXL card.

SMSQ/E is executed in the same way as the basic SMSQ version for the QXL.

C:QXL>SMSQE	<i>Start SMSQ/E on the QXL at the default address</i>
C:QXL>SMSQE /300	<i>Set default address to 300 and start SMSQ/E</i>
C:QXL>SMSQE /	<i>Return to the QXL without restarting SMSQ/E</i>

Note that SMSQ/E incorporates the latest versions of the pointer environment (PTR_GEN, WMAN and HOT_REXT) so these should not be loaded in your BOOT file. Lightning cannot be used when the Pointer Environment is already installed, but this does not matter too much as the CON driver of SMSQ/E for the QXL is, under most circumstances, as fast or faster.

Machine Type

The two standard functions to determine the machine type are, of course, supported.

MACHINE

The MACHINE function returns the machine type - 28 for the QXL.

PROCESSOR

The PROCESSOR function returns the 680x0 family member - 40 for the QXL.

IF MACHINE = 28 AND PROCESSOR <> 40: PRINT "Where's my 68040 gone!!"

QXL Display

DISP_TYPE

The DISP_TYPE function is used to find the type of display. For the QXL, this is an emulation of the standard QL display in mode 4 or mode 8, so DISP_TYPE always returns 0 for those modes. When used in 16-bit colour mode, DISP_TYPE returns 32.

IF DISP_TYPE : PRINT "This is not a QL display"
IF DISP_TYPE = 32 : PRINT "I am in 16-bit colour mode"

DISP_SIZE

DISP_SIZE xpixels, ylines is used to set the display size. The nearest feasible size will be selected by the driver. It is best not to change the display size when the pointer sprite is visible, or you may get some spurious blobs left on the display. There should be few other problems changing from a smaller size to a larger size. You should, however, avoid changing from a larger size to a smaller if there are any windows outside the smaller screen. Values that are well out of range are ignored.

DISP_SIZE 800,600 *change to 800x600 (SVGA)*
DISP_SIZE 1 *ignored.*

Serial (COM) Ports on the PC

Unlike the basic SMSQ serial port drivers, the SMSQ/E serial port drivers are dynamically buffered. There is, therefore, no need to use the PRT device.

BAUD

The Baud rates supported by SMSQ/E on the QXL are

19200
9600
4800
2400
1200
600
300

If one of the ports is already committed to a mouse, the BAUD command will not affect it.

BAUD 19200 *set both ports to 19200*
BAUD 2,1200 *reset SER2 to 1200 baud*

PC Printer Port

The PAR device drives the PC printer port. By default, output is dynamically buffered: the PRT device is not required.

PC Floppy Disks

SMSQ/E accesses the PC floppy disks via the BIOS calls. This, although it allows almost any PC to be used as a host for the QXL, is dependent on the efficiency of your BIOS. The efficiency can usually be greatly improved by using one of the public domain BIOS level cache utilities that are available for the PC.

Floppy Disk Driver Name

The default name of the floppy disk driver is FLP. A: is FLP1 and B: is FLP2.

FLP_USE

FLP_USE may be used to set the name of the FLP device. The name should be 3 characters long and in upper or lower case.

FLP_USE mdv	<i>The FLP device is renamed MDV</i>
FLP_USE FLP	<i>The FLP device is restored to FLP</i>
FLP_USE	<i>The FLP device is restored to FLP</i>

Format FLP

We have not yet discovered any way of reliably formatting diskettes on any PC manufactured since 1985. (All published information that we have found either dates from before the introduction of the PC AT and only applies to 180 kbyte drives or has proved to be wrong). FORMAT, therefore, performs a re-format operation only and cannot be used with virgin disks.

FLP Control Commands

FLP_SEC FLP_START FLP_STEP

The QXL floppy disk driver may not be controlled.

PC Hard Disks

SMSQ/E accesses the PC hard disks via the PCDOS calls (the BIOS calls do not appear to work). This, requires a file (called QXL.WIN) to be set up in the ROOT directory of any hard disk you wish to use as a QDOS format disk. This file is the QDOS format disk.

Hard Disk Driver Name

The default name of the hard disk driver is WIN. C:QXL.WIN is WIN1, and D:QXL.WIN is WIN2 etc.

WIN_USE

WIN_USE may be used to set the name of the WIN device. The name should be 3 characters long and in upper or lower case.

WIN_USE mdv	<i>The WIN device is renamed MDV</i>
WIN_USE WIN	<i>The WIN device is restored to WIN</i>
WIN_USE	<i>The WIN device is restored to WIN</i>

Format WIN

Formatting a WIN device requires the creation of a large file under DOS. This takes a long time. The "name" of the WIN device should be the size required in Megabytes.

WIN_FORMAT

Before you can actually issue the FORMAT command, you have have to allow the drive to be formatted. SMSQ/E has a two-level protection scheme, to make sure you (or somebody else) cannot format your harddisk accidentally. All drives are protected by default, so you have to declare them to be formattable before you issue the FORMAT command.

WIN_FORMAT 1	<i>Allow WIN1_ to be formatted</i>
FORMAT WIN1_10	<i>Create a 10 Megabyte WIN device on C: ... you have to echo the two characters displayed ...</i>
WIN_FORMAT 1,0	<i>protect WIN1_ again against unwanted formatting</i>

Configuration

It is possible to configure the file SMSQE.EXE to pre-define various settings. For doing that, you require the Menu-Extension to be present in your machine, and you need the program MenuConfig to be able to configure the SMSQE.EXE file. Both files (the extension and the config program) can be found on nearly every commercial program disk (QD, QSpread, QSUP, QMAKE etc.), but if you do not happen to find them on any of your commercial program then it is advisable that you get a copy of the QMenu package, which contains both files you need.

You can predefine the port address of your QXL card. Default is 2B0h.

Next you can predefine the default display resolution for SMSQ/E. Default is 512x256.

You can specify if you wish to BOOT from FLP1_ (drive A:) or FLP2_ (drive B:) or none, provided, a disk is inserted. Otherwise specify a WIN drive number to boot from.

The three following items deal with the settings for PAR, SER1 and SER2.

Finally, you can specify the language code (numerical value) as described in the LANG_USE procedure explanation.

SMSQ/E for Q40

Introduction

From the point of view of the hardware dependent features, SMSQ/E as implemented on the Q40 is very similar to other SMSQ implementations. The only significant differences are minor improvements.

The hard disk and floppy disk drivers can handle multiple disk formats, two floppy disk drives and four hard disk drives. Two IO cards can be used to provide up to 4 serial ports and 3 parallel printer ports.

Machine Type

The two standard functions to determine the machine type are, of course, supported.

MACHINE

The MACHINE function returns the machine type. This function returns 17 for the standard Q40.

PROCESSOR

The PROCESSOR function returns the 680x0 family member - 40 for the Q40.

Memory Protection

All production Q40s include a memory management unit but this is not yet fully used by SMSQ/E. The PROT_MEM procedure has, therefore, no effect in current versions and the supervisor mode access peeks and pokes do not have any different effect from their user mode cousins.

PROT_MEM

The PROT_MEM (level) procedure sets the level of the memory protection. This is ignored in current versions.

POKES POKES_W POKES_L POKES_F POKES\$

POKES address, value
POKES_W address, value
POKES_L address, value and
POKES_F address, value
POKES\$ address, s\$

are the "supervisor mode" equivalents of POKE, POKE_W POKE_L POKE_F and POKE\$. By operating in supervisor mode they enable data to be written to the Q40 IO hardware. Do not be surprised if your computer self-destructs when you use them.

PEEKs PEEKs_W PEEKs_L PEEKs_F PEEKs\$

value%=PEEKs (address)
value%=PEEKs_W (address)
value=PEEKs_L (address)
value=PEEKs_F (address) and
s\$=PEEKs\$(address, bytes)

are the "supervisor mode" equivalents of PEEK, PEEK_W PEEK_L PEEK_F and PEEK\$. By operating in supervisor mode they enable data to be read from the QL IO hardware. Do not be surprised if your computer self-destructs when you use them.

Q40 Display

DISP_TYPE

The DISP_TYPE function is used to find the type of display. For the Q40, there are two values that may be returned.

0	Original ST QL emulator (this value is returned on QL based hardware).
1	16 bit colour mode.

ncol = 4

if DISP_TYPE = 1 : ncol=65536

Assume 4 colour display

If it is 16 bit, there are 65536

DISP_INVERSE

The DISP_INVERSE (0 or 1) command is used to invert a monochrome display. It has no effect on the Q40.

DISP_SIZE

DISP_SIZE (xpixels, ylines) is used to set the display size. When a size greater than 512x256 is specified, 16 bit colour mode is selected (not implemented in this version).

DISP_SIZE 1024,512 change to 1024x512 16 bit colour

DISP_RATE

DISP_RATE (frame rate, line rate) is used to specify the frame and line scan rates. It has no effect on the Q40

DISP_BLANK

DISP_BLANK (x blank, y blank) sets the size of the blank area to the sides of and above and below the image. It has no effect on the Q40.

Mouse driver

The mouse driver checks serial ports 4, 3, 2 and 1, in that order, looking for a Microsoft compatible two or three button mouse. If a mouse is used, it should be plugged into the highest port number available.

Because current serial mice for the PC have a much higher resolution (the pointer moves faster) than older mice, the original pointer interface scheme (accelerating slow mice) is no longer adequate. The new MOUSE_SPEED command is used to define the "acceleration". The value specified for the MOUSE_SPEED is the same as the value that can be specified in the QPAC2 SYSDEF menu.

MOUSE_SPEED

MOUSE_SPEED (#channel, speed, wake)

defines both a scaling for the mouse movement and an acceleration factor used for large movements.

SPEED	SCALING	ACCELERATION
0	1/8	low
1	1/8	normal
2	1/4	low
3	1/4	normal
4	1/2	low
5	1/2	normal
6	1	low
7	1	normal
8	1	high
9	1	extreme

The optional 'wake' defines how far the mouse will need to move before the pointer will appear (waking up the pointer) in a text input window.

The channel is optional, if the default channel is available, and is a console, no channel need be specified.

MOUSE_SPEED 2 *standard Microsoft mouse with low acceleration*
MOUSE_SPEED #0,5,8 *cheap mouse with acceleration, pointer reluctant to wake up*

Speeds 7 to 9 are the same as for previous versions. Speeds 0 to 6 are all slower than in previous versions. If a "low acceleration" speed is chosen, the pointer movement may be slightly viscous (this is an advantage in some applications). The default mouse speed is 7 (old mouse with normal acceleration). This default is overwritten by a configurable speed when QPAC2 is loaded.

The default wake speed is 3 which is fairly sensitive. This default is overwritten by a configurable speed when QPAC2 is loaded.

MOUSE_STUFF

MOUSE_STUFF (#channel, string)

defines a 0, 1 or 2 character string to be stuffed into the keyboard queue when the centre (or left and right) buttons are pressed. This is usually used to send a Hotkey. If a Hotkey is required, the first character should be CHR\$(255).

ERT_HOT_THING(".", "Button_Pick") *ALT . picks the button bar*
MOUSE_STUFF CHR\$(255)&'.' *The middle mouse button picks the button bar*

The default stuff string is CHR\$(255) & ".". This default is overwritten by a configurable Hotkey when QPAC2 is loaded.

The channel is optional, if the default channel is available, and is a console, no channel need be specified.

Serial (RS232) Ports on the Q40

The serial ports correspond to the standard IBM COM ports. Note that, unlike the PC BIOS SMSQ does not attempt to renumber the ports if it finds that one or more are missing.

SER1	COM1	address \$3F8
SER2	COM2	address \$2F8
SER3	COM1/3	address \$3E8
SER4	COM2/4	address \$2E8

The baud rates correspond to the normal PC baud rates: standard rates up to 38400 baud and then 57600, 115200, 230400, 460800 and 921600 baud. Only 16550A/16450 compatible serial ports are supported (i.e. any IO card made in the past few years). The availability of rates above 115200 depends on whether the IO card supports these rates and whether the mechanism to produce these rates is recognised by the drivers.

All the SMSQ/E standard serial port control commands are available.

Parallel Printer Ports

The parallel printer ports correspond to the standard IBM LPT ports.

PAR1	LPT1/2	address \$378
PAR2	LPT2/3	address \$278
PAR3	LPT1/2/3	address \$3BC

The standard parallel port driver assumes that the parallel port is IEEE 1284 compatible (ECP) and it will normally operate in SPP FIFO mode. The port can also operate in original PC mode. There are three reasons for operating in original PC mode.

1. Some IO cards are not compatible, in ECP mode, with the Q40 interrupt system. If possible, this problem should be resolved by removing the IRQ7/IRQ5 jumper so that the card does not produce

parallel port interrupts at all. It may, however, be necessary to set the jumpers on the card to SPP (original PC) mode.

2. Some printers may require a longer strobe pulse than is provided in FIFO mode.
3. It is PAR3 which is the LPT port at address \$3BC. This is not an ECP port address.

PAR_PULSE

PAR PULSE (port, pulse length)

sets the notional strobe pulse length in ISA bus cycles. If the port is not specified, PAR1 is assumed. If the pulse length is zero, then the parallel printer port will operate in FIFO mode. If it is greater than 0, then the parallel printer port will operate in original PC mode.

PAR_PULSE 2,2 *drive an old Epson printer on PAR2*
PAR_PULSE 0 *...set PAR1 to FIFO mode*

FIFO mode should be used if possible. The default value for PAR_PULSE is 0 if the IO card is configured for ECP mode or 1 if the IO card is configured for SPP mode.

PAR_WAIT

PAR_WAIT (port, wait cycles) sets the length of time that the parallel port driver will wait for the printer to be ready before it gives up and lets the Q40 do something else. This has no effect in FIFO mode, but in original PC mode it allows the buffer in the printer to be stuffed in bursts. The default value is 0. The larger the value, the higher the probability that a more than one byte of data can be sent on each interrupt, but the higher the load on the machine.

If the IO card does not provide IRQ7 and the machine is busy, PAR_PULSE will have a much greater effect than if IRQ7 is used and/or the machine is idle.

PAR_WAIT 2,20 give the printer on PAR2 a high priority
PAR_WAIT 0 ...set PAR1 use the minimum of processor time

For an Epson Stylus COLOR Pro printer, PAR_WAIT 10 and PAR_WAIT 50 improved the transfer speed by 30% on an idle machine : the rate was primarily determined by the printer. On a busy machine with no interrupts, PAR_WAIT 10 improved the transfer speed by a factor of 3 and PAR_WAIT 50 improved the transfer speed by a factor of 5. The speed of other tasks in the machine was reduced.

Q40 Hard Disks

IDE drives

The current IDE driver does not support removable drives.

WIN Drive Numbers and Name

ATA (IDE) drives are identified by the bus to which they are attached (primary or secondary), whether they are drive 0 or 1 on that bus (for historical reasons these are often called the master and slave drive although ATA compliant drives are neither master nor slaves: they are truly independent) and a partition on the drive.

Windows numbers its drives from C: as it finds them. This causes chaos if a removable media drive (or a normal drive in a rack) is used. (One of my PCs is obsessed by a phantom drive F: it thinks it is a 100kbyte CDROM).

SMSQ/E adopts a rather more cumbersome approach which is, however, much more precise. The initialisation code will attempt to find a file called "BOOT" on any partition on drive 0 . WIN1 will be set to this partition. Thereafter, you must define your own WIN drives for any other drive and partition you wish to access.

This means that if, for example, you have a drive in a rack, the other drive numbers stay the same regardless of whether the drive is in or out when you boot the system.

SMSQ/E does not require the whole of a drive to be used for itself: the drive can be partitioned between different operating systems. Depending on the format of used by the other operating systems, SMSQ/E may be able to read or write these "foreign" partitions. Partitions are numbered from 0.

WIN_DRIVE

WIN_DRIVE (drive, target, unit, partition)

is used to select a particular drive, unit and partition combination to be accessed using a particular WIN drive.

The "target" and "unit" notion comes from the SCSI bus terminology, the target is a physical device and the unit is a subdivision of that device. For IDE bus drives, there is only one unit per drive so the unit number is always zero and may be omitted. If the partition is omitted as well, then partition 0 (or the whole drive) is assumed.

Target	Bus	Drive
0	Primary	0 (Master)
1	Primacy	1 (Slave)
2	Secondary	0 (Master)
3	Secondary	1 (Slave)

Issuing a WIN_DRIVE command for a particular drive will cause the drive map to be re-read the next time the disk is accessed. It can, therefore, be used to force the drivers to recognise a disk change.

WIN_DRIVE 2,0,1 *WIN2 is drive 0 on the primary bus, partition 1*
WIN_DRIVE 3,3 *WIN3 is drive 1 on the secondary bus (whole drive or partition 0)*

WIN_DRIVE\$

WIN_DRIVE\$ is a function which returns a string giving the target, unit and partition used by a particular WIN drive.

WIN_DRIVE 2,0,1 *WIN2 is drive 0 on the primary bus, partition 1*
WIN_DRIVE 3,3 *WIN3 is drive 1 on the secondary bus (whole drive or partition 0)*

PRINT WIN_DRIVE\$(2) *Prints 0,0, 1*
PRINT WIN_DRIVES(3) *Prints 3,0,0*

WIN_USE

WIN_USE may be used to set the name of the WIN device. The name should be 3 characters long and in upper or lower case.

WIN_USE MDV *The WIN device is renamed MDV*
WIN_USE win *The WIN device is restored to WIN*
WIN_USE *The WIN device is restored to WIN*

Format WIN

If a drive is unformatted (or not recognisably formatted) you can format the whole drive as an SMSQ drive.

WIN_FORMAT 1 *Allow WIN drives to be formatted*
WIN_DRIVE 3,2 *Set WIN3 to secondary drive 0, whole drive*
FORMAT win3_Fred *FORMAT WIN3*
WIN_FORMAT 0 *Prevent WIN drives from being formatted*

On the other hand, if you wish to share a drive between different operating systems, you can partition the drive by executing the MKPART utility before formatting.

WIN_FORMAT 1	<i>Allow WIN drives to be formatted</i>
WIN_DRIVE 3,2,1	<i>Set WIN3 to secondary drive 0, partition 1</i>
EW MKPART	<i>Partition drive, setting partition 1 to "QWA"</i>
FORMAT WIN3_Fred	<i>FORMAT WIN3</i>
WIN_FORMAT 0	<i>Prevent WIN drives from being formatted</i>

WIN Control Commands

There are a number of "odd" WIN device control commands.

WIN_WP

WIN_WP (drive, 0 or 1) is used to software write protect a WIN drive.

WIN_WP 1,1	<i>Set the "write protect" flag for the drive accessed by WIN1</i>
WIN_WP 1,0	<i>Clear the "write protect" flag for the drive accessed by WIN1</i>

WIN_START WIN_STOP

The WIN_START (drive) and WIN_STOP (drive, time) commands may be used to start and stop a drive. If a time is given on the WIN_STOP command, the drive should not stop immediately: the time is the period without any disk accesses that must elapse before the drive automatically enters standby mode. A zero time cancels the automatic standby timer.

WIN_STOP 2	<i>Stop the drive accessed by WIN2 now</i>
WIN_STOP 2,3	<i>Stop the drive accessed by WIN2 when there has been no access for 3 minutes</i>
WIN_STOP 2,0	<i>Do not stop the drive accessed by WIN2</i>
WIN_START 2	<i>Start the drive accessed by WIN2</i>

Note that all the operations that might be used to restart a drive (there is no "official" ATA command) are "vendor specific". on your particular drive, the drive may not start again until you try and read from (or write to) the drive, or it may never start again. You should also note that, on some drives, WIN_STOP drive, time will not only set the timer but stop the drive immediately as well.

As with any ATA command, these commands will work if they work, otherwise they will not work.

Q40 Floppy Disks

The Q40 will normally have one or two HD disk drives. The SMSQ/E FLP driver can read or write QL5A, QL5B and MSDOS format diskettes. It can format QL5A (DD) and QL5B (HD) format diskettes.

Floppy Disk Driver Name

The default name of the floppy disk driver is FLP. The internal drive is FLP1. The external drive (if any) is FLP2.

FLP_USE

FLP_USE may be used to set the name of the FLP device. The name should be 3 characters long and in upper or lower case.

FLP_USE mdv	<i>The FLP device is renamed MDV</i>
FLP_USE FLP	<i>The FLP device is restored to FLP</i>
FLP_USE	<i>The FLP device is restored to FLP</i>

Format FLP

The SMSQ/E FLP driver will usually format a diskette to the highest density it can. The density may, however, be set using the FLP_DENSITY command or by adding a special code to the end of the medium name in the format command.

FLP_DENSITY

The SMSQ/E format routines will usually attempt to format a disk to the highest density possible for a medium. The FLP DENSITY (code) is used to specify a particular recording density during format.

The density codes are "S" for single sided (double density), "D" for double density and "H" for high density.

FLP_DENSITY S	<i>Set the default format to single sided</i>
FLP_DENSITY H	<i>Set the default format to high density</i>
FLP_DENSITY	<i>Reset to automatic density selection</i>

The same code letters may be added (after a *) to the end of the medium name to force a particular density format. (For compatibility with older drivers, if the code letter is omitted after the *, single sided format is assumed).

FORMAT 'FLP1 Disk23'	<i>Format at highest density or as specified by FLP_DENSITY</i>
FORMAT 'FLPI_Disk24*'	<i>Format single sided</i>
FORMAT 'FLP1_Disk25*S'	<i>Format single sided</i>
FORMAT 'FLPI_Disk25*D'	<i>Format double sided, double density</i>

FLP_TRACK

The FLP_TRACK (number of tracks) is used to limit the number of tracks formatted.

FLP_TRACK 23	<i>Only format 23 tracks</i>
---------------------	-------------------------------------

FLP Control Commands

FLP_SEC

FLP_SEC (level) was used to set the security level. The security of the data stored on the diskettes can be seriously compromised if you change diskettes while there are files open. The security level affects the amount of time the FLP driver spends maintaining the data on the diskette up to date with the internal copies of the data in memory. In principle, a lower level is more efficient, but more risky. With the increasing use of hard disks, the security level of the FLP has been fixed at level 2: the most secure. FLP_SEC is ignored.

FLP_START

The FLP_START (ticks) command specifies the number of ticks (1/50th of a second) that the FLP driver waits after starting the drive before writing to it. This allows the diskette to get up to speed before the write operation. The default value is 24, which is a wait of about 0.5 s. There should not be any reason to use this command.

FLP_STEP

The FLP_STEP (drive, step) command specifies the step rate for a particular drive. If the drive number is omitted, the step rate applies to both drives. The step rate will be adjusted downwards by the driver if there are repeated seek errors. The FLP_STEP command should not, therefore, be necessary.

Sampled Sound System

The SMSQ/E sampled sound system for the Q40 assumes that a sampling rate of 20 kHz will always be used.

The system is based on a 2 byte wide queue. Sound generators should stuff pairs of bytes (left, right) in the queue. The queue is 200 kilobytes long which allows up to 5 seconds free running. A normal "boing" can be set up in a single operation.

The SMSQ/E sampled sound system provides four basic functions to add a single sample, to add an arbitrary number of samples, to stop the sound and to estimate the length of sound samples remaining in the queue.

The SMSQ / E sampled sound system should be accessed in supervisor mode (in principle, this will be a sound device driver) via the interrupt level 4 auto vector.

```

        move.l $70,a3          interrupt level 4 auto vector
        move.l -(a3),a2       address of sample sound system functions
        cmp.l  #'SSSS',-(a3)  SMSQ/E Sampled Sound System
        bne.s  oops

...     jsr    $04(a2)        add a sample
...     jsr    $08(a2)        set up to add multiple samples
...     jsr    $0C(a2)        notify that multiple samples have been added
...     jsr    $10(a2)        kill the sound

```

SSS_ADD 1 (\$04)

The sss_add1 call is used to add one sample to the sound queue. To limit the overheads, it does not save any registers.

```

D1     call byte    left hand sound level
D2     call byte    right hand sound level
A1     smashed
A3     call         pointer to 'SSSS' flag (see code above)

```

The sound level is a byte value between 0 and 255. The sound "zero" level is 128. This should be the last value written to the left and right hand sound queues.

This call does not have a standard error return. It returns status Z if the operation sample has not been added because the queue is full.

SSS_SETM (\$08)

The sss_setm call sets up to add multiple samples to the sound queue.

```

A1     return      the pointer to the next free byte pair in the queue
A2     return      the pointer past the last free byte pair in the queue
A3     call        pointer to 'SSSS' flag (see code above)

```

The calling routine can fill the area from a1 to a2 with pairs of bytes. It does not, however, need to fill the whole of the area. When it has put samples into the queue, it should call SSS_ADDDM to notify the sampled sound system.

SSS_ADDDM (\$0C)

The sss_adddm call notifies that samples have been added to the sound queue.

```

A1     call        the updated pointer to the next free byte pair in the queue
A3     call        pointer to 'SSSS' flag (see code above)

        move.l $70,a3          interrupt level 4 auto vector
        move.l -(a3),a2       address of sample sound system functions
        cmp.l  #'SSSS',-(a3)  SMSQ/E Sampled Sound System
        bne.s  oops

        jsr    sss_setm(a2)    setup
        bra.s  end_loop

loop
        calculate next sample in d1.b, d2.b
        move.b d1,(a1)+        add left sample
        move.b d2,(a1)+        add right sample

```

```

end_loop
  cmp.l  a2,a1          more samples to do?
  blt.s  loop
      jsr   sss_addm(a2)  notify sampled sound system

```

SSS_KILL (\$10)

The sss_kill call stops the sound system and throws the queue away.

```

A3    call             pointer to 'SSSS' flag (see code above)

```

SSS_SAMPLE (\$14)

The sss_sample call estimates the number of samples remaining in the queue. This figure should be divided by 400 to give the length of the sound in ticks or divided by 20000 to give the length of sound in seconds.

```

D0    return long     number of samples remaining in queue
A3    call             pointer to 'SSSS' flag (see code above)

```

SMSQ/E For QPC2

Mouse

QPC supports the mouse wheel transparently to the applications. For every tick of the mouse wheel several Alt + up/down key combinations are stuffed into the keyboard buffer. The amount depends on the global Windows setting. As Alt + up/down are the standard key-combination for scrolling a window, many applications can immediately profit from the wheel.

MOUSE_SPEED

MOUSE_SPEED [#ch,] acceleration, wakeup

This function adjusts the mouse acceleration and wake up factor. The acceleration factor is of no consequence to QPC2. The wakeup values, however, may still be set. They range from 1 to 9, with 1 being the most sensitive.

MOUSE_STUFF

MOUSE_STUFF [#ch,] hot\$

This function adjusts the string that is stuffed into the keyboard queue when the middle mouse button is pressed (or both left and right buttons are pressed simultaneously). The string cannot be longer than two characters, but this is enough to trigger any hotkey, which in turn, can do almost anything.

MOUSE_STUFF ‘.’

Generates a dot if middle mouse button is pressed

MOUSE_STUFF CHR\$(255)&.’

Generates hotkey Alt + .

Machine Type

There are two standard functions to determine the machine type

MACHINE

mach% = MACHINE

Returns the machine type SMSQ/E is running on; 30 for QPC.

PROCESSOR

proc% = PROCESSOR

Returns the 680x0 family type; 20 for QPC (10 for versions below 3.33).

IF MACHINE=30 AND PROCESSOR<>20:PRINT 'This can hardly be QPC!'

QPC-Specific Commands

QPC_CMDLINE\$

cmd\$ = QPC_CMDLINE\$

This returns the argument that was supplied to QPC after the “-cmdline” command line argument. This can be used to do different actions depending on the way QPC was started.

QPC_EXEC

QPC_EXEC command\$, parameter\$]

This command can be used to call an external DOS or Windows program. The name of the executable file is given in the first parameter. Optionally, you can also supply a second parameter, which is then passed to the executed program as its command line arguments.

Furthermore, you can supply a data file as the first parameter. In this case, the associated application for this file type is executed.

QPC_EXEC 'notepad','c:\text.txt' *Start notepad and load the c:\text file*
QPC_EXEC 'c:\text.txt' *Start the default viewer for .txt files*

QPC_EXIT

QPC_EXIT

This simply quits QPC.

QPC_HOSTOS

os% = QPC_HOSTOS

This function returns the host operating system under which QPC was started. Possible return codes are:
0 = DOS (QPC1) 1 = Win9x/ME (QPC2) 2 = WinNT/2000/XP (QPC2)

QPC_MAXIMIZE QPC_MINIMIZE QPC_RESTORE

QPC_MAXIMIZE, QPC_MINIMIZE, QPC_RESTORE

Maximizes, minimizes or restores the QPC window.

QPC_MSPEED

QPC_MSPEED x_accel, y_accel

This command has no effect on QPC2.

QPC_NETNAME\$

name\$ = QPC_NETNAME\$

This function returns the current network name of your PC (the one you supplied upon installation of Windows). The result can be used to distinguish between different PCs (e.g. in a BOOT program).

QPC_QLSCREMU

QPC_QLSCREMU value

Enables or disables the original QL screen emulation. When emulating the original screen, all memory write accesses to the area \$20000-\$27FFF are intercepted and translated into writes to the first 512x256 pixels of the big screen area. If the screen is in high colour mode, additional colour conversion is done.

Possible values are:

- 1: automatic mode
- 0: disabled (default)
- 4: force to 4-colour mode
- 8: force to 8-colour mode

When in QL colour mode, the emulation just transfers the written bytes to the larger screen memory, i.e. when the big mode is in 4-colour mode, the original screen area is also treated as 4-colour mode. In high colour mode however, the colour conversion can do both modes. In this case, you can pre-select the emulated mode (parameter = 4 or 8) or let the last issued MODE call decide (automatic mode). Please note that that automatic mode does not work on a per-job basis, so any job that issues a MODE command changes the behaviour globally.

Please also note that this transition is one-way only, i.e. bytes written legally to the first 512x256 pixels are not transferred back to the original QL screen (in the case of a high colour screens this would hardly be

possible anyway). Unfortunately, this also means that not all old programs will run perfectly with this type of emulation. If you experience problems, start the misbehaving application in 512x256 mode.

QPC_SYNCSCRAP

QPC_SYNCSCRAP

In order to rapidly exchange text passages between Windows and SMSQ/E the Syncscrap functionality has been introduced. The equivalent of the Windows clipboard is the scrap extension of the menu extensions. After loading the menu extensions you can call this command, which creates a job that periodically checks for changes in either the scrap or the Windows clipboard, and synchronizes their contents if necessary. Please note that only text data is supported. The character conversion between the QL character set and the Windows ANSI set is done automatically. The line terminators (LF or LF+CR) are converted too.

QPC_VER\$

v\$ = QPC_VER\$

This returns the current QPC version.

PRINT QPC_VER\$ *will print 4.00 or higher.*

QPC_WINDOWSIZE

QPC_WINDOWSIZE x, y

This sets the size of the client area (the part that displays SMSQ/E) of the QPC window. It does NOT alter the resolution SMSQ/E runs with, so the pixels are effectively zoomed. It is equivalent to the "window size" option in the main configuration window. If QPC is currently in full screen mode it will switch to windowed mode. Window size cannot be set smaller than the SMSQ/E resolution or bigger than the desktop resolution.

DISP_SIZE 512,256 *set QPC to 512x256 screen resolution*
QPC_WINDOWSIZE 1024,512 *do a 200% zoom of the QPC window*

QPC_WINDOWTITLE

QPC_WINDOWTITLE title\$

Sets the string that can be seen when QPC runs in windowed mode. This can be used to easily distinguish between several QPC instances.

QPC_WINDOWTITLE "Accounting" *sets the title to "Accounting"*

Serial (COM) Ports

Unlike the basic SMSQ serial port drivers, the SMSQ/E serial port drivers are dynamically buffered. There is therefore no need to use the PRT device.

BAUD

The Baud rates supported by SMSQ/E on QPC are

115200
57600
38400
19200
9600
4800
2400
1200
600
300

The BAUD command works as in SMSQ/E on the Atari: If the port number is omitted, only SER1 is affected:

BAUD 19200 *set SER1 to 19200 baud*
BAUD 3,115200 *set SER3 to 115200 baud*

SER_GETPORT\$

com\$ = SER_GETPORT\$(port%)

Returns the device the SER port is connected to, for example "COM1".

SER_SETPORT

SER_SETPORT port%, com\$

Sets the COM port a SER port should be connected with. The change will take effect on the next open of the specified serial port.

SER_SETPORT 4,"COM32" Associate SER4 with COM32

Printer Support (PAR)

The PAR device can be linked to a printer port or to a Windows printer queue. By default, output is dynamically buffered: the PRT device is not required.

Please note that no translation of the printer data is done, the data sent to the device is directly piped into the printer itself. The only exception is the "filter" option in the configuration dialog. A filter gets the raw data and can process it however it wants. QPCPrint, which is sold separately, is just such a filter that emulates the popular ESC P/2 printer language.

PAR_DEFAULTPRINTER\$

name\$ = PAR_DEFAULTPRINTER\$

This returns the name of Windows' default printer. The name can later be used with PAR_SETPRINTER for example.

PAR_GETPRINTER\$

name\$ = PAR_GETPRINTER\$(port%)

This returns the PAR port setting: "LPT1", "LPT2" or "LPT3" if it isn't linked to a printer but directly to a printer port or the name of the printer otherwise. An empty string designates the default printer.

PAR_SETPRINTER

PAR_SETPRINTER port%, name\$

Connects the PAR port either to a hardware port (e.g. name\$ is "LPT1") or to the printer spooler (name\$ is one of the names returned by PAR_PRINTERNAME\$).

PAR_GETFILTER

state% = PAR_GETFILTER(port%)

This returns whether the printer filter is enabled for the specified port.

PAR_SETFILTER

PAR_SETFILTER port%, state%

Enables (state% = 1) or disables (state% = 0) the printer filter for the specified port. If the printer should be enabled although none is available a "not found" error is returned.

PAR_PRINTERCOUNT

n% = PAR_PRINTERCOUNT

This returns the number of printers available on this system.

PAR_PRINTERNAME\$

name\$ = PAR_PRINTERNAME\$(n)

This returns the name of printer number n (counted from 1 to PAR_PRINTERCOUNT).

PC Floppy Disks

QPC2 supports both native floppy access and access to floppy images.

Native Floppy Support

Access to native PC floppy disks is done via low-level Windows calls. Read accesses are buffered internally by QPC2 and should be quite fast. This is not true for write accesses; depending on your Windows version, these might be quite slow. As of version 4 QPC does not physically format floppy disks anymore. The disk must already have been formatted by Windows or any other means. Formatting the disk in QPC only writes the SMSQ/E file system to it.

Floppy Image Support

QPC2 can accept any standard floppy disk image. You can create your own images by formatting an image and filling it with contents:

FLP_DRIVE 2,"C:\TEMP\FLOPPY.IMG"	<i>change location of image file</i>
FORMAT FLP2_	<i>format HD floppy image</i>
WCOPY FLP1_,FLP2_	<i>copy contents from physical floppy</i>

Floppy Disk Driver Name

The default name of the floppy disk driver is FLP.

FLP Control Commands

FLP_USE

FLP_USE may be used to set the name of the FLP device. The name should be three characters long, in upper or lower case.

FLP_USE mdv	<i>The FLP device is renamed MDV</i>
FLP_USE FLP	<i>The FLP device is restored to FLP</i>
FLP_USE	<i>The FLP device is restored to FLP</i>

FLP_DRIVE

FLP_DRIVE drive%, drive\$

This changes the drive/image the floppy device is connected to.

FLP_DRIVE 2,"C:\FLOPPY.IMG"	<i>now FLP2_ is assigned to the floppy image FLOPPY.IMG</i>
FLP_DRIVE 2,"B:\"	<i>now FLP2_ is assigned to the physical B:\ floppy</i>

FLP_DRIVES\$

drive\$ = FLP_DRIVE\$(drive%)

This reads back the current connection of the floppy device.

PRINT FLP_DRIVE\$(2) *will tell you the current setting*

FLP_DENSITY

FLP_DENSITY code

The SMSQ/E format routines will usually attempt to format a disk to the highest density the medium supports. The FLP_DENSITY (code) is used to specify a particular density during format. The density codes are "S" for single sided (double density), "D" for double density and "H" for high density.

FLP_DENSITY S *Set the default format to single sided*
FLP_DENSITY H *Set the default format to high density*
FLP_DENSITY *Reset to automatic density selection*

The same code letters may be added (after a *) to the end of the medium name to force a particular density format. (For compatibility with older drivers, if the code letter is omitted after the *, single sided format is assumed).

FORMAT 'FLP1_Disk23' *Format at highest density or as specified by FLP_DENSITY*
FORMAT 'FLP1_Disk24*' *Format single sided*
FORMAT 'FLP1_Disk25*S' *Format single sided*
FORMAT 'FLP1_Disk25*D' *Format double sided, double density*

FLP_SEC, FLP_START and FLP_STEP

QPC has no influence over how the Windows disk driver works, therefore these commands are ignored.

WIN Disks

SMSQ hard disks for QPC are just large files on the host operating system's file system. The files usually have the suffix ". WIN" but anything else is fine, too. Name and directory can be configured separately for all drives. (See also the configuration section). SMSQ/E's FORMAT command creates the file.

Hard Disk Driver Name

The default name of the hard disk driver is WIN.

WIN_USE

WIN_USE may be used to set the name of the WIN device. The name should be three characters long, in upper or lower case.

WIN_USE mdv *The WIN device is renamed MDV*
WIN_USE WIN *The WIN device is restored to WIN*
WIN_USE *The WIN device is restored to WIN*

Format WIN

Formatting a WIN drive simply creates a large file on the PC's hard disk. The "name" of the WIN device should be the size required in megabytes.

Before you issue the FORMAT command, you have to allow the drive to be formatted. SMSQ/E has a two-level protection scheme to make sure you (or somebody else) cannot format your hard disk accidentally. All drives are protected by default so you have to enable them to be formatted first.

Please note that the FORMAT command for a WIN drive should only be used from the console of job 0, i.e. the first SBASIC.

FORMAT will fail if there is not sufficient space left on the specified drive, if the medium is write-protected, or if the file *.WIN already exists and contains invalid information (e.g. a DOS-subdirectory).

WIN_FORMAT 1 *Allow WIN1_ to be formatted*
FORMAT WIN1_10 *Create a 10 Megabyte WIN device.*

... You have to echo the two characters displayed...

WIN_FORMAT 1,0 *protect WIN1_ again against unwanted formatting*

Drive/Filename Assignment

WIN_DRIVE WINDRIVE\$

Every WIN drive number is assigned to a file on your hard disk, which contains the complete contents of your WINx_. It is possible to change the filename of the file that is assigned to a WIN drive number while QPC2 is running:

WIN_DRIVE 2,"D:\QPC.WIN" *now WIN2_ is assigned to the WIN file QPC.WIN*
PRINT WIN_DRIVE\$(2) *will tell you the current filename.*

Removable Drives

WIN_REMV

Removable drives, such as ZIP or SyQuest, are now supported. If auto-detection fails use the WIN_REMV command:

WIN_REMV 2 *declares WIN2_ to be a removable drive.*
WIN_REMV 2,1 *does the same for WIN2_.*
WIN_REMV 2,0 *magic - WIN2_ is no longer removable!*

When a drive is declared removable, the .WIN file is closed after all SMSQ/E files on it are closed. This can also be used to allow a single .WIN file to be shared over a network. (Files on a remote computer **QPC2** are automatically set to be removable). As long as one instance of QPC has open files on the drive, no other instance can access it.

The DOS Device

The DOS device has been created to transfer data between the Windows and SMSQ/E environments. Using this device you can directly browse your PC hard disks (network drives, CD-ROMs or whatever), as well as read and write files.

Please note that the DOS device is NO replacement for the WIN device (it was never intended to be), all SMSQ header information gets lost on DOS drives; therefore, you cannot store executable code on them.

Drive/Directory Assignment

By default, DOS1_ corresponds to C:\, DOS2_ to D:\ and so on, but the base can be freely chosen in the configuration dialog or even at runtime:

DOS_DRIVE 2,"C:\WINDOWS" *assign DOS2_ to the windows directory*
PRINT DOS_DRIVE\$(2) *would now return "C:\WINDOWS"*

Restrictions And Some Background Information On The DOS Device

You can use this device in the same way as any other QL directory device to access and exchange files between Windows and SMSQ/E. It is easier than ever before. The usual restrictions imposed by the general QDOS file naming convention apply, i.e. the length of the directory + filename is limited to 36 characters. Names longer than that won't show up in the directory lists! Therefore, it is a good idea to place files that you want to access from both SMSQ/E and Windows only one or two directory levels deep, or change the base of a DOS drive to one directly above the desired directories.

Many filenames that are valid under SMSQ are not valid under Windows. The offending characters (e.g. *, /, ? etc. or filenames with spaces at their end) are translated into other, valid ANSI characters. This conversion works quite well, but you are advised to only use valid filenames wherever possible.

One problem with the SMSQ way of accessing files is that the “_” separator can be a valid part of a name or a directory separator. Therefore, the relation SMSQ filename -> Windows filename is ambiguous. This can cause quite some problems:

Let’s say you have two directories named C:\QL\STUFF\ and C:\QL\STUFF_NEW\ and you want to create a file called dos1_QL_STUFF_NEW_BRANDNEW.TXT. Where does that file belong? It could mean any of the following:

```
C:\QL_STUFF_NEW_BRANDNEW.TXT
C:\QL\STUFF_NEW_BRANDNEW.TXT
C:\QL\STUFF\NEW_BRANDNEW.TXT
C:\QL\STUFF_NEW\BRANDNEW.TXT
```

Your intention was probably the last one, but how should QPC now? The easy solution is not to use underscores in directory names. However, if you can’t help it, it becomes essential to know how the DOS device works. The current algorithm is based on the simple assumption that if you have a directory called “QL_STUFF” you won’t also want to create “QL\STUFF”.

The exact working of the algorithm is not easy to describe, but I’ll try nonetheless. The basic principle is that the algorithm always searches for the longest consecutive part of the name. In the example above, QPC would begin by searching for any directory starting with “C:\QL”. If none was found, the process completes and the result is simply “C:\QL_STUFF_NEW_BRANDNEW.TXT”. Otherwise, it will look for any directory starting with “C:\QL_STUFF”. If found QPC will try “C:\QL_STUFF_NEW” and so on. If not found, however, it will test whether the last successful part (“C:\QL_STUFF”) is itself a directory. If it is, it is considered part of the filename and all future searches use this as the base (i.e. the next step would be “C:\QL_STUFF\NEW”). If not, the search terminates with the result again being “C:\QL_STUFF_NEW_BRANDNEW.TXT”. If this sounds too confusing or too badly explained (probably both) just remember one thing: never use “_” within directory names.

Finally, please note that you cannot use RENAME to rename files on a DOS drive. SMSQ/E allows you to rename files from one directory to another one, but this is not compatible with the DOS way of doing things. If you want to rename a file, you need to COPY it to the new location and DELETE the old file.

DOS Control Commands

DOS_USE

DOS_USE may be used to set the name of the DOS device. The name should be three characters long, in upper or lower case.

DOS_USE mdv	<i>The DOS device is renamed MDV</i>
DOS_USE DOS	<i>The DOS device is restored to DOS</i>
DOS_USE	<i>The DOS device is restored to DOS</i>

DOS_DRIVE

DOS_DRIVE drive%, directory\$

This changes the directory the DOS device is connected to.

DOS_DRIVE 2,"C:\WINDOWS" *now DOS2_ points to C:\WINDOWS*

DOS_DRIVE\$

directory\$ = DOS_DRIVE\$(drive%)

This reads back the currently connected directory of the DOS device.

The QPC CD-Audio Module

As a little extra bonus, QPC contains a module to play Audio CDs. There are 23 new BASIC commands for the complete control of all audio functions of a CD-ROM drive. A tiny CD-player comes with QPC2 as an example.

First some terms of CD programming:

Track: one title Frame: one sector of a CD. The sector length on Audio CDs is 2352 Bytes

REDBOOK-Format: a standard format for direct sector addressing. Sectors are addressed through a time index in the form of a longword formatted as \$00MMSSFF. MM is the minute, SS the second and FF is the frame. One second has $44100(\text{Hz}) * 2(\text{Stereo}) * 2(16 \text{ Bit}) / 2352$ (sector length) = 75 frames.

HSG-Format: another format to address a sector. Here they are only addressed sequentially.

$\text{HSG} = (\text{minute} * 60 + \text{second}) * 75 + \text{frame}$

New Basic Commands

As usual, all parameters in square brackets are optional. Unless specified, all sectors are addressed in Redbook-Format.

CD_INIT

CD_INIT ['name']

This command must be used before any other in order to initialize the CD drive for SMSQ. After the first call, the command is ignored on all subsequent calls. The string parameter is ignored on QPC2.

CD_PLAY

CD_PLAY [start[,end]]

This is the most important command. Without parameters the whole CD is played. An optional start and end track can be given. The command returns as soon as the CD starts playing. The parameters are given in tracks (bit 31 clear) or in sector units (bit 31 set).

CD_PLAY 3 *or with the same effect*
CD_PLAY CD_TRACKSTART(3) + \$80000000

CD_STOP

Pauses playing. If the driver was already in pause mode, a complete stop is performed (as if a new CD was inserted; restart from track 1 and so on)

CD_RESUME

Resumes playing from where it stopped.

CD_EJECT, CD_CLOSE

Opens/closes the drive tray.

CD_ISPLAYING, CD_ISCLOSED, CD_ISINSERTED, CD_ISPAUSED

x% = CD_xxx

These functions return the current status according to the keyword. Please note that Windows cannot tell whether the tray is closed or not, therefore CD_ISCLOSED always returns the same result as CD_ISINSERTED when used on QPC2. An empty tray was obviously something the Microsoft geniuses could not imagine.

CD_TRACK

track% = CD_TRACK

Returns the number of the track currently being played.

CD_TRACKTIME

x = CD_TRACKTIME

Returns the elapsed time within the current track.

CD_ALLTIME

x = CD_ALLTIME

Returns the total elapsed time of the CD.

CD_HSG2RED, CD_RED2HSG

red=CD_HSG2RED hsg hsg=CD_RED2HSG red

Converts an HSG address to Redbook and vice versa.

CD_TRACKSTART

x = CD_TRACKSTART track

Returns the start sector of a track.

CD_TRACKLENGTH

x = CD_TRACKLENGTH track

Returns the length of a track. **Attention:** This is the only function that returns an HSG-number.

CD_FIRSTTRACK, CD_LASTTRACK

x% = CD_xxx

Returns the number of the first/last track.

CD_LENGTH

x = CD_LENGTH

Returns the total length of the CD.

CD_HOUR, CD_MINUTE, CD_SECOND

x% = CD_xxx Redbook

Returns the hour, minute or second of a Redbook address

SMSQ/E Manual Revision History

- 1.00 First release version. [02/04/14]
- 1.01 Indexes and headings changed at suggestion of Marcel Kilgus to use Word Table of Contents and Index systems to make it easier to update the content. [08/04/14]
- 1.02 Long list of typos corrected (thank you, Dave Westbury). New sections added on CTRL-C behaviour and Execution Delay Times (sys_xdly) [28/04/14]
- 1.03 Some minor typos and layout issues fixed. FEX_M keyword added. HTML version created for online use. [09/02/16]
- 1.04 Added documentation for ALPHA_BLEND, Recent Thing and SMSQ/E for Aurora.

Index

\$ Hex Values	17	COLOUR_NATIVE.....	50
\$nnn	14	COLOUR_PAL.....	50
% and \$	69	COLOUR_QL.....	50
% Binary Values	17	COLOUR_xx.....	14
%nnn	14	Colours List.....	51
ABC keyboard	88	Common keyboard driver.....	56
ACSI and SCSI Drives on ST/TT.....	76	Configuration.....	80, 86, 88, 92
ALPHA_BLEND.....	50	Cursor Extensions.....	55
ALT ENTER.....	70	CURSPRLOAD	14, 55
ALTKEY.....	70	CURSPROFF.....	14, 55
Archive Runtimes	69	CURSPRON	14, 55
ATAN.....	14, 25	DATA_USE	63
Atari ST and TT	72	DATEs in Archive/Abacus.....	69
Atari ST and TT Hard Disks.....	76	DAY%	14, 25
Atari ST Printer Port	76	DEV	14, 62, 63
ATARI_rext.....	70	DEV_LIST	14, 62
ATARIDOS_rext.....	70	DEV_NEXT	14, 63
ATR_rext	70	DEV_rext.....	70
Aurora.....	2, 89	DEV_USE	14, 62, 63
Background drawing.....	55	DEV_USE\$.....	14
BAUD	14, 58, 82, 91, 104	DEV_USEN.....	14, 63
BAUDRATE%.....	87	DEVTYPE	15, 21
BGCOLOUR_24.....	48	Directory Devices.....	63
BGCOLOUR_QL.....	48	DISP_BLANK.....	45, 74, 94
BGCOLOUR_xx.....	14	DISP_COLOUR	46
BGET.....	14, 24	DISP_INVERSE.....	46, 73, 94
BGIMAGE.....	14, 49	DISP_RATE	46, 74, 94
BLS.....	87	DISP_SIZE.....	47, 74, 90, 94
BPUT.....	14, 24	DISP_SIZE Experimenter	74
C programs on QXL.....	70	DISP_TYPE	47, 73, 81, 89, 90, 94
CACHE_OFF.....	14, 16	DISP_xxx.....	15, 45
CACHE_ON	14, 16	DMEDIUM_DENSITY	29
CD_ALLTIME	111	DMEDIUM_DRIVE\$.....	29
CD_CLOSE	110	DMEDIUM_FORMAT.....	29
CD_EJECT.....	110	DMEDIUM_FREE	29
CD_FIRSTTRACK.....	111	DMEDIUM_NAME\$	29
CD_HOUR.....	111	DMEDIUM_RDONLY.....	29
CD_HSG2RED.....	111	DMEDIUM_REMOVE	29
CD_INIT	110	DMEDIUM_TOTAL	29
CD_ISCLOSED.....	110	DMEDIUM_TYPE	29
CD_ISINSERTED.....	110	DMEDIUM_xxx	15, 29
CD_ISPAUSED.....	110	DOS Device	108
CD_ISPLAYING.....	110	DOS disks.....	63, 68
CD_LASTTRACK.....	111	DOS_DRIVE	109
CD_LENGTH.....	111	DOS_DRIVE\$.....	109
CD_MINUTE	111	DOS_USE.....	109
CD_PLAY	110	DOS_xx.....	15
CD_RED2HSG.....	111	DRVCHK.....	65
CD_RESUME	110	DRVLINK	65
CD_SECOND.....	111	EASYEXT	70
CD_STOP	110	EASYPTR	69
CD_TRACK.....	111	ED.....	15, 27
CD_TRACKLENGTH.....	111	END	18
CD_TRACKSTART	111	END FOR.....	15
CD_TRACKTIME.....	111	END REPeat.....	15
CD_xx.....	14	EOF_W	15
CHAR_DEF	14, 26	EOFW	29
CHAR_USE	27	EPROM_LOAD	15, 22
Colour Commands.....	52	Event Handling.....	64
COLOUR_24	50	EW	15

EX.....	15	LPUT.....	15, 24
EX_M.....	15, 28	LRESPR.....	15
EXEC.....	15	LRUN.....	15, 21
EXEC_W.....	15	MACHINE.....	15, 45, 72, 81, 89, 90, 93, 102
EXF.....	15, 28	Memory Protection.....	72
EXIT.....	15, 18	MENU_rext.....	70
FEP.....	15, 28	MERGE.....	15, 21
FET.....	15, 28	MIDINET_rext.....	70
FEW.....	15, 28	Monochrome Display.....	73
FEX.....	15, 28	MONTH%.....	15, 25
Floppy Image Support.....	106	MOUSE_SPEED.....	15, 94, 102
FLP_DENSITY.....	79, 83, 99, 107	MOUSE_STUFF.....	15, 95, 102
FLP_DRIVE.....	106	MRUN.....	15, 21
FLP_DRIVES\$.....	106	NEXT.....	15, 18
FLP_SEC.....	79, 83, 91, 99, 107	NUL.....	15
FLP_START.....	79, 83, 91, 99, 107	NUL Device.....	60
FLP_STEP.....	80, 84, 91, 99, 107	OUTLN.....	15, 27
FLP_TRACK.....	79, 83, 99	PALETTE_8.....	49
FLP_USE.....	79, 83, 91, 98, 106	PALETTE_QL.....	49
FLP_xxx.....	15	PALETTE_xx.....	15
FOR.....	15, 18	PAR.....	15, 91
Format WIN.....	107	PAR_ABORT.....	59
GD2.....	48	PAR_BUFF.....	59
Gold Card.....	81	PAR_CLEAR.....	59
GOLD Card Display.....	81, 89	PAR_DEFAULTPRINTER\$.....	105
Gold Card Microdrives.....	84	PAR_GETFILTER.....	105
Hermes.....	85	PAR_GETPRINTER\$.....	105
HGET.....	15, 25	PAR_PRINTERCOUNT.....	106
HISTORY.....	15	PAR_PRINTERNAME\$.....	106
HISTORY Device.....	61	PAR_PULSE.....	96
Home Thing, The.....	36	PAR_SETFILTER.....	105
HOME_CSET.....	37	PAR_SETPRINTER.....	105
HOME_CURR\$.....	36	PAR_USE.....	59
HOME_DEF.....	36	PAR_WAIT.....	96
HOME_DIR\$.....	36	PAR_xx.....	15
HOME_FILE\$.....	36	Parallel Port Control.....	59
HOME_SET.....	37	PC Floppy Disks.....	91, 106
HOME_VER\$.....	37	PC Hard Disks.....	91
HOME_xxx.....	15, 36	PE_BGOFF.....	15, 55
HOT_GETSTUFF\$.....	15, 27	PE_BGON.....	15, 55
HOT_GO.....	70	PEEK.....	15, 23
HOT_rext.....	70	PEEK\$.....	15, 23
HPUT.....	15, 25	PEEK_F.....	23
HSG-Format.....	110	PEEK_L.....	23
IF 15, 17		PEEK_W.....	23
In-Line Loops.....	18	PEEK\$.....	15, 73, 93
Input Line Editing.....	33	PEEKSS\$.....	73, 93
INSTR.....	26	PEEK\$_F.....	73, 93
INSTR_CASE.....	15, 26	PEEK\$_L.....	73, 93
IO_PRIORITY.....	15, 16	PEEK\$_W.....	73, 93
JMON.....	68, 70	PIPE.....	15
JOB_NAME.....	15, 31	PIPE Device.....	60
JOBID.....	15, 28	Pointer Tools.....	70
KBD_TABLE.....	15, 35	POKE.....	15, 23
LANG_USE.....	15, 34	POKE\$.....	15, 23
LANGUAGE.....	15, 35	POKE_F.....	23
LANGUAGE LANGUAGES\$.....	35	POKE_L.....	23
LANGUAGES\$.....	15	POKE_W.....	23
LBYTES.....	15, 22	POKES.....	15, 73, 93
LGET.....	15, 24	POKES\$.....	73, 93
LIGHTNING.....	70	POKES_F.....	73, 93
LOAD.....	15, 21	POKES_L.....	73, 93
Loading SMSQ/E.....	81, 90	POKES_W.....	73, 93

PRINT_USING	15, 30	RCNT_GARJ	39, 42, 43
PROCESSOR	15, 45, 72, 81, 89, 90, 93, 102	RCNT_GARR.....	39, 41, 42
PROG_USE	63	RCNT_GFFA\$	39, 41
PROT_DATE	15, 25	RCNT_GFFJ\$	39, 41
PROT_MEM	15, 72, 93	RCNT_HASH\$	39, 43
PRT	15	RCNT_INFO	39, 41, 42, 43
PRT_USE	15, 59	RCNT_JOBS	39, 40
PTR_GEN	70	RCNT_LOAD	39, 43
PTRMENR_cde	70	RCNT_REMV	39, 44
Q40 Display	93	RCNT_SAVE	39, 43, 44
Q40 Floppy Disks	98	RCNT_SYNC	39, 44
Q40 Hard Disks	96	Recent Thing, The	37
Q40 Mouse driver	94	REDBOOK-Format	110
Q40 Parallel Printer Ports	95	REPeat.....	15, 19
Q40 Serial Ports	95	RESET	16, 22
Q40 Sound	99	Sampled Sound System.....	99
Q40/Q60.....	93	SAVE	16, 21
QBASIC_rext	70	SAVE_O.....	16, 21
QD	70	SBAS/QD F10 Thing.....	68
QLIB_bin	70	SBASIC.....	16, 31, 68
QLIB_ext	71	SBYTES	16, 22
QLIB_run	71	SBYTES_O	16, 22
QLiberators EXTERNals.....	70	SCR_BASE.....	16, 24
QLOAD.....	15, 21, 70	SCR_LLEN	16, 24
QLOADREF_bin.....	71	SCR_XLIM.....	16, 24
QLRUN.....	15, 21	SCR_YLIM.....	16, 24
QMERGE	15, 21	SDUMP	71
QMON	68, 71	SElect	16, 17
QMRUN.....	15, 21	SEND_EVENT	16, 65, 67
QPAC2	71	SER	16
QPC CD-Audio Module	110	SER Mouse.....	84
QPC_CMDLINE\$.....	102	SER_ABORT	59
QPC_EXEC	102	SER_BUFF	58
QPC_EXIT.....	103	SER_CDEOF	59
QPC_HOSTOS.....	103	SER_CLEAR.....	59
QPC_MAXIMIZE	103	SER_FLOW	58
QPC_MINIMIZE.....	103	SER_GETPORT\$	105
QPC_MSPEED.....	103	SER_PAUSE	82
QPC_NETNAME\$	103	SER_ROOM	58
QPC_QLSCREMU	103	SER_SETPORT	105
QPC_RESTORE	103	SER_USE	59
QPC_SYNCSCRAP	104	SER_xx.....	16
QPC_VER\$	104	Serial (RS232) on ST/TT.....	75
QPC_WINDOWSIZE	104	SERIAL IO Devices.....	57
QPC_WINDOWTITLE	104	Serial Port Control.....	58
QPC_xx.....	15	SERMAWS	87
QPC2.....	102	SERMCUR.....	87
QPC2 Mouse.....	102	SERMOFF	87
QPC2 Printer Support (PAR).....	105	SERMON	87
QPC2 Serial (COM) Ports	104	SerMouse Cable Connector.....	85
QPC2 WIN Disks.....	107	SERMPTR	87
QPTR	71	SERMRESET.....	87
QREF	69	SERMSPPEED	87
QSAVE	15, 21	SERMWAIT.....	88
QSAVE_O	15, 21	SERNET Batchfile Execution.....	67
QTYP_SPELL	71	SERNET V3.....	65
QUIT.....	15, 33	SERNET via Modem.....	66
QXL	90	SEXEC.....	16, 22
QXL Display	90	SEXEC_O.....	16, 22
QXL.WIN	107	SLUG	16, 17
RCNT_ADDF.....	39, 40	SMSQ/E Troubleshooting	68
RCNT_GALJ	39, 40, 41	SNET_xx.....	16
RCNT_GALL	39, 40, 41, 42	SP_GET	53

SP_GETCOUNT.....	53	WIN_START	78, 98
SP_JOBOWNPAL	54	WIN_STOP	78, 98
SP_JOBPAL	54	WIN_USE.....	77, 92, 97, 107
SP_RESET	53	WIN_WP	78, 98
SP_SET	53	WIN_xxx.....	16
SP_xx.....	16	Window Manager 2	51
SPEEDSCREEN	71	Window Move	54
SRX	16	WINDRIVE\$	108
STX	16, 82	WM_BLOCK	53
Super Gold Card.....	81	WM_BORDER	53
Super Gold Card Printer Port	82	WM_INK.....	52
Sysmon	69	WM_MOVEALPHA	16
SYSSPRLOAD	16, 56	WM_MOVEMODE	16, 54
System Palette	51	WM_PAPER	52
THING_rext	71	WM_STRIP.....	52
TRA	16, 35, 70	WM_xxx	16, 52
TRA_rext	71	WMAN.....	71
UPUT.....	16, 25	WMON	16, 31
VER\$.....	16, 26	WPUT	16, 24
Virtual Devices.....	60	WTV	16, 31
WAIT_EVENT.....	16, 64	xNET_BAD%	66
Wallpaper	48	xNET_RETRIES%	66
WEEKDAY%	16, 25	xNET_START	66
WGET.....	16, 24	xNET_STATION	66
WHEN ERROR.....	16, 18	xNET_STATION%	66
WIN_DRIVE	77, 97, 108	xNET_STOP	66
WIN_DRIVE\$	77, 97	xNET_TEST%.....	66
WIN_FORMAT	78, 92, 97	XON XOFF.....	82
WIN_REMV	78, 108	YEAR%.....	16, 25
WIN_SLUG.....	77		